RECOMP II USER'S PROGRAM NO. 1107

PROGRAM TITLE:

CALCULATION OF PI (DEMONSTRATION)

PROGRAM CLASSIFICATION:

Demonstration

AUTHOR:

W. Wellman

Servomechanisms, Inc. Research Division Goleta, California

PURPOSE:

For demonstration, this program calculates

the value of m from Pierce's algorithm

DATE:

9 December 1961

Published by

RECOMP User's Library

at

AUTONETICS INDUSTRIAL PRODUCTS
A DIVISION OF NORTH AMERICAN AVIATION, INC.
3400 E. 70th Street, Long Beach 5, Calif.

DISCLAIMER

Although it is assumed that all the precautions have been taken to check out this program thoroughly, no responsibility is taken by the originator of this program for any erroneous results, misconceptions, or misrepresentations that may appear in this program. Furthermore, no responsibility is taken by Autonetics Industrial Products for the correct reproductions of this program. No warranty, express or implied, is extended by the use or application of the program.

Calculation of Pi

Purpose

For demonstration, this program calculates the value of π from Pierce's algorithm:

$$\pi = 3 \times f_0 \times f_1 \times f_2 \times - - - f_m$$

$$f_{\rm m} = 1 + \frac{1}{16m^3 + 60m^2 + 72m + 27}$$

Result is displayed on the console.

Use

To start, press start 3. To stop, use preset stop at 4021.0 If interrupted in mid-program, restart may give wrong result; stop program in 4021.0 and restart. To stop at any m, place that m in 4073 (floating).

Time

| Correct significant figures | 0 | 2 | 3 | 4 | 5 | 6 | 12 |
|-----------------------------|-----|-----|------|------|------|------|------|
| Time, minutes/seconds | 0/3 | 0/4 | 0/14 | 0/33 | 1/34 | 6/46 | 63/0 |

Accuracy

After 12 significant figures, round-off error gradually reduces the number of correct figures to zero. The accuracy of any displayed result is better than 1 part in d, where d is the floating point number in 4054-5 when program is stopped at 4027.0

Location

4000-4100 inclusive, non-relocatable, and 0003.0

File Uniterms

demonstration, pi, round-off, display

Contained Original Subroutines none,