SBC-300 SINGLE BOARD COMPUTER OPERATIONS MANUAL

SD #7140170 REVISION C AUGUST 25, 1983

)



SBC-300 SINGLE BOARD COMPUTER OPERATIONS MANUAL

SD #7140170 REVISION C AUGUST 25, 1983

EMI NOTICE

This equipment has been designed and constructed to professional standards. However, the equipment must be utilized correctly by the user to obtain proper performance and to comply with applicable industry and governmental regulations.

Since the equipment is supplied as an unconfigured component and cannot be tested for electro-magnetic interference (EMI) in all possible configurations, the equipment is not subject to standards imposed by Subpart J of Part 15 of FCC Rules and Regulations.

Final system configuration will require compliance with applicable FCC regulations. SDSystems recommends the installation of shielded data cables for all external cabling. Electro-magnetic interference (EMI) levels are dependent upon final system hardware configuration and application.

Contact SDSystems Customer Service if additional configuration information is required.

TERMINATION NOTE

SDSystems recommends the use of active termination circuitry on the S-100 bus to avoid system problems.

MODIFICATION FOR SBC-300 REVISION & ARTWORK WITH MONITOR ROM 2.0

The Revision A artwork for the SBC-300 is missing pull up resistors on the EPROM for pins 1 and 27. To correctly function with a 2764 EPROM, these pins must be tied to +5V. To accomplish this, wire pins 1 and 27 to pin 28. This will enable the EPROM.

TABLE OF CONTENTS

Subsection Number

Title

Page No.

SECTION I INTRODUCTION

1.0	GENERAL		1-1
1.1	PEATURES	STATISTICS STATISTICS	1-1
1.2	SCOPE		1-1

SECTION II FUNCTIONAL DESCRIPTION

2.0	GENERAL	2-1
2.1	CENTRAL PROCESSING UNIT	2-2
2.1.1	CPU	2-2
2.1.1.1	PROCESSOR OPERATION	2-2
2.1.1.2	Z-80 CPU	2-2
2.1.2	CLOCK RATE GENERATOR	2-3
2.1.3	CPU CLOCK SPEED SELECTION	2-4
2.2	MEMORY	2-5
2.2.1	RAM	2-5
2.2.1.1	REFRESH	2-6
	PIN 1 REFRESH MEMORY DEVICES	2-6
	AVOIDING LONG WAIT STATES	2-6
2.2.1.1.3	REFRESH DURING DMA OPERATIONS	2-7
2.2.1.2	REFRESH WAIT STATE GENERATOR	2-7
2.2.1.2.1	WAIT STATES	2-8
2.2.1.2.2	WAIT STATE SELECTION	2-8
2.2.1.2.3	PIN 1 REFRESH GENERATION	2-9
2.2.1.3	MEMORY TIMING	2-9
2.2.1.3.1	RAM ADDRESS DECODE	2-9
2.2.1.3.2	ROW AND COLUMN TIMING	2-10
2.2.2	ROM	2-10
2.2.3	MEMORY ADDRESS AND I/O PORT DECODE	2-10
2.2.3.1	MEMORY ADDRESS DECODE	2-11
2.2.3.2	I/O PORT DECODE	2-11
2.2.4	PARITY	2-11
2.2.5	MODE DEPENDENT MEMORY CHARACTERISTICS	2-11
2.2.5.1	BUS MASTER MODE MEMORY	2-11
2.2.5.2	SLAVE PROCESSOR MODE MEMORY .	2-12
2.3	MEMORY MAPPER	2-12
2.3.1	MAPPER OPERATION	2-12
2.3.1.1	BOARD ADDRESS SELECT	2-13
2.3.1.2	MAPPER RAM	2-13
2.4	INTERRUPT CONTROLLER	2-14
2.4.1	INTERRUPT SELECT	2-14
2.5	BUS INTERFACE	2-15
2.5.1	BUS TIMING CONTROLLER	2-15
2.5.2	POWER ON CLEAR AND RESET SLAVE CONTROL	2-16
2.6	MASTER/SLAVE CONTROL	2-18
2.6.1	MASTER/SLAVE CONTROL MASTER/SLAVE SELECT	2-18
8 . V . I	PUDIER DEALE DEALECT	2-10

TABLE OF CONTENTS (Continued)

Subsection Number

Title

Page No.

0

SECTION II--Continued FUNCTIONAL DESCRIPTION--Continued

2.6.2	LINE TERMINATION	2-18
2.7	SASI/PARALLEL PORT	2-19
2.7.1	CIO	2-19
2.8	SERIAL I/O	2-19
2.8.1	ASCC	2-20
2.9	POWER REGULATION	2-20
2.9.1	5 VOLT BUS OPERATION	2-20

SECTION III THEORY OF OPERATION

3.0	GENERAL	3-1
3.1	MASTER/SLAVE MODES	3-1
3.1.1	MASTERS	3-1
3.1.1.1	PERMANENT BUS MASTER	3-1
3.1.1.2	TEMPORARY BUS MASTER	3-1
3.1.2	SLAVES	3-2
3.1.2.1	SLAVE PROCESSORS	3-2
3.1.2.2	SLAVE PROCESSORS AND MULTI-USER SYSTEMS	3-2
3.1.3	BUS CYCLE OPERATIONS	3-3
3.1.3.1	BUS CYCLES	3-4
3.1.3.2	TEMPORARY MASTER ACCESS CYCLES	3-4
3.2	SLAVE PRIORITY	3-5
3.3	INTERRUPTS	3-5
3.3.1		3-5
	NON-MASKABLE INTERRUPTS	
3.3.2	MASKABLE INTERRUPTS	3-5
3.3.3	INTERRUPT ENABLE	3-6
3.3.4	INTERRUPT CONTROL	3-6
3.3.4.1	OFF-BOARD INTERRUPT PRIORITIZATION	3-7
3.3.4.2	ON-BOARD INTERRUPT PRIORITIZATION	3-7
3.3.4.3	ON-BOARD INTERRUPT ARBITRATION	3-8
3.3.5	INTERRUPT ACKNOWLEDGE	3-9
3.4	MAPPER CONCEPTS	3-10

SECTION IV OPERATIONS

4.0	GENERAL	4-1
4.1	INSTALLATION	4-1
4.1.1	IEEE-696	4-1
4.1.2	SDSYSTEMS S-100 AND OTHERS	4-1
4.1.3	INITIAL CHECKOUT	4-1
4.2	SERIAL I/O	4-2

TABLE OF CONTENTS (Continued)

Subsection Number

.

Title

Page No.

SECTION V MONITOR

5.0	GENERAL	5-1
5.1	SD MONITOR START-UP	5-1
5.1.1	COMMAND SYNTAX	5-1
5.2	MEMORY COMMANDS	5-3
5.2.1	MEMORY MANAGEMENT - "A" COMMAND	5-3
5.2.2	MEMORY DISPLAY - "D" COMMAND	5-4
5.2.3	EXAMINE MEMORY - "E" COMMAND	5-5
5.2.4	FILL MEMORY - "F" COMMAND	5-5
5.2.5	EXTENDED MEMORY TEST - "J" COMMAND	5-6
5.2.6	LOCATE STRING - "L" COMMAND	5-6
5.2.7	MOVE MEMORY - "M" COMMAND	5-7
5.2.8	MEMORY TEST - "T" COMMAND	5-7
5.2.9	VERIFY MEMORY - "V" COMMAND	5-7
5.3	INPUT/OUTPUT COMMANDS	5-8
5.3.1	INPUT FROM PORT - "I" COMMAND	5-8
5.3.2	OUTPUT FROM PORT - "O" COMMAND	5-8
5.3.3	PORT EXAMINE - "P" COMMAND	5-9
5.4	PROGRAM CONTROL COMMANDS	5-9
5.4.1	BREAKPOINT - "B" COMMAND	5-10
5.4.2	"GO" TO PROGRAM - "G" COMMAND	5-11
5.4.3	SINGLE STEP - "S" COMMAND	5-11
5.4.4	REGISTER EXAMINE - "X" COMMAND	5-12
5.4.5	HEX ARITHMETIC - "H" COMMAND	5-12
5.4.6	COMMAND PROCESSING - "Y" COMMAND	5-13
5.5	DISK UTILITY COMMANDS	5-13
5.5.1	BOOT UP - "C" COMMAND	5-13
5.5.2	READ FROM DISK - "R" COMMAND	5-14
5.5.3	WRITE TO DISK - "W" COMMAND	5-15
5.5.4	FORMAT A DISK - "Z" COMMAND	5-15
5.6	CIO INITIALIZATION AND USE	5-15
5.6.1	ACCESSING THE CIO INTERNAL REGISTERS	5-15
5.6.2	SBC-300 MONITOR AND CIO INITIALIZATION	5-16
5.6.2.1	PORT B	5-16
5.6.2.2	PORT C	5-18
5.6.2.3	PORT A	5-19
5.6.2.4	COUNTER/TIMERS	5-19
5.7	ASCC INITIALIZATION	5-19
5 8		

SECTION VI ENVIRONMENTAL CONSIDERATIONS

6.0	GENERAL	6-1
6.1	POWER REQUIREMENTS	6-1
6.2	PHYSICAL SPECIFICATIONS	6-1

TABLE OF CONTENTS (Continued)

Subsection	
Number	

Title

.

APPENDICES

A	SELECTED IEEE-696 SPECIFICATION SHEETS	A-1
B	BEXADECIMAL TO DECIMAL CONVERSION	B-1
С	STANDARD ASCII CODES	C-1
D	EBCDIC TABLE	D-1
E	CIO SPECIFICATION	E-1
F	ASCC SPECIFICATION	F-1
G	PAL16L8 SPECIFICATION	G-1
B	PORT ASSIGNMENTS	H-1
I	PARALLEL INTERFACES: SASI/CENTRONICS	I-1
J	MONITOR LOCATIONS	J-1
K	SAMPLE I/O SUPPORT CODE	K-1
L	JUMPER CONNECTION QUICK REFERENCE TABLES	L-1
M	DISCLAIMER	M-1
N	LIMITED WARRANTY	N-1
0	PARTS LIST FOR SBC-300	0-1
P	PARTS PLACEMENT DIAGRAM	P-1
Q	SCHEMATIC	Q-1

ILLUSTRATIONS

Figure No.	Title	Page No.
2-1	BLOCK DIAGRAM	2-1
4-1	ADDRESS SWITCH	4-1
4-2	SIGN-ON MESSAGE	4-2
4-3	MEMORY ERROR MESSAGE	4-2

TABLES

Table No.	Title	Page No.
NU.	AILIC	
2-1	CPU CLOCK SPEED SELECTION	2-4
2-2	WAIT STATE SELECTION	2-9
2-3	ON-BOARD MEMORY LOCATION IN BUS SYSTEM	
•	SELECTION	2-12
2-4	JUMPER CONNECTIONS FOR BUS MASTER OPERATION	2-19
2-4 5-1	SD MONITOR COMMAND SUMMARY	5-2
5-2	SD MONITOR REGISTER MAP	5-10
5-3	DISK FORMATS	5-14

SECTION I INTRODUCTION

1.0 GENERAL

The SBC-300 is a high performance, self-contained microcomputer system designed around the Z-80 family of microprocessors. Control (CPU), memory, and extensive input/output facilities are all contained on a single printed wiring board conforming both physically and electrically to every S-100 BUS requirement as specified by IEEE-696. Operation as either the IEEE-696 Permanent Bus Master or as one of any number of slave processors on the bus is supported. The advanced design of the system allows a wide variety of function and performance options to be selected and easily implemented by the end user in most cases by simple dip switch or jumper arrangement. In addition, the SBC-300 is available with the appropriate CPU, support, memory elements, and jumpers installed for operation at clock speeds of 4 or 6 mHz.

In most cases, options are selected by the connection or disconnection of one or more jumpers; a table will show the specific jumper connections to be made for each option desired. The SBC-300 will be configured at the factory in a manner which is likely to suit the greatest number of users. Those requiring different performance may change option selections as required.

1.1 FEATURES

-	S-100 Bus Compatible (IEEE-696)	-	Serial, Parallel, and Counter-Timer I/O
-	Z-80 CPU: 4 or 6 mHz	-	SASI Port
-	64K Bytes of Internal RAM Plus Parity	-	Fully Programmable Communications Options

- 2 to 16K Bytes of PROM Dual Programmable Serial Using Byte-Wide PROM Full-Duplex Channels
- System Memory Addressing . Dual Programmable Baud to 16Mbytes
 Rate Generators

1.2 SCOPE

This document describes the function, performance, electrical and physical characteristics of the SBC-300 single board microcomputer system and its interface to the IEEE-696 bus. For detailed description and analysis of individual integrated circuit components, the SASI port, and the IEEE-696 bus beyond what is presented here, consult the various manufacturer data books and standard specifications.

THIS PAGE INTENTIONALLY LEFT BLANK

STATES AND A DESCRIPTION OF A DESCRIPTIO

SECTION II FUNCTIONAL DESCRIPTION

2.0 GENERAL

This section provides a functional description of the basic blocks that make up the SBC-300 single board microcomputer. A block diagram of the SBC-300 appears in Figure 2-1, and each block is discussed in this section. Refer to Section III for an in-depth theory of operation.

The SBC-300 communicates with peripherals through one SASI/parallel and two synchronous or asynchronous serial ports. When operated as the Permanent Bus Master in accordance with the IEEE-696 standard, the SBC-300 controls all aspects of bus operation and provides timing, control, and status signals for S-100 bus operation as well as its own operation.

In the slave processor mode, the SBC-300 responds to bus cycles initiated by the current bus master and/or processes data in accordance with instructions stored in the on-board ROM and RAM. It is able to communicate with the outside world via its serial and parallel ports. A slave appears to the bus as a 64K block of RAM. Data is transferred between the slave and the bus via the slave's on-board dual ported RAM. A slave device may request service from the bus master by generating an interrupt request.




Figure 2-1. BLOCK DIAGRAM

2.1 CENTRAL PROCESSING UNIT

This block of the SBC-300 includes the CPU and the clock rate generator. The CPU of the SBC-300 is a member of the Z-80 family and can be run at clock speeds of 4 or 6 mHz as selected by the appropriate configuration of the clock speed jumpers.

2.1.1 CPU

During normal operation, the CPU directs all aspects of data manipulation, movement, storage, and retrieval within the SBC-300 microcomputer. The CPU controls communications with the outside world (serial and parallel I/O), other bus peripherals, and dynamic memory refresh during normal bus cycles.

2.1.1.1 Processor Operation

The function of the CPU is to get instructions from memory and perform the desired operations.

The CPU accesses a location in memory and retrieves a coded instruction. This instruction is decoded and then performed by the CPU. The address of the next instruction to be executed is applied to the address lines and the instruction (OP CODE) is fetched and executed. This process is continued indefinitely or until the processor is stopped for some reason.

The system memory is used to contain the instructions for the CPU to execute and the data that is to be processed. A typical instruction sequence may be to read data from a particular peripheral device, store it in a specific location in memory, and then write it out to another peripheral.

2.1.1.2 Z-80 CPU

The Z-80 CPU itself contains many of the same functions (on a smaller scale) as the SBC-300. There is an internal data bus for moving data to and from internal memory (registers) as well as into and out of the Z-80. There are areas that process data, control the operation of the rest of the chip, and generate control and status signals that are required to control and interface with things in the outside world.

Registers are used within the CPU to store instructions and data. These registers are small areas of memory which are controlled directly by the CPU Control (there is no internal address bus for accessing registers). The Z-80 contains 208 bits of R/W memory that are accessible to the programmer. This memory is arranged as eighteen 8 bit registers and four 16 bit registers. All Z-80 registers are constructed of static RAM and include 2 sets of 6 general purpose registers. These registers may be used individually as six 8 bit registers or in pairs as three 16 bit registers. There are also 2 sets of accumulator and flag registers and 6 special purpose registers.

The actual processing in the Z-80 takes place in the Arithmetic and Logic Unit (ALU) which communicates with the internal data registers as well as the external data bus by way of the internal data bus. The ALU can perform a number of logical and arithmetic operations on data contained in internal registers at the direction of the CPU Control. These operations include:

ADD	XOR	INCREMENT
SUBTRACT	COMPARE	DECREMENT
AND	SHIFT L/R	SET BIT
OR	TEST BIT	RESET BIT

One instruction at a time is retrieved from the system memory and loaded in the instruction register. The CPU Control section decodes the instruction and generates all control signals necessary to execute the instruction. These signals read and write data from and to the registers, control the ALU, and control all external items as required by the rest of the system.

Dynamic RAM must be refreshed by accessing each row in the memory matrix once every 2 or 4 milliseconds, depending on the RAM type. While the CPU is busy decoding an instruction that has been fetched, the internal memory refresh register sends address data out on the lower portion of the address bus along with a refresh control signal to access a row of memory. The register is incremented one and the new data sent out to access the next row of memory after every instruction fetch. As the register rolls over, the first row is again accessed. As long as the CPU is running (fetching and performing instructions), the memory is automatically refreshed by the memory refresh counter. This operation is completely transparent to the system.

2.1.2 Clock Rate Generator

The clock rate generator includes the crystal controlled clock oscillator, the division logic to derive the CPU clock (\emptyset) and the 2 mHz CLOCK signal for the bus from the crystal frequency, and the line driver for \emptyset . The divider supplies either a 6 mHz or a 4 mHz CPU clock and a 2 mHz clock. The 6 mHz clock is derived from a 12 mHz crystal, and the 4 mHz clock is derived from an 8 mHz crystal. These rates are selected by a combination of the appropriate chip installed in the board and the installation of a jumper. A 74LS93 must be installed for 4 mHz operation.

This IC also applies the proper division ratio to the crystal frequency to arrive at an output of 2 mHz for either of the two possible crystal frequencies that might be installed. The

bus line CLOCK must always carry a signal of 2 mHz regardless of the processor clock speed to comply with the IEEE-696 specification.

2.1.3 CPU Clock Speed Selection

The SBC-300 is configured at the factory for the processor speed specified, but may be reconfigured by the user for other CPU clock speeds. If the clock speed is to be increased, the speed of the CPU, peripherals, and memory chips must be increased as well. This requires the removal of the existing parts and installation of faster parts in these locations. If the clock speed is to be reduced for some reason, no change of these units is required.

* * * CAUTION * * *

MULTI-LAYER PRINTED WIRING BOARD

When removing parts from the SBC-300 board, ensure that the proper desoldering tools and techniques are used to prevent damage to the printed wiring board surface and inter-layer etches.

The actual CPU clock speed is determined by a combination of jumper connections and parts (crystal frequency and division ratio). One or both of these parts must be changed to effect a change of the CPU clock speed. Once these parts are in place and the appropriate speed units are installed for ICs U46 through U48 and the on-board RAM (Table 2-1), the SBC-300 is configured for one of two CPU clock speeds.

Proc. Speed (mHz)	Xtal (Yl) (mHz)	U42 74LS-	U46 Periph	U47 erals	U48 CPU	RAM Speed (ns)	Delay Line (ns)
6	12	'92	Z8536A	Z8531Å	Z-80B	150	150
4	8	193	Z8536	Z8531	Z-80A	200	200

Table 2-1. CPU CLOCK SPEED SELECTION

If the fastest (most expensive) CPU, peripheral, and memory chips are installed, it is recommended that the CPU clock be run as fast as is consistent with the slowest chip on board. If the fast units are installed, there is little to be gained (slightly less power will be dissipated) by running the CPU clock at a lower than maximum speed. If the SBC-300 is to be run at a low CPU clock rate, populate the board with the slowest parts.

2.2 MEMORY

The SBC-300 supports full 24 bit memory addressing in accordance with the IEEE-696 specification and may be operated in either the PERMANENT BUS MASTER or the SLAVE mode. Appropriate memory facilities are provided on board to fully exploit the flexibility and utility of the standard bus.

A full 64K of dynamic RAM (64Kxl parts) with parity is installed at the factory. Any byte-wide (up to 128K) PROM may be plugged into the 28 pin socket on the board. Upgrading the on-board memory system requires removal of the existing parts and installation of the replacement memory chips. Several modes of refresh are available to cope with any anticipated situation that might arise on the bus.

The on-board memory, as well as any memory that might be visible to the bus, can be mapped to reside in any location within the 16Mbyte range specified by the IEEE-696 S-100 standard. The 16 bit address capability of the Z-80 processor is augmented by a memory mapper which affords the Z-80 access to the entire 16Mbyte potential of the new S-100 bus standard.

The basic memory block of the SBC-300 can be divided into several subsystems: RAM, ROM, MEMORY ADDRESS AND I/O PORT DECODE, and PARITY. These subsystems are required to support the 2 internal memory systems (RAM and ROM) and to ensure compatibility with the bus standard and the various other blocks on the SBC-300.

2.2.1 RAM

The RAM devices that are installed prior to shipment allow pin 1 refresh and are selected so that their speed is consistent with the CPU clock rate.

Upgrading the on-board RAM requires replacement of the set of memory IC chips and the possible connection of a few jumpers to select the proper wait states. The only constraints are that the RAM speed be compatible with the CPU clock rate and that the refresh requirements are met (acceptable device numbers for replacement appear in the Parts List Appendix). CPU clock rate considerations are discussed above in the CPU subsection and the refresh restrictions are covered below.

The RAM subsystem includes a latch for data out and line drivers for interface to the bus as well as several small blocks and functions which work together to allow the RAM to perform properly and interface with the rest of the system. These items are: refresh, refresh wait state generator, and memory timing.

2.2.1.1 Refresh

Any memory device equivalent or similar to the items noted in the Parts List Appendix may be installed in place of the existing RAM devices to increase capacity, replace failed parts (all chips in the array should be of the same type), or satisfy any other particular need of the user. There is, however, one refresh restriction which must be observed:

* * * CAUTION * * *

REFRESH IS NOT SUPPORTED DURING LONG BUS WAIT STATES IF NON-PIN 1 REFRESH PARTS ARE INSTALLED

There are 2 easy solutions to the situation. One is to use pin 1 refresh memory devices in the on-board memory system, and the other is to make sure that items which might cause a long wait state for the processor are never attached to the bus.

2.2.1.1.1 Pin 1 Refresh Memory Devices

Industry standard 64K dynamic RAM devices are refreshed by addressing each row of the storage matrix within 2 milliseconds. This is called Row Address Strobe or RAS refresh. Pin 1 is not connected to the IC die (it is a nonconnect) and the only method of refresh is through the refresh address access cycle generated elsewhere.

The Z-80 is rather unique among microprocessors in that it has an internal 7 bit address counter which generates memory refresh cycle addresses after every OP CODE fetch. If the processor is stopped (in a wait state) for an extended period of time, there will not be an OP CODE fetch in time to refresh the memory. If this happens, the data in the memory devices becomes uncertain and cannot be used.

Memory devices with pin 1 refresh, however, allow refresh to be performed by an additional procedure. There is logic on the SBC-300 that detects long wait states. This logic then generates a refresh cycle which is applied to pin 1 of the appropriately equipped memory devices. The pin 1 refresh cycle is repeated at the proper interval until the processor is running again and pin 1 refresh is no longer needed to maintain the memory. The only time this cycle is implemented is during wait states where the CPU is stopped for excessive amounts of time.

2.2.1.1.2 Avoiding Long Wait States

The other method of preventing loss of memory data during long wait states is to never install any device on the bus that might generate a long wait state. Sources of long wait states include items such as polled I/O disk controllers. These devices use wait states to transfer data into the system memory.

If, for example, the processor directs the disk controller to read a sector into memory and the sector requested has just passed the heads, the controller must then wait (which means that the CPU must wait) until that sector comes around again to retrieve the data. This can take as long as 150 ms, which is 148 ms too long if the memory content is to remain valid. The Versafloppy II disk controller is an example of a polled I/O device that uses a wait state to transfer data to and from the memory. DMA devices such as the Versafloppy III disk controller do not cause long wait states for data transfer and so are safe to use without pin l refresh memory devices.

2.2.1.1.3 Refresh During DMA Operations

During a DMA operation, where the SBC-300 is the permanent bus master but has relinquished control of the bus to a DMA device, the SBC-300 generates standard memory refresh cycles from bus activity. As a result, even if there is a DMA controller transferring data into another memory board on the bus, SBC-300 memory is preserved due to its self-generation of refresh cycles.

Depending on the design of other memory boards that might be installed on the bus, this self-generated refresh cycle might take care of memory on the bus as well as on the SBC-300 board. Older designs (such as the EXPANDORAM II and III) can be refreshed in this manner, while newer designs (EXPANDORAM IV) support this procedure as well as several others during DMA transfers.

These boards, which might be used with other processors (no other processors generate memory refresh cycles), take care of the refresh for on-board memory devices themselves and do not care if the bus master processor is stopped or not. With that type of design, when refresh is not obtained from the bus master processor, the memory board generates cycles for itself. The bus is held off by the memory board until it is finished so it will not be busy with a refresh cycle at the moment its services are required by the bus. Refresh occurs independently of all other activity on the bus, and memory is thus immune to long wait states. There is usually a jumper selected option on these boards, however, which allows refresh to be forced at certain times.

2.2.1.2 Refresh Wait State Generator

The refresh wait state generator performs 2 functions. It simultaneously generates the pin 1 refresh signal and holds the wait line low. The wait line is held low only during the refresh cycle; so if the long wait state which activated the pin 1 refresh cycle goes away, the pin 1 refresh cycle will not be interrupted until the refresh is complete.

2.2.1.2.1 Wait States

Wait states are ordered by devices attached to the S-100 bus and by the SBC-300 itself. Generally wait states are called to hold up the processor because the CPU runs faster than some peripheral devices are capable of responding. To ensure that valid data read from memory has settled on the data lines before the processor tries to use it, or to prevent the processor from removing the address and data from those lines before a write cycle is complete, the processor is stopped for a period of time until it is safe to proceed.

The wait state is implemented by pulling down the WAIT* line to the processor. The CPU checks this line on the falling edge of the clock during clock cycle T2 and, if it finds that the WAIT* line is active, it suspends all processing that might have occurred during the next clock cycle. This creates a wait state. The CPU will continue to create wait states as long as its WAIT* line is held low.

This line (WAIT*) is controlled by the wait state generator. It can be triggered by the wait state generator (jumper W3; see Appendix called Jumper Connection Quick Reference Tables) when lines indicating an OP CODE or memory operation become active. This memory operation trigger produces a synchronous wait state of exactly 1 clock period. A device on the bus can trigger a wait state of any duration beginning at the next falling edge of the clock by pulling and holding down either of 2 lines on the bus (RDY and XRDY). And finally, the refresh wait state generator can cause a wait state to hold off the processor while it applies a refresh cycle to pin 1 of the on-board RAM. The RAM cannot be written to or read from during refresh, so the processor and bus must be prevented from trying to use the RAM until refresh is complete.

2.2.1.2.2 Wait State Selection

There are 3 modes of memory operation wait state generation possible as selected by jumper W3 (Table 2-2). If the M1 mode is selected, a wait state is generated each time the processor fetches an OP CODE from memory. A wait state will not be generated during a normal memory access because the memory is fast enough to respond to the processor between clock T states. During OP CODE fetches, however, the CPU must refresh the on-board RAM after the read, so a wait state is generated to allow this refresh to be completed before things continue.

If the MREQ* option is selected, a wait state is generated during both OP CODE fetches and normal memory accesses. This allows slower memory devices to be used with a faster processor; the processor is held up during a memory read from the slow memory but operates at full speed otherwise. If no memory option wait state is selected, then no wait states are generated during memory operations.

Wait	Wait State					
Selection	Jumper	Function				
Ml* MREO*	W3-2 to W3-3 W3-1 to W3-2	<pre>1 wait state during OP CODE fetches 1 wait state during memory accesses</pre>				
None	None	No waits inserted				

Table 2-2. WAIT STATE SELECTION

2.2.1.2.3 Pin 1 Refresh Generation

During long wait states, the CPU is stopped. This means that there will be no RAS refresh cycles from the processor to maintain the memory. If the processor is stopped for more than approximately 2 msec, the content of the memory will no longer be valid. To prevent such loss of data, the refresh wait state generator provides pin 1 refresh cycles to the RAM whenever the CPU is in a wait state. This causes a wait state to be generated in order to prevent the CPU from accessing the RAM during refresh.

2.2.1.3 Memory Timing

Memory timing is basically concerned with restructuring the address information that appears on the internal address bus into a form that is compatible with the memory devices and then applying that data to the RAM chips. These 2 functions are implemented by the RAM address decode and the row and column timing areas.

2.2.1.3.1 RAM Address Decode

The RAM address decode is very simple. It serves to interface the RAM chip address lines to the SBC-300 internal 16 bit address bus. This is required because in order to fit into a

standard 16 pin package, large capacity memory devices have only 8 address lines.

The 16 bit address on the bus is broken into two 8 bit bytes and applied first one and then the other to the 8 address lines of the memory chip array. The two halves of the address are referred to as the row and the column address. Each pair of row and column addresses defines a unique storage location within the storage matrix of each memory device. This is the same addressing scheme that was developed for magnetic core memories. First the row address portion of the information on the address bus is applied to the memory array address lines and then the row enable line (RAS strobe) to the memory device array is activated. Next the column address portion of the information on the address bus lines is applied to the same memory array address lines and then the column enable line (CAS strobe) is activated. This procedure loads the 16 bit address of the desired location into the memory device where it is internally decoded to specify a unique location in the storage array.

There are specific intervals of time which must elapse between each segment of the addressing operation (enables, settling time, change between row and column address, etc.). The row and column timing area is responsible for generation of these intervals.

2.2.1.3.2 Row And Column Timing

The memory devices require a time interval between the different parts of the addressing operation. A delay line with multiple taps provides these intervals. A pulse applied to the input appears at each successive tap a specific time after it appears at the previous tap (or the input, if the first tap is being considered). Devices and lines connected to these taps are therefore activated sequentially with specific time intervals inbetween.

This area also contains logic which, when activated by the signals from the delay line, controls all aspects of RAM reads and writes.

2.2.2 ROM

A 28 pin socket on the SBC-300 board allows any of several byte-wide (2Kx8, 4Kx8, etc.) ROMs to be plugged in. The Parts List Appendix shows compatible device type numbers. The ROM installed before shipment includes the Monitor firmware and the system BIOS. There is empty space in the ROM that can be used for any purpose the user desires. However, the user is responsible for programming the ROM with additional code.

The ROM portion of the on-board memory occupies the first 64K segment of the total 128K block even though a relatively small device might be installed in the socket. Because the ROM is invisible to the bus, the SBC-300 appears to other items on the bus as an ordinary 64K block of RAM when in the slave mode.

2.2.3 Memory Address And I/O Port Decode

The on-board address and port decoding is handled by a combination of the Zilog 8536 Counter Input/Output chip (CIO),

a PAL1 (U28) and a decoder chip. The CIO generates a signal (BOOT) which is used by the PAL in conjunction with other timing signals to decide whether the processor is talking to ROM, RAM or off-board memory. When an I/O address is being generated, the PAL inhibits the enables to memory devices, and the port decoder (U57) enables the particular I/O device being addressed.

2.2.3.1 Memory Address Decode

The memory decoder generates 4 signals which are used to determine what the SBC-300 is addressing. These 4 signals are created within a PAL (U28) from a combination of standard Z-80 timing signals and on-board hardware/software switches.

The 4 signals are PROM ENB*, RAM ENB*, RDOFF* and GORAM*. PROM ENB* is the on-board ROM enable signal. It is created when the BOOT signal is active. RAM ENB* is the on-board RAM enable signal for the ROM data latch. RDOFF* is the signal which determines that the present memory cycle is off board on another 696 board. The 4th signal is GORAM* and is used to generate the RAS* and CAS* RAM timing signals.

2.2.3.2 I/O Port Decode

The I/O port decoder is an address decoder which enables a particular I/O device whenever its preselected address is found on the address bus. The I/O decoder generates the enable signals for the ASCC, CIO, memory mapper, SASI Port and the ATTEN interrupt bit.

2.2.4 Parity

The SBC-300 generates and checks odd parity in its on-board RAM. The parity checker generates 2 parity error signals for use by the on-board processor and, if in the slave mode, the bus master. Parity error detection is enabled by jumper W14-4. The on-board parity error signal is also sent to CIO port C bit 1.

2.2.5 Mode Dependent Memory Characteristics

Some memory characteristics exhibited by the SBC-300 change according to the SBC-300 mode selected. The SBC-300 may be operated as either the Permanent Bus Master (PBM) or as a slave processor in accordance with IEEE-696 specifications.

2.2.5.1 Bus Master Mode Memory

In the PBM mode, the SBC-300 occupies 128K of the system memory space. The 1st 64K segment is PROM (even though there may be only an 8K PROM installed in the socket), and the 2nd

1PAL - Programmable Array Logic MMIR

64K segment is the RAM. The entire on-board memory can be mapped into any 128K location in the 16Mbyte bus memory system desired by the appropriate setting of dip switch SW-1 elements as detailed in Table 2-3.

Table 2-3. ON-BOARD MEMORY LOCATION IN BUS SYSTEM SELECTION

SW-1 (X=Off; O=On)					1		Always Off When Master	SBC-300 On-Board Memory Begins At (In Hex)		
	(1	-01	11	0-0	11)		Master	Begins AL (in nex)		
8	7	6	5	4	3	2	1	and the states birth in		
				the first floor first						
0	0	0	0	0	0	0	X	010000		
0	0	0	0	0	0	Х	X	030000		
0	0	0	0	0	Х	0	X	050000		
0	0	0	0		Х	X	Х	070000		
								and both and prepares light		
х	х	х	x	х	Х	0	X	FD0000		
X X	X	X	X	X X	X	Х	X	FF0000		

2.2.5.2 Slave Processor Mode Memory

In the slave mode, only the 64K of on-board RAM is accessable by the bus. The ROM is completely invisible to the bus, even though the on-board processor might be operating out of it. The RAM portion of the on-board memory is dual ported--it can be accessed by the on-board processor and the bus as well. In the slave mode, the on-board RAM is the only means through which the PBM and all other items on the bus can communicate with the slave processor.

2.3 MEMORY MAPPER

Since the Z-80 microprocessor contains 16 address lines, it can address 64K of memory directly. In order to meet the IEEE-696 specification and allow the addressing of the full 16Mbyte of memory, an additional 8 address lines must be generated. A memory mapper allows the Z-80 to control indirectly, through the mapper, all 24 address lines of the S-100 bus. The memory mapper consists of bipolar RAM, a multiplexer, gating logic, and a switch and comparator for selecting which 64K block of system memory the board occupies.

2.3.1 Mapper Operation

The upper 4 bits of the Z-80 physical address lines (Al2-Al5) are applied to the address inputs of the memory mapper RAM to determine which location within the mapper will be accessed

and output to the extended address bus (A12-A23). The mapper is accessed as I/O port 71H for purposes of updating the stored address. The memory mapper is bypassed during I/O operations and during accesses to the on-board EPROM. During these periods the upper 4 address bits are passed directly to the logical address bus.

2.3.1.1 Board Address Select

The board address select consists of a dip switch and a comparator containing internal 20K pullup resistors. One set of inputs to the comparator is tied to address bus lines Al6 to A23 on the S-100 bus side of the on-board address line drivers. The other set of inputs to the comparator is connected to the board address select dip switch SW1.

Once the starting address of the board is decided, SWl is set to reflect the board starting address. The 8 elements of SWl are capable of defining 256 different 64K boundaries anywhere in the 16Mbyte range (28). The boundaries can be thought of as boundary 0 (beginning at address 0) through boundary 255 (beginning at address 16,711,680). The user selects the binary equivalent for the decimal number of the desired boundary by means of the 8 elements of SWl.

The comparator constantly checks the state of each of the address lines to which it is connected against the setting of the address select switch SW1. When a match is found, the comparator indicates the match by activating its output line. This output is used elsewhere on the board to indicate that the on-board 64K of RAM is being addressed.

Care must be taken to ensure that no 2 boards attached to the bus have memory that is set to the same starting address.

2.3.1.2 Mapper RAM

The memory mapper RAM is composed of a 16x12 bit bipolar highspeed static RAM matrix (three 16x4 devices). The upper 4 bit address lines (Al2-Al5) from the Z-80, when applied to the mapper RAM address input lines, select one of sixteen 12 bit data words. This 12 bit word is applied to the upper 12 bits of the S-100 address bus (Al2-A23). These 12 address lines from the mapper, along with the 12 lower address lines from the CPU, create 24 real address lines that are driven out onto the bus, allowing access to the entire 16Mbyte address range by the Z-80.

The 12 bits of data to be loaded into the mapper RAM appear on the 8 data lines (D0-D7) of the data bus and 4 lines (A8-A11) of the address bus of the SBC-300 board. Just after power up the monitor firmware loads the mapper RAM with initial data by applying the appropriate data to the input lines for each address and selecting each of the 16 locations sequentially with A12-A15 of the on-board address bus. Once the operating system is in control, it can change the content of the mapper RAM at any time as required. Application programs can, in certain circumstances, change the mapper RAM content dynamically as the program executes, allowing immediate access to the entire system memory.

2.4 INTERRUPT CONTROLLER

The SBC-300 provides service for the Non-Maskable Interrupt and the 8 vectored interrupt lines from the S-100 bus as well as the interrupts from the 2 serial communication ports. The interrupt controller prioritizes on-board interrupt requests and the vectored interrupt lines from the bus, generates the least significant 8 bits of the interrupt vector, and starts the interrupt cycle. An interrupt can also be generated in response to the status of several other lines on the bus (jumper selectable by the user) to allow special features to be implemented.

2.4.1 Interrupt Select

An area of the SBC-300 board is reserved for the user to install jumpers to connect any of several lines from other places on the board as well as the S-100 bus to the NMI and vectored interrupt lines. If the SBC-300 is configured to be the bus master, there are 2 lines from the bus that are considered inputs (PWRFAIL and ERROR). As a slave processor, there are 7 jumpers that might be installed in order to put the on-board parity error and attention lines out onto the bus as vectored interrupts.

As a master, the power failure line might be jumpered to the NMI and the parity error line jumpered to one of the vectored interrupt lines so that if devices on the bus detected these conditions, the bus master processor would be immediately notified and could proceed accordingly.

As a slave, the on-board attention line could be jumpered to any of 6 vectored interrupt lines on the S-100 bus. This would allow the interrupt controller on the bus master to easily determine which slave was requesting the interrupt and then generate the appropriate service routine vector. This procedure limits the number of slaves on the bus to 6.

In situations where there are more than 6 slaves on the bus, all slave attention lines could be jumpered to one or a few interrupt lines on the bus. Then the bus master CPU can poll the slaves to determine which one requested the interrupt as part of the interrupt service routine. All slave parity error lines are usually jumpered to a single interrupt line (VII), and the bus master CPU can poll the slaves to determine the location of the error.

2.5 BUS INTERFACE

The IEEE-696 S-100 bus standard specification describes a universal bus that can support a wide range of processors rather than just a particular processor or family of processors. Signals required to be on the bus were deemed to be the best compromise between ease of implementation and utility. The bus is configured to allow the widest range of processors the most flexibility possible without being completely incompatible with existing systems.

Because the bus is a universal design, it is not expected that all status and control signals from a particular processor will be directly applicable to the bus. Nor will all signals on the bus be directly compatible with the requirements of a particular CPU.

All processor manufacturers have slightly different ways of accomplishing the same task with their machines. Signal names, polarity, phase, and timing might vary radically from one CPU to another even though the bottom line of what gets accomplished is identical. As a result of all this, some of the signals from the Z-80 CPU on the SBC-300 must be processed a little before they can be applied to the bus, and some signals on the bus must be processed a little before the Z-80 can understand them. This is the task of the bus interface.

The bus interface block consists of several smaller blocks, each one handling a portion of the job. As bus master, the SBC-300 supplies all timing and control signals on the bus. The bus timing controller uses signals from the CPU and other areas of the board to synthesize the signals required to run the bus. The Power On Clear (POC) and RESET area simply handles power clears and resets when the SBC-300 is in either mode.

When the SBC-300 is operated in the slave mode, the slave control area translates the bus signals into a form that can be understood by the Z-80 so that the SBC-300 can be properly synchronized to the activity on the bus.

2.5.1 Bus Timing Controller

As bus master, the SBC-300 must supply all timing and control signals for the bus. The IEEE-696 specification calls for a bus that runs almost everything off the rising edge of the clock. The Z-80 runs almost everything off the falling edge of the clock. The solution is to invert the clock and signals out of the CPU and to delay some signals to get the proper timing relationships for the bus. Other signals that the Z-80 does not provide directly are derived from the signals that it does generate.

The status and control signals that must be applied to the bus when the SBC-300 is operated as bus master are derived from the status and control signals from the Z-80 CPU. Through combinational logic (gates), bus standard equivalent signals are constructed from those available from the CPU and applied to the bus. Clocked logic allows the timing relationship of signals to be adjusted to meet the bus specification.

Signals that need to be delayed or have the timing adjusted are derived from a chain of flip-flops. As the input propagates through the chain, different signals are picked off at the appropriate points and sent out to the bus. These signals have a constant and predictable relationship to each other in time and match the signal function and timing relationships required by the IEEE-696 bus specification.

The address bus is derived from two sources. The low order bits (A0-All) are taken directly from the Z-80, while the high bits (Al2-A23) are derived from the memory mapper. The low order address bits are driven directly by the Z-80 CPU and will not hold on the bus as long as the high bits. Therefore, care should be taken to insure that no conflict is created by the short hold time on the low order address bits.

In the slave mode, the SBC-300 must not apply any of the on-board status and control signals to the bus. The bus timing controller causes the output of the gated line drivers for these signals to become a high impedance when the master mode is selected, thereby preventing problems on the bus.

2.5.2 Power On Clear (POC) And RESET

This area performs a few simple tasks. In the master mode, it holds down the RESET line on the bus until the power has come up and stabilized. This makes sure that all items on the bus (including the SBC-300) get a RESET signal **after** the power lines are up far enough for the devices to fully reset. Otherwise, there may be random data in memory cells and registers that could cause trouble if they are not cleared out before normal operation.

The RESET signal is applied to the POC and SLVCLEAR lines on the S-100 bus line only when enabled as a master. The RESET line is also usually connected to some sort of mechanical momentary switch which is accessible to the operator for manual resets.

As a slave processor, the SLVCLEAR and RESET lines are monitored and acted upon instead of driven. When the bus master sends out a SLVCLEAR signal on the bus, the slave processors on the bus decode this signal as an on-board RESET and reset.

2.5.3 Slave Control

The same bus signals which were derived, inverted, and/or time shifted from the Z-80 before they were applied to the bus by

the SBC-300, acting as bus master, must be decoded by the SBC-300, acting as a slave processor on the bus, before they can be understood by the SBC-300. The slave control area takes care of this task.

Combinational logic elements (gates) and a Programmed Array of Logic (PAL) device are used as a decoder to condense many of the status and control signals on the bus down to a few signals that are meaningful to the SBC-300 and the on-board Z-80. This requires that some signals be inverted and/or shifted in time.

All the timing signals that the on-board CPU would normally generate for the on-board memory come from the bus during communication with the slave. Normally the slave is running free with its CPU controlling all aspects of its operation. But when it has to communicate with the bus (through the memory), the bus must control the memory so that everything on the bus will be compatible and synchronized to the bus universal timing. The slave control logic accomplishes this.

Because slave control logic is required to interface the slave to the bus during memory transfers, the slave's memory does not appear (respond) exactly as just another board of **fast** memory. There is an appreciable propagation delay through the several layers of decoding in the slave control area before the appropriate signals are applied to the on-board memory.

The slave control area contains a wait state generator that sends an adjustable number of waits to the bus master CPU to hold things up until the slave decoding logic and memory systems have had a chance to settle and respond. The wait state generator is simply a counter that holds down the RDY line on the bus until it has counted a specific number of cycles from the bus clock. The number of waits sent to the bus master CPU is selected by jumper.

A jumper (W13) selects from 0 to 5 waits to be sent to the master during the slave memory cycle. If there is no jumper installed, there will be no wait states sent during a memory cycle to the slave. The number of waits that should be sent is dependent on the processor clock speed of the bus master and how fast the rest of the memory in the system runs. The bus master inserts waits into an ordinary memory access, the number depending on the speed of the memory installed. The number of waits needed to be inserted by the slave is in addition to the waits generated by the master during an ordinary memory access.

In the master mode, the entire slave control area is disabled because as the master the SBC-300 is supplying the status, timing and control signals to the bus instead of receiving them.

2.6 MASTER/SLAVE CONTROL

The IEEE-696 S-100 specification allows for the connection of 3 main types of devices to the bus. There must be exactly 1 Permanent Bus Master (PBM) on the the bus at all times. Up to 16 Temporary Bus Masters (TBM) and any number of bus slaves are allowed on the bus (short of the 22 maximum slots called for in the specification).

The SBC-300 may be operated as either the PBM or a slave processor. There is a significant difference between one mode and the other in the way the SBC-300 operates and interfaces to the bus. These differences are effected by logic on the SBC-300 board responding to the mode selection jumpers and switch.

2.6.1 Master/Slave Select

The main difference in the activities of an SBC-300 operating in the master mode and the slave mode is that in the master mode, the SBC-300 puts status, timing, and control signal on the bus, while in the slave mode, it is controlled by those signals on the bus. In order to accomplish the necessary changes, a single hardware jumper (W4) is used to tell the CPU whether the board is a master or slave.

In the master mode, the board ignores the status, timing, and control signals on the bus and arranges to drive these lines on the bus instead. In the slave mode, the drivers are disabled and the decoders are enabled so that the signals on the bus control the slave.

2.6.2 Line Termination

The IEEE-696 bus standard provides that pull up resistors for certain lines on the bus shall reside either on the bus (mother board) itself or on the PBM. Since the SBC-300 can be operated either as a PBM or as a slave processor, there is a means of providing the pull up resistors for the bus lines that require them when in the master mode (if the bus does not have them). A group of jumpers must be installed if the SBC-300 is to provide the pull up resistors for the bus. If the SBC-300 is not to supply this pull up function or is operating as a slave processor, these jumpers are to be removed. Table 2-4 shows the line termination jumpers.

2.7 SASI/PARALLEL PORT

The SASI/Parallel port is an 8 bit parallel data port along with 8 status lines. The data port is a bi-directional 8 bit port located at I/O address 70H. The 8 SASI control lines are controlled by the CIO port A, which is addressed as I/O port 7AH. The port is available to the user through connector J4 and can be configured to be any parallel device required. See the Appendix called Parallel Interfaces: SASI/Centronics for a detailed pin out.

2.7.1 CIO

The Zilog 8536 Counter Input/Output chip (CIO) is a parallel I/O device containing two 8 bit parallel ports and one 4 bit port. Internally, the device has three 16 bit counter/timers which are user configurable. The SBC-300 uses port A of the CIO as the status lines for the parallel port, port B as the vectored interrupt controller and port C as general purpose control lines. See the Appendix called CIO Specification for a brief description of the CIO.

Table 2-4. JUMPER CONNECTIONS FOR BUS MASTER OPERATION (See the Appendix called Jumper Connection Quick Reference Tables for detailed list)

Jumper #	Master	Slave	Notes
w4	OUT	IN	Master/Slave select
Wll	IN	OUT	MWRT select
W15	IN	OUT	Pull ups
W19			Slave clear input
1-2	OUT	(manual reset	Manual slave clear when in
		for slave)	position 1-2
2-3	OUT	IN	Standard position for
			slave
W21	IN	OUT	RDY and XRDY enable

2.8 SERIAL I/O

The SBC-300 contains 2 full duplex serial ports. Port A (J3) is a general purpose port for use with serial printers or any user selectable device. Port B (J2) can be used for a terminal when a video board is not used or as a general purpose port. When a video board is not present, the Monitor checks for a terminal on port B and waits for a response from the port. The ports can be used as DTE or DCE, depending upon the way the configuration jumpers (J5, J6) are wired.

2.8.1 ASCC

The heart of the serial ports is the Zilog 8531 Asynchronous Serial Communications Controller chip (ASCC). This chip contains 2 full duplex asynchronous serial ports along with dual programmable baud rate generators. See the Appendix called ASCC Specification for the programming model.

2.9 POWER REGULATION

The SBC-300 is equipped with an on-board 5 volt linear regulator for use on 8 volt power busses in accordance with the IEEE-696 S-100 standard. The regulator provides a tightly controlled 5 volts for use by the various devices on the board and is immune to minor fluctuations of the 8 volt power bus.

If 5 volt operation is required (instead of the normal 8 volt operation) and an adequate source of well regulated 5 volts is available, a jumper connection will configure the SBC-300 for 5 volt operation.

A separate area of the power supply section provides +/-12 volts DC from the +/-16 volts DC power lines on the bus. The +/-12 volts is used on the SBC-300 board only by the Asynchronous Serial Communications Controller (ASCC) for the standard RS-232 communication protocol. Very little power is dissipated in this area, and so a zener stabilized supply is more than adequate for the purpose.

2.9.1 5 Volt Bus Operation

If the SBC-300 is to be installed on a bus using a **regulated** 5 **volt** power supply to operate the 8 volt S-100 lines (this deviates from the IEEE-696 specification), the on-board regulator may be bypassed by the installation of a jumper between the input and the output pins of the regulator device. If all items to be attached to the system bus are able to operate with a 5 volt power bus instead of the 8 volts called for in the specification and if a suitable high performance 5 volt regulated power supply is available, it may be advantageous to operate the system on 5 volts.

Operation of the SBC-300 on a 5 volt line eliminates the heat generated by the on-board regulator, allowing a system to be safely operated without a fan. A high performance regulator (such as a switching regulator) for the bus dissipates little or no heat itself and provides generally superior regulation.

*** CAUTION ***

The on-board regulator must remain in place when the SBC-300 is operated on an 8 volt power bus, or destruction of the logic devices may result.

SECTION III THEORY OF OPERATION

3.0 GENERAL

This section covers the general theory behind the subdivisions of the SBC-300 and the basic requirements of the IEEE-696 bus specification. For detailed information about the IEEE-696 specification, the user needs to obtain a copy of the specification from IEEE as it cannot be reproduced in full in this manual.

3.1 MASTER/SLAVE MODES

3.1.1 Masters

There are 2 types of bus masters, permanent and temporary. Each serves a different purpose in the system from the other. The Permanent Bus Master (PBM) is a processor type device that controls the bus and the system, while the Temporary Bus Master (TBM) is usually a DMA device such as a disk or tape controller that obtains control of the bus from the PBM from time to time for the purpose of transferring data to or from the PBM or any slave on the bus.

The acting bus master (permanent or temporary) may initiate bus cycles and, if it is the PBM, may grant control of the bus to a TBM on the bus.

3.1.1.1 Permanent Bus Master (PBM)

As the PBM, the SBC-300 directs all bus activity within the system, driving all data, address, status, and control lines of the bus in accordance with the IEEE-696 bus standard. In this mode, the SBC-300 may utilize any resource that might be attached to the bus including system memory, any I/O device such as a disk controller or a multiple port I/O card, keyboard and video boards, and any slave processor on the bus.

Control of several lines on the bus is retained by the PBM whether it has control of the bus or not. These signals include both clocks, the Power On Clear (POC), and the memory write line and are always controlled by the PBM to avoid timing and synchronization problems with the other items on the bus.

3.1.1.2 Temporary Bus Master (TBM)

A TBM is a device on the bus that may request control of the bus from the PBM to conduct some business that requires the use of the bus. When a TBM gains control of the bus, it becomes the acting bus master until it returns control to the PBM. The TBM does not generate all possible bus cycles nor does it generate all signals required to drive the bus. It may not grant control of the bus to another TBM nor accept an interrupt request.

TBMs acquire control of the bus, conduct as much business as required, and return control of the bus to the PBM. Disk and tape controllers are examples of devices that are considered TBMs.

3.1.2 Slaves

The SBC-300 may be configured as a slave processor and interfaced to the bus as a bus slave. However, not all bus slaves are slave processors.

A slave on the bus responds to bus cycles initiated by the acting bus master. The slave constantly monitors the bus and, if addressed during a particular bus cycle, accepts the data it finds on the bus data lines or applies data to the lines as directed by the control signals present on the bus. At the completion of the bus cycle, the slave resumes its regular activity if it is a slave processor or some similar device, or waits for the next bus cycle if it is a memory board or other unintelligent device.

The slave appears to the bus as simply another block of memory. Each slave only takes up a slot on the bus and a block of memory in the map. The location (address) of the slave in the memory map is selected on the slave board by means of a switch. Slaves can be added to the system until there are no more available slots on the bus or blocks in the memory map.

3.1.2.1 Slave Processors

In the slave processor mode, the SBC-300 operates exclusively out of on-board memory and may utilize any resource that it can access through any means except the S-100 bus (serial ports and the SASI interface). Unless addressed during a bus cycle, the slave processor operates independently of most lines on the bus.

The acting bus master may communicate with the slave processor only through the slave processor RAM which is dual ported. As a slave processor, the SBC-300 may not initiate a bus cycle, and the only way it can access the bus master is if it pulls down an interrupt, wait, or error line to get the attention of the bus master in response to some condition on the board.

3.1.2.2 Slave Processors And Multi-User Systems

Slave processors on the bus spread the intelligence and processing power around, allowing high performance multi-user and/or multi-tasking systems to be easily configured on the S-100 bus. Each slave processor runs at full speed regardless of activity on the bus or in other processors attached to the bus. The only time bus activity impacts a particular slave processor is when it must interrupt the PBM to access some shared resource (hard disk, tape controller, etc.).

This approach offers an excellent compromise between a large, shared processing system with its high cost, inherent response time problems, and all or nobody operation and a locally networked, fully independent array of work stations with its high cost due to duplication of hardware and high speed network communication problems.

In this configuration, each user has essentially a fullfeatured system operating independently of the bus. This is a vast improvement over previous small multi-user systems where a single processor served every user and attended to system housekeeping as well. That type of system spreads a single 8 bit microprocessor too thinly and causes overall system performance to deteriorate dramatically with each added user.

Previously, the solution to this problem was to run multi-user systems on minicomputers using powerful (and expensive) 16 and 32 bit processors, operating systems, and applications programs. A single user on the system seldom required the power of a large processor--which was good--because the power of the single large processor in a shared system was diluted by the addition of each user. Beyond a certain number, the addition of more users would often cause the performance of the entire system to deteriorate to the point that it was no longer acceptable and a still larger system was required.

More recently, arrays of small, completely independent systems have been linked via one form or another of a high speed serial communication network. However, there has not yet been a lot of satisfaction with the performance of these systems, and the cost is quite high owing to the duplication of hardware (each user has a power supply, floppies, maybe a hard disk, etc.).

A multi-user system consisting of 1 PBM to manage the shared resources attached to the bus and a slave processor for each user offers performance almost independent of the number of users on the system. In addition, this approach allows the use of the enormous amount of familiar and inexpensive application software available to run on the Z-80 and other microprocessors.

3.1.3 Bus Cycle Operations

There are 2 kinds of bus cycles that might occur on the bus, generalized bus cycles and Temporary Master Access (TMA) cycles. All effective communication between 2 devices attached to the bus takes place during a generalized bus cycle (or simply, bus cycle). The process of a TBM gaining control of the bus from the PBM, conducting its business, and then returning control of the bus to the PBM is called a TMA.

3.1.3.1 Bus Cycles

A bus cycle is initiated by a device acting as the bus master and is responded to by a device acting as a bus slave. Communication must occur between the bus master and the addressed bus slave. The device acting as the bus master may be either the PBM or a TBM that has acquired control of the bus from the PBM, and the bus slave may be any addressable slave on the bus.

For example, if the PBM requires some data stored in a memory board somewhere out on the bus, it initiates a bus cycle by applying the address of the required data to the address lines of the bus. The slave (memory board), recognizing its address on the bus address lines, then responds to the control signals put on the bus by the PBM by retrieving the data from the specified address, putting it on the bus data lines, and informing the PBM that the operation is complete. The PBM deselects the slave, ending the bus cycle, and continues its processing.

3.1.3.2 Temporary Master Access (TMA) Cycles

The TMA bus cycle is initiated by the TBM requiring the use of the bus. The PBM turns over control of the bus to the highest priority TBM requesting the bus. Once a TBM gains control of the bus, it may initiate generalized bus cycles as often as its task requires before returning control of the bus to the PBM.

While the TBM has control of the bus, however, another TBM may not gain control of the bus from the TBM acting as bus master. Only the PBM may assign control of the bus to a requesting TBM, and it can only do so it when it has control of the bus. If, for example, the PBM required data from a disk, it would direct the disk controller (a TBM) to read a sector from the disk and load the data into memory beginning at a specific address. The starting address may indicate memory on the PBM board or any memory on the bus.

When the disk controller has read the data and checked for errors, it initiates a TMA cycle by requesting control of the bus. The PBM then releases the bus to the disk controller. The disk controller takes control of the bus and initiates a bus cycle to load the data from the disk into memory, beginning at the starting address requested by the PBM. When the transfer is complete, control of the bus is returned to the PBM, thus completing the TMA cycle.

While the disk controller TBM is the acting bus master, any requests for the bus from other TBMs are ignored. When the current TMA is complete and the bus has been returned to the PBM, control of the bus may be granted to the highest ranking requesting TBM.

3.2 SLAVE PRINTER

Slave priority is determined by jumpering the ATTEN line (W14) to the vectored interrupt bus. Priority is given to slaves as determined by the jumper setup. The bus master then arbitrates and gives priority to the correct slave.

3.3 INTERRUPTS

The purpose of an interrupt is to allow peripheral devices to suspend CPU operation in an orderly manner, and begin a service routine for the peripheral. This service routine usually involves the exchange of data or status and control information between the CPU and the peripheral requesting the interrupt. When the interrupt service routine is complete, the CPU resumes operation exactly where it left off when it received the interrupt request.

There are 2 types of interrupts recognized by the Z-80, a software maskable interrupt (INT) and a Non-Maskable Interrupt (NMI). A control line for each goes into the CPU. The NMI cannot be ignored by the CPU. When this interrupt line goes active, the CPU must accept it. The maskable interrupt function can be enabled or disabled by instructions in the program that the CPU is executing.

3.3.1 Non-Maskable Interrupts (NMI)

An NMI will be accepted by the CPU whenever it is requested. Because of this characteristic, the NMI is usually reserved for indicating very important conditions such as power failure or error detection. The SBC-300 allows the user to select (by jumper) any of several lines from the S-100 bus for connection to the NMI line into the Z-80.

When an NMI is accepted, the CPU ignores the next instruction that it fetches and does a restart to location 0066 HEX instead. This location is usually in ROM and should contain the starting address out in RAM of the service routine for the NMI. What the CPU finds in 66 and the rest of the service routine (if any) is completely at the discretion of the user.

3.3.2 Maskable Interrupts

The maskable interrupt function can be enabled or disabled by the program that the CPU is executing. If there are areas of a program where timing or other constraints would make an untimely interrupt inconvenient or catastrophic, the user has the option of disabling the maskable interrupts by means of an instruction until the sensitive parts of the program are completed. The interrupt line can then be enabled. There are 3 possible modes of INT response by the Z-80, each selectable by the user. The most powerful and therefore the most popular is the MODE 2 response. When the Z-80 is operated in this mode, the program maintains a table of 8 bit starting addresses for every interrupt service routine in memory. The CPU I register is loaded with the 8 high order address bits of the table by the program. When an interrupt is accepted by the CPU, the low order bits are supplied by the interrupt controller. The high and low order bits form a pointer which points to one of the service routine starting addresses in the table according to the low order address bits.

The CPU then obtains the starting address from the pointed to location in the table, jumps to that address, and executes the service routine that begins at that location. The table can be changed at any time by the program if it is stored in RAM, allowing different service routines for the same peripheral.

3.3.3 Interrupt Enable

There are 2 enable flip-flops (IFF1 and IFF2) in the Z-80 to take care of the status of the maskable interrupt. The state of IFF1 is used to enable and disable the INT line of the Z-80 while IFF2 acts as a storage latch for the state of IFF1 under certain circumstances. When IFF1 is set, interrupts are enabled. When IFF1 is reset, interrupts are inhibited. If the CPU is RESET, both flip-flops are reset and interrupts are ignored. The instruction EI (Enable Interrupts) changes the state of both flip-flops and interrupts are enabled. DI resets both flip-flops and then interrupts are disabled.

When an EI instruction is encountered by the CPU, any pending interrupts will not be accepted until after the instruction following EI has been executed. This prevents any trouble should the next instruction be a RETURN which must be executed before any interrupts are allowed. Both IFF1 and IFF2 are reset when the CPU accepts an interrupt, inhibiting further interrupts until the CPU encounters another EI instruction.

When dealing with maskable interrupts, the state of IFFl and IFF2 is always equal. The function of IFF2 is to save the status of IFFl when an NMI is accepted by the CPU. This resets IFFl only, preventing further interrupts until the EI instruction is executed. After the NMI is serviced, executed instructions may cause the content of IFF2 to be examined, tested, or copied into IFFl in accordance with executed instructions so that the complete state of the CPU before the NMI occurred can be restored.

3.3.4 Interrupt Control

Interrupt control is handled by the Counter/Timer and Parallel I/O unit (CIO). The CIO is a multi-function device containing 2 general purpose 8 bit bidirectional parallel ports, 1

special purpose 4 bit port, 3 counter/timers, pattern recognition logic and several assorted registers.

The CIO prioritizes the interrupt requests from items on the S-100 bus and from its internal parts that might be programmed to cause an interrupt in response to some condition (counter/timers, for example). The Asynchronous Serial Communications Controller (ASCC) looks after the 2 serial ports and may need to interrupt the CPU from time to time in response to some condition on the serial channels. Conflicts between interrupt requests from these 2 devices are resolved through a daisy chain arbitration procedure.

3.3.4.1 Off-Board Interrupt Prioritization

Service for the 8 vectored interrupt lines from the S-100 bus is implemented through the general purpose 8 bit parallel port B of the CIO. The 8 lines from the bus are applied to the parallel port for prioritization. When a request for interrupt service is received from a device on the bus, the pattern recognition area of the CIO determines which interrupt line was activated and causes the CIO to generate a unique vector for each of the 8 interrupt lines from the S-100 bus and place the vector on the lower 8 lines of the address bus when the CPU accepts the interrupt.

At initialization, the CIO is loaded with a vector starting location. Each interrupt line on the bus, if activated, causes a data word with a unique offset from this starting point to be generated by the internal CIO logic and applied to the low order lines of the address bus upon acceptance of the interrupt request by the CPU. These 8 bits, together with the high order 8 bits supplied from the Z-80 I register, form a 16 bit pointer. This pointer indicates a unique service routine starting address in a table. The CPU reads the starting address from the table and jumps to that location to begin execution of the interrupt service routine specific to the interrupt line activated on the bus.

3.3.4.2 On-Board Interrupt Prioritization

The CIO can generate interrupts based on the condition of the other 8 bit parallel port (A) or any of the 3 on-board counter/timers. Each of these items has a register for holding the starting value for vector generation. When activated, internal logic generates a unique offset from this starting value for each origin of the interrupt request and applies this data to the lower 8 lines of the address bus. Data in other registers and additional logic determine the priority of each of these items.

These items and functions are accessible to the user (programmer) and, through implementation, allow the overall function of the CIO to be radically altered to fit almost any special application. All the functions, modes of operation, and features of the CIO are selected, programmed, and exploited via the programming of the CIO. This is normally done by the monitor firmware at power up initialization, but the CIO can be dynamically reconfigured easily by the Operating System (OS) and applications program as required during the execution of programs.

3.3.4.3 On-Board Interrupt Arbitration

There is an arbitration procedure to decide which on-board device will be serviced by the CPU when requests for interrupt service are received from more than one peripheral at the same moment. The CIO controls and prioritizes interrupts requested by items on the bus (8 or maybe more) and may be configured to generate interrupts based on other criteria as well (counter/timer results, etc.). The ASCC controls communication with the outside world through the 2 serial ports. These are the only sources of interrupts to the CPU that are generated in response to events occurring off the board.

Each device capable of pulling the CPU interrupt line down in response to a request for an interrupt from a peripheral (on the bus or external to the system) is provided with priority arbitration logic. There are 2 pins on each of these devices that allow priorities to be set and disputes settled. One is the Interrupt Enable Input (IEI) and the other is the Interrupt Enable Output (IEO).

The design of the system determines the priority of each interrupt control device on the board, and the board is etched accordingly. The IEI (input) line of the highest priority device is tied directly to the positive power bus (permanently logic high). The IEO (output) line of the highest priority device is connected to the IEI line of the next highest priority device whose IEO line is connected to the IEI line of the next highest priority device and so on. This forms the daisy chain.

The Interrupt Acknowledge (INTACK*) line is connected to all devices on the arbitration daisy chain and signals that the CPU has accepted the interrupt and is ready for the daisy chain to determine which device has priority. This signal also causes the winner of the arbitration to apply the vector to the address lines. When the current interrupt service is complete, the interrupt acknowledge line goes inactive and the CPU continues with the task suspended by the interrupt.

There are several internal registers in the CIO--Interrupt Pending (IP), Interrupt Under Service (IUS), and Interrupt Enable (IE)--that the CPU can set or reset to enable or disable the interrupt initiating ability of the device. There is also a Master Interrupt Enable (MIE) register that enables or disables the entire device with a single bit. The contents of these registers reflect the condition of the device. When a device needs to pull down the CPU INT line to initiate an interrupt service routine, it must first examine the status of its internal control registers. If it finds that it has an interrupt pending (IP bit high), that the device is enabled (MIE and IE bits high), and that there is not another interrupt under service (IUS bit low), then the IEI line is examined.

If the device contains several possible sources of interrupts (as does the CIO), an internal daisy chain determines interrupt priority. The internal daisy chain is the same sort of arrangement as the external one. The IEI line must be high for a device (or part of a device) to assume it has the highest priority. Once the internal prioritization is determined, the device inspects the IEI line to the device.

If the IEI line is high, it assumes it has highest priority of all devices needing an interrupt at that moment; and, if all other conditions are met, it initiates an interrupt by pulling down the INT line to the CPU. If the INT function of the CPU is enabled, the CPU will accept the interrupt and return an INTACK* signal.

The INTACK* signal is applied to all devices in the daisy chain, causing every device that meets the conditions required to request an interrupt (enabled, IP set, etc.) to send a low out its IEO line to disable all devices of lower priority. Each IEO is the IEI to the device having the next highest priority in the daisy chain. Each device thus passes this low to the next device on the chain and so on down to the end of the chain.

When the chain settles, only 1 device will have its IP bit set high (indicating need to initiate an interrupt) and its IEI line high (indicating it is the highest item in chain requesting interrupt). This device wins the arbitration, applies its vector to the bus, and has its interrupt serviced by the CPU.

The highest priority device will always have a logic high on its IEI (it is wired to logic high); so when it is enabled and its IP bit is set, it will always win the arbitration. The highest priority device on the SBC-300 is the CIO and the next (last) item in the chain is the ASCC. This ranking is determined by the board etch layout and is fixed.

3.3.5 Interrupt Acknowledge (INTACK*)

The INTACK* signal is derived from the M1* and MREQ* lines from the CPU. The Z-80 examines the INT line at the rising edge of the last clock cycle at the end of each instruction. If the CPU finds the INT line active and it has been enabled by the software, it generates a special M1* cycle consisting of the activation of the M1* line and then the IOREQ* line (instead of the MREQ*). This combination, or rather the combination of the M1* signal and the **absence** of the MREQ*, is decoded by the logic of the interrupt acknowledge area to produce the INTACK* signal. During normal processing, this combination will never occur.

INTACK* is applied to the on-board interrupt controllers (CIO and ASCC) to indicate that priority arbitration should begin, the winner applying the low order vector to the address lines, and to lock out any additional interrupt requests from those locations. The CPU releases the INTACK* line after it has completed the interrupt service routine and is ready to continue processing or accept another interrupt.

3.4 MAPPER CONCEPTS

The 16 address lines of the Z-80 allow it to address or "see" only a 64K page of memory. This 64K page can be thought of as a window 64K high that the Z-80 can look through. The Z-80 cannot see out above or below this window--only through it-and considers the address of the lowest location visible through the window to be 0 and the address of the highest location visible through the window to be 64K (65,535). To access locations that are visible through the window, the Z-80 will generate an address accordingly (0 through 65,535).

The memory mapper allows the repositioning (moving up or down) of this 64K window in 4K increments so that the Z-80 can see into any area of the installed memory. This means that the 64K of memory that the Z-80 can see and address through the window can physically be anywhere in the installed memory beginning at a 4K boundary. When the 64K page is moved about, it always comes to rest with the beginning address that the Z-80 can see (0) at some multiple of 4K (4K, 8K, 256K, 1M, etc.) in the system memory and the highest address that the Z-80 can see, 64K higher.

If, for example, a 1Mbyte (1,048,576 bytes) memory board is installed on the bus, the SBC-300 on-board 64K of RAM might be assigned to address 0 through 65,535 and the 1Mbyte board to address 65,536 through 1,114,111 (1Mbyte+64K). In this situation, there are now 1,114,110 bytes of contiguous logical and physical memory extending from 0 to 1,114,111. But as far as the Z-80 is concerned, there is only 64K out there--it can only see a 64K block through its window.

The mapper, under direction of the monitor firmware or the OS, can move the 64K window that the CPU looks through to any area of the installed memory. The lowest location that the Z-80 can see and address through the window will be located at a 4K boundary and is considered by the Z-80 to be location 0. So, in the example, if the mapper moves the window up into the memory board area, to begin at 81920 (64K+16K), a 4K boundary, the Z-80 can directly address all physical memory between 81,920 and 147,455. Even though this area begins far above the addressing capabilities of an unaided Z-80, it is still only a 64K range which is exactly defined by the 16 bit physical addressing of the Z-80 (0 to 65,535). It is very unlikely that a greater range of memory will need to be addressed at any one time. However, the versatility of the mapper is such that if a greater range is required, the window can be moved to different locations between memory accesses, thereby simulating a 16Mbyte range. The implementation and efficiency of this operation is dependent on the characteristics of the monitor firmware, OS, and application program.

The end result of using the memory mapper is similar to that obtained by a page select. Both allow different areas of a large memory to be accessed by the limited addressing capability of an 8 bit CPU. The main difference is in the implementation and flexibility of the 2 methods. The page select brings pages of memory into the range of the CPU by changing the addresses of the selected block to coincide with the addressing range of the CPU. As a new block is paged in, the block that was previously in the addressing range of the CPU is paged out.

Memory mapper operation simulates the addressing abilities of many 16 bit processors. The mapper creates a real 24 bit address on the S-100 address lines corresponding to the location of the desired area of memory instead of just moving a block of memory into and out of the addressing range of the CPU. Using a mapper is somewhat faster than page selecting, and the physical and logical addresses of all memory elements on the bus are never manipulated by the mapper and remain constant.

When the mapper is being used to generate an address beyond the 64K capability of the Z-80, its operation is completely transparent to the CPU on the SBC-300 board and all other items on the bus.

THIS PAGE INTENTIONALLY LEFT BLANK

este 14k in manifile, of che 7-10, ave magneta va address beruht tie 14k in manifile, of che 7-10, ave messation 14 che fielelle from av 10, but

SECTION IV OPERATIONS

4.0 GENERAL

The SBC-300 can be configured to operate in several different bus modes. It can be configured to operate in accordance with the IEEE-696 bus specification or, through the use of jumpers, can be used with older systems which do not conform to the IEEE-696 specification.

4.1 INSTALLATION

4.1.1 IEEE-696

The SBC-300 can be configured to operate as either the bus master or a bus slave as specified by the IEEE-696 specification. Refer to the Appendix called Jumper Connection Quick Reference Tables for the standard jumper configurations.

4.1.2 SDSystems S-100 And Others

To configure the SBC-300 to run with older SDSystems boards (EXPANDORAM III, VERSAFLOPPY II, VDB-8024), first jumper the board as a bus master (see the Appendix called Jumper Connection Quick Reference Tables). Then change jumper W6 to be on pins 2 and 3 (lower position). This connection jumpers the system clock (Ø1) to bus pin 25 (pSTVAL*) and allows proper operation.

4.1.3 Initial Checkout

After setting the jumpers and configuring the serial port, the address switch must be set. The address switch selects which 128K block the master resides in (64K block for a slave). The 8 position dip switch corresponds to the 8 most significant bits of the 24 bit extended address bus. Up is a logic 0 and down is a logic 1 when reading the switches. The leftmost switch (S1) is the LSB (A16).

	A16							A23	
Set to address 01XXXXH (H=Hex;	*	*	*	*	*	*	*	*	ON OFF
X=Don't care)	LSB							MSB	

Figure 4-1. ADDRESS SWITCH

Next, insert the SBC-300 into the bus and either connect a serial terminal to J2 or insert an SDSystems VDB-8024 board into the bus (the Monitor will talk to either one). Apply power to the system and observe the sign-on message.

SDSYSTEMS SBC-300 MONITOR Vx.x

Figure 4-2. SIGN-ON MESSAGE

After the sign-on message is displayed, the Monitor performs a nondestructive RAM test of all the on-board RAM and either returns the Monitor prompt (.) or an error message giving the bad memory location.

MEMORY ERROR aaaa bb cc

aaaa = memory address, bb = data written, cc = data read

Figure 4-3. MEMORY ERROR MESSAGE

4.2 SERIAL I/O

The serial ports (J5 and J6) can be configured to appear as Data Terminal Equipment (DTE) or Data Communications Equipment (DCE) through the installation of a 16 pin dip header in the proper location.

During initialization the SBC-300 monitor checks serial port B (I/O connector J2, jumper J5) for a terminal or the bus for a VDB-8024 board. The SBC-300 responds to whichever type of terminal communicates first.

To talk to a standard RS-232 terminal, J5 must have a header installed with a minimum of pins 1-16 and 2-15 connected. This connects transmit and receive data together and will allow most terminals to communicate with the SBC-300. The SBC-300 does not require any of the handshake signals (RTS, CTS, DSR, DTR) to be connected to function. However, some terminals may require certain of these lines to be active so that these signals are available at the header for the user to jumper as desired.

4-2

BECTION V MONITOR

5.0 GENERAL

The SDSystems Monitor for the SBC-300 must be ordered to support the specific disk controller used. Contact SDSystems for available Monitors.

The SD Monitor program was developed by SDSystems to assist the SBC-300 user in software and hardware debug. Commands are included to provide control and testing of memory and input/output ports. Software debug is aided with breakpoint, single step, and register examine commands. Additionally, when using the VERSAFLOPPY II or VFW-III disk controller board, commands are provided to support reading and writing to disk from memory and booting up a floppy disk based operating system.

5.1 SD MONITOR START-UP

The SD Monitor start-up is as follows:

1. Power on or depress system reset.

2. Response:

SDSYSTEMS SBC-300 MONITOR V2.0

(3-4 second pause while RAM memory test executes. The address of any memory location which fails the test is printed followed by the test byte and memory byte.)

3. Reply:

The operator may proceed to use any or all of the SD Monitor commands as described in this document.

4

NOTE: On start-up the Monitor program will accept input from either an SDSystems VDB-80.24 or a 9600 baud serial device connected to the SBC-300 serial port B (i.e. connector J2 at top left center of board). The source from which the first input is received will be recognized as the console device until the next system reset occurs.

5.1.1 Command Syntax

Each SD Monitor command is initiated by entering an alpha letter (see Table 5-1) followed by optional hexadecimal operands. The number of operands varies and when there are more than one, each must be separated by a space or a comma. Note, however, that a space is automatically inserted when the command letter is keyed in and the user must not enter a space before the first operand.

Table 5-1. SD MONITOR COMMAND SUMMARY

	Command	Description
A	nbbb	Map the bbbth 4K memory block in 16Mbyte address space to Z-80's n th 4K memory block
B	8888	Set breakpoint at aaaa
c	n	Boots up operating system from disk unit n
D	aaaa bbbb	Display memory from aaaa to bbbb
E	aaaa	Examine memory at aaaa
F	aaaa bbbb dd	Fill memory from aaaa to bbbb with dd
G	a aaa	Go to program at aaaa
B	aaaa bbbb	Bex sum and difference
I	pp nn	Input from port pp, nn times
J	aaaa bbbb n	Test RAM pages aaaa through bbbb in the 16Mbyte address space of the 16Mbyte memory using the Z-80s nth 4K memory block
L	aaaa bbbb cco ccl ccn	Locate string in memory from aaaa to bbbb
M	aaaa bbbb cccc	Move memory block from aaaa to bbbb to block starting at cccc
0	pp đđ nn	Output dd to port pp, nn times
P	PP	Examine port pp
R	aaaa fd tt ss nn	Read from disk to memory at aaaa
5	aaaa nn	Single step at aaaa, nn times
T	aaaa bbbb	Test RAM from aaaa to bbbb
V	aaaa bbbb cccc	Verify (Compare) memory blocks
W	aaaa fd tt ss nn	Write data to disk from memory
x	ab	Examine CPU registers (map)
¥	aaaa bbbb	Yank a hex file into memory
Z	fd n	Format a disk (f=format, d=unit, & n=skew factor)

26

);

When entering an operand, only hexadecimal characters (0-9, A-F) are accepted. If a non-hex character is entered, a question mark (?) is printed and the command is aborted. If, while entering an operand, a wrong number is entered, the user may start over, as only the **last 4 digits** of an operand are used. **Leading zeroes** are assumed if less than 4 digits are entered. Alpha characters may be upper or lower case.

Examples:

.B 6A defaults to 006A (Hex). .B 123456 defaults to 3456 (Hex).

All command lines are terminated with a carriage return (<cr>) which causes the command to execute. To abort a command before the carriage return (<cr>), enter a period (.).

5.2 MEMORY COMMANDS

The SD Monitor contains nine (9) system memory commands providing: memory management, display, modification, block fill, extended memory test, string location, block move, Random Access Memory (RAM) test and block comparison.

5.2.1 Memory Management - "A" Command

SYNTAX .A naaa mbbb ... qeee

Where each of n, m, ...q is the most significant digit of a Z-80 4 digit hex address, and each of aaa, bbb, ...eee is the most significant half of a 16Mbyte 6 digit hex address.

The purpose of the "A" command is to manage memory in blocks of 4K bytes.

Although the Z-80 can address only 64K bytes (i.e. 16 4K blocks) of memory, the SBC-300's memory management capability allows access to 16Mbytes. In order to make this 16Mbytes of memory accessible to the Z-80 microprocessor, sections of the 16Mbyte address space are mapped into the Z-80 64K address space in blocks of 4096 bytes.

The first 64K of the 16Mbyte space (000 000 thru 00f fff) is reserved for the SBC-300 on board ROM. The second 64K (010 000 through 01f fff) addresses the SBC-300 on board RAM.

A maximum of 10 operands can be entered on a single command line.

Note that the 4K blocks need not be continuous or unique.

Example:

.A 1040 305f

After executing the above Monitor command, a memory reference by the Z-80 to location lnnn will actually access location 040nnn in the 16Mbyte memory space; and, similarly, the Z-80 will see 05fnnn in the 16Mbyte as its memory address 3nnn.

NOTE: Extended memory addressing is effective only to the extent that it is recognized by a memory device. That is, given a memory device with 16 bit addressing capability, the above Monitor command would make memory location f001 of the memory device accessible to the Z-80 as address 3001 and, similarly, 0fff as 1fff.

> In addition, alternate memory management techniques used by other memory devices are not directly affected by the SBC-300's memory management capability. The SDSystems Expandoram III memory board, for example, is a memory device which is limited to a 16 bit address, but which has 256K bytes of RAM, the 256K bytes of RAM being accessible by a bank select via an I/O port. Whichever memory section of the Expandoram III is currently selected is the memory that the SBC-300's memory management will access. Since the Expandoram III is a 16 bit addressable device, any 24 bit address will access it unless no bank is selected (i.e. a bank which does not exist is selected). Note, however, that a 24 bit memory address will access only the Expandoram III if the address is not valid for any other memory devices on the bus.

5.2.2 Memory Display - "D" Command

SYNTAX .D aaaa bbbb <cr>

Where aaaa is the hexadecimal value of the memory address to start displaying from, and bbbb is the optional end address. If bbbb is omitted, 256 bytes are displayed starting at aaaa.

When the specified memory is displayed, the Monitor waits for the user to enter a "space" to display the next 256 bytes or a period (.) to return to the SD Monitor command mode.

The memory is displayed 16 bytes per line, hexadecimal and ASCII form, with the starting address (hex) at the beginning of each line. The ASCII output displays periods (.) for all non-printable characters.

The space bar can be used to toggle a pause in execution.

If the user wishes to terminate a display before completion, a period (.) is entered to return to the SD Monitor command mode.

5.2.3 Examine Memory - "E" Command

SYNTAX - .E aaaa <cr>

Where aaaa is the hexadecimal memory address at which the user wishes to begin examination and/or modification.

. Der bier bies imr bies imr bies wer wer ann bies imr bies imr bies mer bies imr bies imr ber bir bie

The purpose of the "E" command is to print the memory address and data for user examination. The user may then enter new data and a carriage return (<cr>) to change the data in that memory location. The Monitor will then advance to the next memory location and display the contents. A period is used at any time to return to the SD Monitor command mode.

The "up caret" (^) is used in lieu of the carriage return after data entry to re-examine the same address allowing verification of the change. If the "up caret" (^) is used without data entry, the previous memory address is examined.

Note that the memory is not altered unless an operand (hex data) is entered before the carriage return or "up caret" (^). If no hex data is entered before the carriage return, the next location is examined. If no data is entered before the "up caret" (^), the previous location is examined.

Note also that if a period (.) is entered after a hex data operand, memory is not altered before returning to the SD Monitor command mode.

5.2.4 Fill Memory - "F" Command

SYNTAX - .F aaaa bbbb cc <cr>

Where aaaa is the starting address, bbbb is the ending address and cc is the fill data.

The purpose of the "F" command is to cause the hex data (cc) to write to every Random Access Memory (RAM) location from aaaa through bbbb.

5.2.5 Extended Memory Test - "J" Command

SYNTAX - .J aaaa bbbb c <cr>

Where aaaa and bbbb are the 4 most significant hex digits of a 24 bit memory address, and c is the most significant hex digit of a 16 bit address.

The purpose of the "J" command is to perform a modified incrementing memory test on a range of 256 byte pages anywhere in the SBC-300's 16Mbyte address space. aaaa is the address of the start page, and bbbb is the address of the end page. If not entered, bbbb defaults to aaaa.

In order to test a section of the 16Mbyte memory, the Z-80 needs to map the section into its address space. The c parameter specifies the 4K memory region for the Z-80 to use. c defaults to 1 (i.e. the Z-80 addresses 1000 through lffff will be used to map in sections of the 16Mbyte memory for testing. If specifying a value for c, do not use any of the blocks occupied by the Monitor program (i.e. blocks e and f if using a 4K Monitor, blocks d, e, and f if using an 8K Monitor).

All errors are reported to the console with the 6 digit hex memory address, data written, and data read back being displayed for all bad locations.

At the end of each pass through the range specified, a "P" is displayed on the console.

At any time during the test, the space bar can be used to toggle a pause in execution.

A period (.) must be entered to terminate the test.

NOTE: After execution of a "J" command, the mapped state of the Z-80 4K address space used for the test is unknown.

5.2.6 Locate String - "L" Command

SYNTAX - .L aaaa bbbb cc0 cc1 cc2....ccn <cr>

Where aaaa and bbbb are hex memory addresses and cc₀ through cc_n are single byte hex data values.

The purpose of the "L" command is to search memory starting at aaaa and ending at bbbb for the string (up to 6 bytes) specified by the hex values cc_0 through cc_n .

Each time the string is located, the address of the first byte is printed on the console, followed by the first 16 bytes of data found at that address in hexadecimal and ASCII.

The space bar can be used to toggle a pause in execution.

The search is terminated at any time by entering a period (.) on the console.

5.2.7 Move Memory - "M" Command

SYNTAX - .M aaaa bbbb cccc

Where aaaa, bbbb and cccc are hexadecimal memory addresses.

The purpose of the "M" command is to cause the memory block starting at address aaaa and ending at address bbbb to copy to the memory block starting at cccc. bbbb must be greater than aaaa.

5.2.8 Memory Test - "T" Command

SYNTAX - .T aaaa bbbb <cr>

Where aaaa and bbbb are hexadecimal memory addresses.

The purpose of the "T" command is to perform a modified incrementing memory address test on the Random Access Memory (RAM) starting at aaaa and ending at bbbb.

All errors are reported on the console with the memory address, data written and data read back being displayed for all bad locations.

At the end of each complete pass on the specified memory block, a "P" is displayed on the console.

At any time during the test, the space bar can be used to toggle a pause in execution.

A period (.) must be entered to terminate the memory test.

5.2.9 Verify Memory - "V" Command

SYNTAX - .V aaaa bbbb cccc <cr>

Where aaaa, bbbb and cccc are valid hexadecimal memory addresses and bbbb is greater than aaaa. The purpose of the "V" command is to compare the memory block starting at aaaa and ending at bbbb with the memory block starting at cccc.

Any differences in the memory blocks are reported on the console with the first block address with data followed by the second block address with data.

The space bar can be used to toggle a pause in execution.

The verification is terminated by entering a period (.) at any time.

5.3 INPUT/OUTPUT COMMANDS

The SD Monitor contains 3 commands for reading and writing to input and output ports: "I" command for input from ports, "O" command for output to ports and "P" command for port examination.

5.3.1 Input From Port - "I" Command

SYNTAX - .I pp nn <cr>

Where pp is the input port address and nn is the number of times the port is read.

The purpose of the "I" command is to read the input port "pp" and display the data nn times. If "nn" is omitted, the default is one (1) read. If "nn"=0, the port is continuously read and displayed until a period (.) is entered to terminate the operation. The space bar can be used to toggle a pause in execution.

5.3.2 Output From Port - "O" Command

SYNTAX - .0 pp dd nn <cr>

Where pp is the port address, dd is the data to output, nn is the number of times to output the data.

The purpose of the "O" command is to write the data defined by dd to port pp. The data is written the number of times defined by nn. If nn is omitted, the default is one (1). If "nn"=0, the data is continuously written until a period (.) is entered to terminate the operation. The space bar can be used to toggle a pause in execution. 5.3.3 Port Examine - "P" Command

SYNTAX - .P pp <cr>

Where pp is the hexadecimal port number (address) to begin examining and/or modification.

After the command is entered, the specified input port address and data are printed. The user may then enter new data and a carriage return (<cr>) to change the data in that input/output port. The monitor will then advance to the next input/output port number and display the contents. A period can be entered at any time to return to the SD Monitor command mode.

The "up caret" (^) may be used in lieu of the carriage return after data entry to re-examine the same input/output port. If the "up caret" is used without data entry, the previous input/output port is examined.

Note that the port is not altered unless an operand (hex data) is entered before the carriage return or "up caret" (^). If no hex data is entered before the carriage return, the next input/output port is examined. If no hex data is entered before the "up caret" (^), the previous input/output port is examined.

Note also that if a period (.) is entered after a hex data operand, the input/output port is not altered before returning to the SD Monitor command mode.

5.4 PROGRAM CONTROL COMMANDS

The SD Monitor provides several commands designed to facilitate rapid Z-80 software development.

The user has total control of all the Z80 Central Processing Unit (CPU) registers via a register map in memory. This map is loaded into the Z-80's registers each time a program is executed from the monitor. Conversely, each time a breakpoint is encountered, the Z-80 CPU registers are saved in the register map and displayed on the console.

During single step operation, the registers are loaded and saved in between each instruction step.

The user may also set up the register map using the "E" command. Table 5-2 contains the memory addresses of each of the Z-80 registers in the map.

All of the register map is preserved through system resets except for the Stack Pointer (FFE6-FFE7), the Interrupt Enable Flag (FFFA) and the Program Counter (FFFE-FFFF).

Memory Address (Hex)	Register	Description
FFE6	SP (LSB)	Stack Pointer Lower Half
FFE7	SP (MSB)	Stack Pointer Upper Half
FFE8	IY (LSB)	Index Reg IY Lower Half
FFE9	IY (MSB)	Index Reg IY Upper Half
FFEA	IX (LSB)	Index Reg IX Lower Half
FFEB	IX (MSB)	Index Reg IX Upper Half
FFEC	L'	Alternate L
FFED	H ¹	Alternate H
FFEE	E	Alternate E
FFEF	D	Alternate D
FFFO	C	Alternate C
FFF1	B	Alternate B
FFF2	F'	Alternate Flags
FFF3	A'	Alternate A
FFF4	L	L Register
FFF5	H	H Register
FFF6	E	E Register
FFF7	D	D Register
FFF8	C	C Register
FFF9	B	B Register
FFFA	IF	Interrupt Enable Flag (04=enabled)
FFFB	I	I Register
FFFC	F	Flags
FFFD	A	A Register
FFFE	PC (LSB)	Program Counter Lower Half
FFFF	PC (MSB)	Program Counter Upper Half

Table 5-2. SD MONITOR REGISTER MAP

5.4.1 Breakpoint - "B" Command

SYNTAX - .B aaaa <cr>

Where aaaa is the address at which to insert the breakpoint.

The purpose of the "B" command is to insert a software breakpoint in the user's RAM based program. The breakpoint consists of a 3 byte jump instruction replacing the user's code at the specified address. If "aaaa" is omitted, any existing breakpoint is removed.

When the breakpoint is encountered, the user's code is restored and the CPU registers are displayed on the console. The monitor then enters the single step mode and the user may proceed as discussed under Single Step, Subsection 5.4.3, or may enter a period (.) to return to the monitor command mode. The monitor only tracks one breakpoint at a time. If a breakpoint is inserted while another is still in memory, the previous one is automatically removed before inserting the new one. Note that this results in single step execution also removing any existing breakpoint.

If the user inserts a breakpoint and a system reset occurs without the breakpoint having been executed or removed, the breakpoint will still be imbedded in the user's code. In this case, the monitor will not remove the breakpoint or restore the user's code unless the breakpoint is flagged by writing a Ol to location ffc0 (the "E" command may be used to do this). The breakpoint will then be removed by either executing it or by using the monitor "B" or "S" commands. Alternatively to flagging the breakpoint, the user may, of course, restore his code manually either by using the "E" command or by moving it back to the breakpoint address from locations ffcl-ffc3.

5.4.2 "GO" To Program - "G" Command

SYNTAX - .G aaaa <cr>

Where aaaa is the hexadecimal address at which the user wishes to begin execution.

The purpose of the "G" command is to begin execution of a program anywhere in memory (aaaa).

When the "G" command is entered, the Random Access Memory (RAM) register map is loaded into the Z-80's registers before executing the address aaaa.

A program is resumed after a breakpoint (or single step) by omitting the aaaa. This causes execution to begin at the address defined by "PC" in the register map (as displayed by "X" command).

5.4.3 Single Step - "S" Command

SYNTAX - .S aaaa nn <cr>

Where aaaa is the address to begin stepping and nn is the number of steps to trace.

The purpose of the "S" command is to single step through Random Access Memory (RAM) based programs, displaying all the CPU registers after each step. If the nn is omitted, the default value is 1. If the aaaa is omitted, the default value is the previous "PC" loaded into the Random Access Memory (RAM) register map either by a breakpoint, the memory examine "E" command, or a previous single stepping sequence. When the "S" command is entered, the Z-80 registers are displayed with the registers labeled over each column. The user may then step 1 instruction by entering a carriage return. If the user enters a "space," the Monitor steps 11 steps along with a heading and register display. The user must enter a period (.) to return to the SD Monitor command mode.

The space bar can be used to toggle a pause in execution.

Once back in the SD Monitor command mode, all commands may be used. Single stepping is resumed at the address left off by entering "S <cr>" with no operands.

5.4.4 Register Examine - "X" Command

SYNTAX - .X a b <cr>

Where "a" is the heading print option and "b" is the length option.

The purpose of the "X" command is to examine the Random Access Memory (RAM) register map at any time.

If "a" is omitted, the registers are displayed without a label heading.

If "a" is non-zero, a label heading is printed above the registers.

If "b" is entered, it sets the register display length.

If b=0, it sets the display to short mode; if b=1, it sets the display to the long mode (short mode only displays "PC" and "AF"). This effects breakpoint and single step in addition to the "X" command.

The display mode remains set until the "X" command is used to change it.

Note that if "b" is omitted, the display mode is not altered.

The user must remember also that the Random Access Memory (RAM) register map is only altered by a breakpoint, single step or manual changes via the "E" command.

5.4.5 Hex Arithmetic - "H" Command

SYNTAX - .H aaaa bbbb <cr>

Where aaaa and bbbb are any 2 hexadecimal numbers.

The purpose of the "H" command is to display the hexadecimal sum and difference of aaaa and bbbb. The sum aaaa + bbbb is displayed first preceeded by a "+." The difference (aaaa bbbb) is displayed second, preceeded by a "-."

5.4.6 Command Processing - "Y" Command

SYNTAX - .Y aaaa bbbb

Where aaaa is the optional override load address and bbbb is the optional byte count.

The purpose of the "Y" command is to provide a means of loading intel hex data from dart port a into memory starting at the address specified by the incoming data stream and (optionally) loading a specified number of bytes.

5.5 DISK UTILITY COMMANDS

The SD Monitor provides several commands that are useful in a disk based system. These commands are only operative when a VERSAFLOPPY II or VFW-III disk controller board is present in the SDSystems microcomputer.

These commands operate on both mini and standard drives. All parameters relating to drive type are contained in the SBC-300 PROM.

5.5.1 Boot Up - "C" Command

SYNTAX - .C a <cr>

Where a is the drive number 0 through 3.

The purpose of the "C" command is to boot up a floppy disk operating system from the specified drive. If the drive number is not specified in the SD Monitor .C command, it defaults to 0.

NOTE: A compatible disk operating system diskette must be in the defined drive before entering this command.

Once the boot up is complete, the SD Monitor is exited and the disk operating system is activated causing the associated prompt to display on the console.

If nonrecoverable errors are encountered, the message COLD BOOT ERROR is displayed and the user is returned to the Monitor command mode.

5.5.2 Read From Disk - "R" Command

SYNTAX - .R aaaa fd tt ss nn

LICH STREETS STR

Where aaaa is a valid RAM memory address, f is the format type (see Table 5-3), d is a valid drive number, tt is a valid track number (base 0), ss is a valid sector number (base 1) and nn is the number of sectors to read into memory (up to FF). All parameters are required.

The purpose of the "R" command is to provide a means of reading data starting at the specified drive, track and sector into the RAM buffer (starting at aaaa). The number of bytes is determined by nn times the sector size.

	Numberly phones	Bit		
at these at	al final zerter	£	đ	
	Format Code	7 6 5 4	3 2 1 0	
	Unit No. Not Used No. of Sides Size (8" or 5") Sector Size	x x x x	XX XX	
Unit No.	No. of Si	des Size	Sector	Size
00 = 0 01 = 1 10 = 2 11 = 3	0 = Single 1 = Double	sided 0 = 8" sided 1 = 5"	01 = 250 10 = 512	6 bytes
EXAMPLES:		and an balle		
Code 23 (0) Code 32 (0)	$001 \ 0000) = 8^{\circ} dc$ $010 \ 0011) = 5^{\circ} si$ $011 \ 0010) = 5^{\circ} dc$ $100 \ 0001) = 8^{\circ} si$	ngle sided sin uble sided sin	gle density	unit 3 unit 2

Table 5-3. DISK FORMATS

Code 53 (0101 0011) = 8" double sided double density unit 3

5.5.3 Write To Disk - "W" Command

SYNTAX - .W aaaa fd tt ss nn

Where aaaa is a valid memory address, f is the format type (see Table 5-3), d is a valid drive number (0 to 3), tt is a valid track number (base 0), ss is a valid sector number (base 1), and nn is the number of sectors to be written from memory (up to FF). All parameters are required.

The purpose of the "W" command is to provide a means of writing data starting at the specified drive, track and sector from the memory starting at aaaa. The number of bytes written is determined by nn times the sector size.

5.5.4 Format A Disk - "Z" Command

SYNTAX - .Z fd n

Where f is the format type (see Table 5-3), d is a valid drive number (0 to 3), and n is the skew factor.

The purpose of the "Z" command is to provide a means of formatting a disk according to the formats in Table 5-3. The skew factor n, if not specified, defaults to a value of 1.

5.6 CIO INITIALIZATION AND USE

A detailed discussion of programming the CIO chip is beyond the scope of this manual and therefore only a brief discussion of its use is given. A summary of the CIO registers can be found in the Appendix called CIO Specification. The specific initialization code used by version 1.2 of the SBC-300 Monitor can be found in the Appendix called Monitor Locations.

For more detailed information on the 8536, see the Zilog publication "Z8036 Z-CIO/Z8536 CIO Counter/Timer and Parallel I/O Unit Technical Manual."

5.6.1 Accessing The CIO Internal Registers

Access to the CIO internal registers is via an internal pointer register. Access to the internal pointer register is via the CIO internal state machine logic. The state machine can determine whether accesses to the CIO are via the data ports (SBC-300 ports 78H-7AH) or via the control port (SBC-300 port 7BH). Reads and writes to the data ports do not effect the state of the CIO; those to the control port do. There are three states possible in the CIO: the reset state (which should only be active during a SBC-300 reset), state 0, and state 1. The latter two are the normal operating mode for the CIO.

When in state 0, reads to SBC-300 port 7BH access the CIO register currently addressed by the CIO pointer register and leave the CIO in state 0; writes to port 7BH update the internal CIO pointer register and leave the CIO in state 1. When in state 1, reads or writes to port 7BH access the CIO register currently indicated by the internal register pointer and return the CIO to state 0. Since any read to port 7BH, whether in state 0 or in state 1, always leaves the CIO in state 0, a read can be used to force the CIO to state 0. State 1 suspends many internal CIO operations, especially those related to interrupt generation and control; therefore, the CIO should not be left in state 1.

Note that because the CIO operates as a state machine, it is important that code which accesses the CIO internal registers not be interrupted if the interrupt itself would result in access to the CIO's internal registers. If such an interrupt is possible, the user should disable interrupts at the Z80 during CIO internal register access.

5.6.2 SBC-300 Monitor And CIO Initialization

Version 2.0 of the SBC-300 Monitor program performs minimal configuration on the Zilog 8536 CIO chip. Port A and the counter/timers are left in a post-reset condition, port B is configured as an interrupt controller for the S-100 vectored interrupt lines, and port C is configured in accordance with necessary hardware requirements.

5.6.2.1 Port B

For use as an interrupt controller, port B is configured as a bit port using Or-Priority Encoded Vector pattern recognition. The correspondence of vectored interrupts to port B's data lines follows the CIO's internal prioritization under Or-PEV mode. As data bit D7 is highest priority, it is tied to VIO. Data bit D0 is tied to VI7, D1 to VI6, etc. All port B data lines are set as non-inverting inputs with 1's catchers. Enabling of particular vectored interrupts is controlled by the pattern definition registers, i.e. the Pattern Polarity, Pattern Transition and Pattern Mask registers. For each interrupt line, the settings of its respective bit in these registers determine whether the line can generate an interrupt to the CPU and, if so, under what conditions. See Figure 5 in the Appendix called CIO Specification for available configurations.

As is, all the bits in the Pattern Polarity register have been set to 1 by the Monitor and those of the Pattern Transition register to 0. VII has been enabled by writing a 1 to D6 of the Pattern Mask register, while all the other vectored interrupts have been disabled by writing 0's to their respective bits. VII is assumed to be the parity line (PBERR) off the SBC-300 or Expandoram IV. This configuration of the pattern definition registers recognizes a high level on port B data bit D6 as an active interrupt (note that jumper W14-4 must be in place for the SBC-300's on board parity to be seen by the CIO).

Writing a 1 to its respective bit in the Pattern Mask register would enable interrupts for any other particular vectored interrupt line, with a high signal recognized as active. For example, the following Monitor commands would enable VIO:

.I 7B - force CIO to state 0 with read to 7B 7B 40 - prints contents of currently addressed register .0 7B 1 - set pointer register to address register 1 .I 7B - read CIO register 1 7B 90 - prints contents of register 1 (ports B and C are enabled) .0 7B 1 - set pointer register to write register 1 .0 7B 10 - write 10H to register 1 : disable port B by resetting D7 in register 1 (MCC) - set pointer to address register 2F .0 7B 2F .I 7B - read register 2F 7B 40 - prints contents of register 2F (VII is already enabled) .0 7B 2F - set to write register 2f .0 7B CO - write CO to register 1 : enable VIO and VII - set pointer register to address register 1 .0 7B 1 .0 7B 90 - renable port B by setting D7 in MCC register (and also leave port C enabled)

OI	CO	a	0	a	
VL	20	u	c	u	

•••

	dovi0:		; assume CIO is already in state O
	đi		; disable interrupts
		c,7bh	7 7b is the CIO control port
	mvi	D,1	; 1 is the master configuration
			; control
	outp	b	; set access up to register 1
	inp		; read register 1
			J lead legister 1
	ani	7fh	; disable port B by resetting bit D7
	outp	b	; set write to register 1
	outp		; send the new info
2	mv1	b,2fh	; 2f is the pattern mask register

outp	b	set pointer register to read it
inp	8	read it
ori	80h 1	set D7 to enable VIO
outp		Bet up the write to 2f
outp	8	write out the new info
mvi	b,1 1	now go back and reenable port B
outp		set the access
inp	a	read register 1
ori		reenable port B by setting bit D7
outp		set the write access
outp	a	write register 1
ei		reenable interrupts

When an interrupt is received by the CIO on a vectored interrupt line which has been enabled, the CIO will request an interrupt at the 280. When the interrupt is acknowledged by the Z80, the CIO will imbed into bits D3-D1 of the port B interrupt vector the number of the highest priority port B data bit which exhibits a pattern match at the time of the interrupt acknowledge, and will provide this to the Z80 in response to the mode 2 interrupt acknowledge. In conjunction with the 280 I register, the port B interrupt vector points to the service routine addresses for vectored interrupts at memory locations ffl0-fflf. The vectored interrupts are set up with routines which will print a message noting which vectored interrupt occurred, reset the CIO interrupt logic and the respective port B data line l's catcher, display the state of the 280 registers at the time of the interrupt acknowledge, and return the Monitor to command mode. VII has a special routine to handle parity. See Subsection 5.8 for more information on how VIl is handled.

An interrupt can be handled differently by placing the address of the desired service routine into the appropriate word of the port B vector table at ffl0. The interrupt service routine will have to reset the interrupt logic by code similar to that in the Resetting Vectored Interrupts section of the Appendix called Sample I/O Support Code.

5.6.2.2 Port C

Port C is enabled as a bit port with non-inverting data bits: bits D3, D2, D0 output and bit D1 input. D1 must be an input to avoid erratic signals on the parity error line. D3 must not go low or the SBC-300 PROM will be forced active with subsequent loss of control. D2 is held low during Monitor initialization and then set high to enable S-100 bus slaves. D1 is for use when port A is configured as a SASI port.

Note that because of D3, port C must always remain enabled. Thus, the CIO must never be reset via D0 in CIO register 0 (Master Interrupt Control), and port C must never be disabled via D4 in CIO register 1 (Master Configuration Control).

10

5.6.2.3 Port A

Though not done by the Monitor, port A can be configured in conjunction with the SBC-300 parallel I/O data port 70H as either a SASI port or a parallel printer port. See the Monitor Initialization Code section of the Appendix called Sample I/O Support Code.

5.6.2.4 Counter/Timers

The Monitor does not initialize the CIO counter/timers, but space is reserved at ff08-ff0f for a vector table to service the CIO counter/timer interrupts. See the Monitor Initialization Code section of the Appendix called Sample I/O Support Code.

5.7 ASCC INITIALIZATION

Version 1.2 of the SBC-300 Monitor has configured both ASCC serial ports for 9600 baud with 8 data bits, 1 stop bit, and DTR and RTS on. The x16 clock is used, with the baud rate generator enabled from the system PCLK and output to TX and RX clocks. See the Appendix called ASCC Specification for a summary of ASCC registers. Refer to the Zilog publication "Z8030/Z8530 SCC Serial Communications Controller Technical Manual" for more detailed information on programming the ASCC.

5.8 PARITY ERRORS

Version 1.2 of the SBC-300 Monitor handles parity errors through bit D6 of the data port of CIO port B. Under most circumstances, when a parity error is acknowledged, the parity error service routine prints the message "PARITY ERROR" on the console, resets the interrupt logic in the CIO and at the data port of CIO port B, displays the contents of the 280 CPU registers at the time of the interrupt acknowledge, and returns the monitor to the command mode.

There are two conditions under which a parity error is handled differently: during execution of the Monitor "T" test and during execution of the "J" test. If a parity error is acknowledged at the time of the read memory instruction during the verify loop of the test, the message "PARITY ERROR" is displayed at the console followed by the memory address of the location being read at the time of the interrupt. If the error occurs during the "T" test, this memory address is the \$80 four digit hex address of the location being tested. If the error occurs during the "J" test, this memory address is the six digit hex address within the 16Mbyte memory space of the location being tested. If possible, execution of the test then resumes.

Note that removing jumper W14-4 on the SBC-300 will disconnect the SBC-300's on-board parity error line.

THIS PAGE INTENTIONALLY LEFT BLANK

strong testing failers a se pass diffine to the

The Morison does not initiation the 210 counter/disers. but every is the first counter, the state of the state of the decript the first counter, there is the state of the spendic called Empire 1/5

COLUMN TRUE NOTE

Verseien (12 es the 950-200 Wakter handles partiry sroors attended be Df of the Society error is addresinger, the partiry attended to the source print Se accord without state partiry bereast of C10 part 21 dispire logic is the totant of the SE CF action of C10 part 21 dispire logic is the totant of the SE CF action is the time of the intering and the totant of the SE CF action is the time of the intering and a source of the totant of the second of the time of the intering and a source totant of the SE CFD

These while computer coupler wild-d on the SUC-100 will discomment

SECTION VI ENVIRONMENTAL CONSIDERATIONS

6.0 GENERAL

The maximum recommended ambient operating temperature is 50°C (122°F).

6.1 POWER REQUIREMENTS

		8V	+16V	-16V
		and any own has done to him own man and him him has been done		
4	mHz	1.9A	50 mA	50mA
6	mHz	2.1A	50mA	50mA

6.2 PHYSICAL SPECIFICATIONS

The SBC-300 is contained on a multi-layer printed circuit board which conforms to the IEEE-696 specification. The board dimensions are $5.125" \times 10.0"$. No components extend more than 0.50" from the component side of the board or more than 0.125"from the solder side of the board.

THIS PAGE INTENTIONALLY LEFT BLANK

APPENDIX A SELECTED IEEE-696 SPECIFICATION SHEETS

NOTE: For additional information, see the complete document "IEEE Standard 696 Interface Devices."

IEEE-696 Bus Pin List

Pin No.	Signal & Type	Active Level	Description
1	+8 V (B)		Instantaneous minimum greater than 7 V, instantaneous maximum less than 25 V, average maximum less than 11 V.
2	+16 V (B)		Instantaneous minimum greater than 14.5 V, instantaneous maximum less than 35 V, average maximum less than 21.5 V.
3	XRDY (S)	Н	One of two ready inputs to the current bus master. The bus is ready when both these ready inputs are true. See pin 72.
4	VIO* (S)	L OC	Vectored interrupt line 0.
5	VII* (S)	L OC	Vectored interrupt line 1.
6	VI2* (S)	L OC	Vectored interrupt line 2.
7	VI3* (S)	L OC	Vectored interrupt line 3.
8	VI4* (S)	L OC	Vectored interrupt line 4.
9	VI5* (S)	L OC	Vectored interrupt line 5.
10	VI6* (S)	L OC	Vectored interrupt line 6.
11	VI7* (S)	L OC	Vectored interrupt line 7.
12	NMI* (S)	L OC	Nonmaskable interrupt.
13	PWRFAIL* (B)	L	Power fail bus signal.
14	TMA3* (M)	L OC	Temporary master priority bit 3.
15	A18 (M)	Н	Extended address bit 18.

No.	Signal & Type	Active Level	Description
 16	Al6 (M)	Н	Extended address bit 16.
17	Al7 (M)	Н	Extended address bit 17.
18	SDSB* (M)	L OC	The symbol to disable the 8 status signals.
19	CDSB* (M)	L OC	The signal to disable the 5 control output signals.
20	0 V (B)		Common with pin 100.
21	NDEF		Not to be defined. Manufacturer must specify any use in detail.
22	ADSB* (M)	L OC	The signal to disable the address signals.
23	DODSB* (M)	L OC	The control signal to disable the data output signals. (DO7-0 for 8 bit transfers, ED7-0 and OD7-0 for 16 bit transfers.)
24	ø (B)	A	The master timing signal for the bus.
25	pSTVAL* (M)	L	Status valid strobe.
26	phlda (M)	Н	A control signal used in conjunction with HOLD* to coordinate bus master transfer operations.
27	RFU		Reserved for future use.
28	RFU		Reserved for future use.
29	A5 (M)	Н	Address bit 5.
30	A4 (M)	Н	Address bit 4.
31	A3 (M)	Н	Address bit 3.
32	A15 (M)	Н	Address bit 15 (most significant for nonextended addressing).

	Signal	Active Level	
33	Al2 (M)	Н	Address bit 12.
34	A9 (M)	Н	Address bit 9.
35	DOl (M)/EDl (M/S)	Н	Data out bit 1, bidirectional data bit 1.
36	DOO (M)/EDO (M/S)	Н	Data out bit 0, bidirectional data bit 0.
37	Al0 (M)	Н	Address bit 10.
38	DO4 (M)/ED4 (M/S)	Н	Data out bit 4, bidirectional data bit 4.
39	DO5 (M)/ED5 (M/S)	Н	Data out bit 5, bidirectional data bit 5.
40	DO6 (M)/ED6 (M/S)	Н	Data out bit 6, bidirectional data bit 6.
41	DI2 (S)/OD2 (M/S)	Н	Data in bit 2, bidirectional data bit 2.
42	DI3 (S)/OD3 (M/S)	Н	Data in bit 3, bidirectional data bit 3.
43	DI7 (S)/OD7 (M/S)	Н	Data in bit 7, bidirectional data bit 7.
44	sMl (M)	Н	The status signal which indicates that the current cycle is an op-code fetch.
45	SOUT	Н	The status signal identifying the data transfer bus cycle to an output device.
46	sINP (M)	Н	The status signal identifying the data transfer bus cycle from an input device.
47	sMEMR (M)	Η	The status signal identifying bus cycles which transfer data from memory to a bus master, which are not interrupt acknowledge instruction fetch cycle(s).

Pin No.	Signal & Type		tive vel	Description
48	SHLTA (M)	Н		The status signal which acknowledges that a HLT instruction has been executed.
49	CLOCK (B)	A		2 MHz (+0.5%) 40-60% duty cycle. Not required to be synchronous with any other bus signal.
50	0 V (B)			Common with pin 100.
51	+8 V (B)			Common with pin 1.
52	-16 V (B)			Instantaneous maximum less than -14.5 V, instantaneous minimum greater than -35 V, average minimum greater than -21.5 V.
53	0 V (B)			Common with pin 100.
54	SLAVE CLR* (B)	L	oc	A reset signal to reset bus slaves. Must be active with POC* and may also be generated by externl means.
55	TMAO* (M)	L	oc	Temporary master priority bit 0.
56	TMAl* (M)	L	oc	Temporary master priority bit 1.
57	DMA2* (M)	L	oc	Temporary master priority bit 2.
58	SXTRQ* (M)	L		The status signal which requests 16-bit slaves to assert SIXTN*.
59	A19 (M)	н		Extended address bit 19.
60	SIXTN*	L	OC	The signal generated by 16-bit slaves in response to the 16 bit request signal sXTRQ*.
61	A20 (M)	Н		Extended address bit 20.
62	A21 (M)	н		Extended address bit 21.

A-4

Pin No.	Signal & Type	Active Level	Description
63	A22 (M)	Н	Extended address bit 22.
64	A23 (M)	Н	Extended address bit 23.
65	NDEF		Not to be defined signal.
66	NDEF		Not to be defined signal.
67	PHANTOM* (M/S)	L OC	A bus signal which disables normal slave devices and enables phantom slaves primarily used for bootstrapping systems without hardware front panels.
68	MWRT (B)	Н	pWR*-sOUT (logic equation). This signal must follow pWR* by not more than 30 ns.
69	RFU		Reserved for future use.
70	0 V (B)		Common with pin 100.
71	RFU		Reserved for future use.
72	RDY (S)	н ос	See comments for pin 3.
73	INT* (S)	L OC	The primary interrupt request bus signal.
74	HOLD* (S)	L OC	The control signal used in conjunction with pHLDA to coordinate bus master transfer operations.
75	RESET* (B)	L OC	The reset signal to reset bus master devices. This signal must be active with POC* and may also be generated by external means.
76	pSYNC (M)	Н	The control signal identifying ^{BS} 1.
77	pWR* (M)	L	The control signal signifying the presence of valid data on DO bus or data bus.

IEEE-696 Bus Pin List (Continued)

Pin No.	Signal & Type	Active Level	Description
78	pDBIN (M)	Н	The control signal that requests data on the DI bus or data bus from the currently addressed slave.
79	AO (M)	Н	Address bit 0 (least significant).
80	Al (M)	Н	Address bit 1.
81	A2 (M)	Н	Address bit 2.
82	A6 (M)	н	Address bit 6.
83	A7 (M)	Н	Address bit 7.
84	A8 (M)	Н	Address bit 8.
85	A13 (M)	Н	Address bit 13.
86	Al4 (M)	Н	Address bit 14.
87	All (M)	Н	Address bit 11.
88	DO2 (M)/ED2 (M/S)	Н	Data out bit 2, bidirectional data bit 2.
89	DO3 (M)/ED3 (M/S)	Н	Data out bit 3, bidirectional data bit 3.
90	DO7 (M)/ED7 (M/S)	Н	Data out bit 7, bidirectional data bit 7.
91	DI4 (S)/OD4 (M/S)	Н	Data in bit 4 and bidirectional data bit 12.
92	DI5 (S)/OD5 (M/S)	Н	Data in bit 5 and bidirectional data bit 13.
93	DI6 (S)/OD6 (M/S)	Н	Data in bit 6 and bidirectional data bit 14.
94	DIl (S)/ODl (M/S)	Н	Data in bit land bidirectional data bit 9.
95	DIO (S)/ODO (M/S)	Н	Data in bit 0 (least significant for 8 bit data) and bidirectional data bit 8.

Pin No.	Signal & Type	Active Level	Description
96	SINTA (M)	Н	The status signal identifying the bus input cycle(s) that may follow an accepted interrupt request presented on INT*.
97	sWO* (M)	L	The status signal identifying a bus cycle which transfers data from a bus master to a slave.
98	ERROR* (S)	L OC	The bus status signal signifying an error condition during present bus cycle.
99	POC* (B)	L	The power-on clear signal for all bus devices; when this signal goes low, it must stay low for at least 10 microseconds.
100	0 V (B)		System ground.

IEEE-696 Bus Pin List (Continued)

IEEE-696 Bus Layout--Quick Reference

pin l	+8 V (B)		pin 51	+8 V (B)	
pin 2	+16 V (B)		pin 52	-16 V (B)	
pin 3	XRDY (S)	H	pin 53	0 V	
pin 4	VI0* (S)	L	pin 54	SLAVE CLR* (B)	L
pin 5	VIl* (S)	L	pin 55	TMAO* (M)	L
pin 6	VI2* (S)	L	pin 56	TMAl* (M)	L
pin 7	VI3* (S)	L	pin 57	TMA2* (M)	L
pin 8	VI4* (S)	L	pin 58	SXTRQ* (M)	L
pin 9	VI5* (S)	L	pin 59	A19	Н
pin 10	VI6* (S)	L	pin 60	SIXTN* (S)	L
pin ll	VI7* (S)	\mathbf{L}	pin 61	A20 (M)	H
pin 12	NMI* (S)	L	pin 62	A21 (M)	Η
pin 13	PWRFAIL* (B)	L	pin 63	A22 (M)	Н
pin 14	TMA3* (M)	L	pin 64	A23 (M)	Н
pin 15	A18 (M)	H	pin 65	NDEF	
pin 16	A16 (M)	H	pin 66	NDEF	
pin 17	A17 (M)	H	pin 67	PHANTOM* (M/S)	L
pin 18	SDSB* (M)	L	pin 68	MWRT (B)	Н
pin 19	CDSB* (M)	L	pin 69	RFU	
pin 20	0 V		pin 70	0 V	
pin 21	NDEF		pin 71	RFU	
pin 22	ADSB* (M)	L	pin 72	RDY (S)	H
pin 23	DODSB* (M)	L	pin 73	INT* (S)	L
pin 24	ø (B)	H	pin 74	HOLD* (M)	L
pin 25 pin 26	pSTVAL* (M)	L H	pin 75	RESET* (B)	L
pin 27	pHLDA (M) RFU	п	pin 76 pin 77	pSYNC	HL
pin 27 pin 28	RFU		pin 77 pin 78	PWR* (M) pDBIN (M)	H
pin 20	A5 (M)	H	pin 78 pin 79	AO (M)	Н
pin 30	A4 (M)	H	pin 80	Al (M)	Н
pin 31	A3 (M)	H	pin 81	A2 (M)	H
pin 32	A15 (M)	H	pin 82	A6 (M)	H
pin 33	Al2 (M)	H	pin 83	A7 (M)	H
pin 34	A9 (M)	H	pin 84	A8 (M)	H
pin 35	DO1 (M)/ED1 (M/S)	Н	pin 85	Al3 (M)	H
pin 36	DOO (M)/EDO (M/S)	H	pin 86	Al4 (M)	Н
pin 37	Al0 (M)	H	pin 87	All (M)	H
pin 38	DO4 (M)/ED4 (M/S)	H	pin 88	DO2 (M)/ED2 (M/S)	H
pin 39	DO5 (M)/ED5 (M/S)	H	pin 89	DO3 (M)/ED3 (M/S)	H
pin 40	DO6 (M)/ED6 (M/S)	H	pin 90	DO7 (M)/ED7 (M/S)	Н
pin 41	DI2 (S)/OD2 (M/S)	Н	pin 91	DI4 (S)/OD4 (M/S)	Н
pin 42	DI3 (S)/OD3 (M/S)	H	pin 92	DI5 (S)/OD5 (M/S)	Н
pin 43	DI7 (S)/OD7 (M/S)	H	pin 93	DI6 (S)/OD6 (M/S)	Н
pin 44	sMl (M)	H	pin 94	DI1 (S)/OD1 (M/S)	Н
pin 45	SOUT (M)	H	pin 95	DIO (S)/ODO (M/S)	Н
pin 46	SINP	H	pin 96	SINTA (M)	Н
pin 47	SMEMR	Н	pin 97	sWO* (M)	L
pin 48	SHLTA (M)	Н	pin 98	ERROR* (S)	L
pin 49	CLOCK (B)		pin 99		
pin 50	0V		pin 100	V 0	

APPENDIX B HEXADECIMAL TO DECIMAL CONVERSION

		6					5		1		4		1	3	3		ļ		2		!		1		
I	IEX	=]	DEC	;	HE	x	=	DEC	HE	X	=	DEC	HEX	=	=	DEC	HE	x	=	DEC	HE	X	=	DI	EC
0				0	0			0	0		-	0	0			0	0			0	10			(0
1	1	,04	8,5	76	11	6	5,	536	11	4	,(96	11		2	56	11			16	11				L
2	2	,09	7,1	52	2	13	1,	072	2	8	,]	92	12		5	12	2			32	12				2
3	3	,14	5,7	28	3			608		12	,2	288	13		7	68	3			48	3				3
4	4	,19	4,3	04	4	26	2,	144	4	16	13	384	4	1,	,0	24	4			64	4			6	4
5	5	,24	2,8	880	5	32	7,	680	15	20	,4	80	15	1,	,2	80	5			80	15			5	5
6	6	,29	1,4	56	6	39	3,	216	6	24	,!	576	6	1,	, 5	36	16			96	6			6	5
7	7	,341	0,0	32	17	45	8,	752	17	28	, (572	17	1,	,7	92	17]	.12	17				7
8	8	,38	8,6	08	8	52	4,	288	8	32	, ,	768	8	2	,4	80	8		1	.28	8				8
9	9	,43	7,1	.84	9	58	9,	824	9	36	,8	364	9	2	,3	04	9]	44	9			9	9
A	10	,48	5,7	60	A	65	5,	360	A	40	,!	960	A	2	, 5	60	A		1	.60	A			10)
В	11	,53	4,3	36	B	72	0,	896	B	45	,()56	B	2	, 8	16	B		1	.76	B			11	L
С	12	,58	2,9	12	C	78	6,	432	C	49	,]	52	C	3	,0	72	IC		1	.92	1C			12	2
D	13	,63	1,4	88	D	85	1,	968	D	53	12	248	D	3	,3	28	D		2	208	D			13	3
E	14	,68),(64	E	91	7,	504	E	57	1	344	E	3	,5	84	E		2	24	E			14	4
F	15	,72	8,6	40	F	98	3,	,040	F	61	"	140	F	3	, 8	40	F		2	240	F			1!	5
	() 1	2	3	4	1 5	6	5 7	1 0) 1	2	2 3	4	5	6	7	1 0	1	2	2 3	1 4	1	5	6	7

THIS PAGE INTENTIONALLY LEFT BLANK

APPENDIX C STANDARD ASCII CODES

				BIT PC	SITIO	N		
7 6 5	7 6 5 	7 6 5		1919 - 1919 - 1949 1919 - 1919 - 1949	6 7 6	5 7 6 5	7 6 5 	4 3 2 1
0 0 0	0 0 1	0 1 0	011	1 0 0 		1 1 1 0	1111	
NUL	DLE	SP	0	[P		р	0000
S OH	DC1	!	1	A	i @	a	q	0001
STX	DC2		2	і в	R	b	r	0010
ETX	DC3	#	3	і с	S	c	S	
EOT	DC4	\$	4	D	T	d	t	0 1 0 0
ENQ	NAK	8	5	Ε	U	e	u	0101
ACK	SYN	&	6	F	V	f	V	0 1 1 0
BEL	ETB	1	7	G	W	g	Ŵ	0111
BS	CAN	(8	H	X	h h	x	1000
HT	EM)	9	I	Y	i	У	1001
LF	SUB	*	:	J	Z	j	Z	1010
VT	ESC	+	;	K	[k	{	1011
FF	FS	,	<	L		1		1 1 0 0
CR	GS	-	=	M]	m	}	1101
SO	RS	•	>	N N	^ 	n	~	1110
SI	US	/	?	0		0	DEL	1111
SOHSSTXSETXEEOTEENQEACKABELBBSBHTHLFLVTVFFFCRCSOSSIS	ull or tart of tart of nd of t nquiry cknowle ell, or ackspac orizont ine fee ertical orm fee arriage hift or hift in	head text text cansm edge calari ce cal tal ed tabu ed return	ing ission n pulati lation cn	on	DC1 DC2 DC3 DC4 NAK SYN ETB CAN EM SUB ESC FS GS RS US SP DEL	Device Device Device Negati Synchro End of Cancel End of Substi Escape File so Group S Record	medium	l 2 l 3 l 4 owledge dle ission block ission block

C-1

Start of Last

APPENDIX D EBCDIC TABLE

	- 3									В	it Positi	ons 0, 1	, 2, 3				
Bit Positio 4, 5, 6,		0000	0001	0010	0011	0100	0101	0110	0111	1000	1001	1010	1011	1100	1101	1110	111
	Hex	0	1	2	3	4	5	6	7	8	9	A	В	с	D	E	F
0000	0	NUL	DLE	DS		SP	8	-						(`)	N	0
0001	1	soh	DCI	sos		38				o	j	\sim		A	J		1
0010	2	STX	DC2	FS	SYN					ь	k	5		В	к	s	2
0011	3	ETX	DC3							c	I.	t		с	L	т	3
0100	4	PF	RES	BYP	PN					d	m	U		D	м	U	4
0101	5	нт	NL	LF	RS					e	n	v		E	И	v	5
0110	6	LC	BS	EOB ETB	UC					f	0	w		F	0	w	6
0111	7	DEL	IL	PRE	EOT					9	р	x		G	Ρ	×	7
1000	8		CAN							h	q	У		н	Q	Y	8
1001	9	RLF	EM						1	ĩ	r	z		I	R	z	9
1010	A	SMM	сс	SM		¢	1	1	:			-					
1011	в	VT				•	s		,								
1100	с	FF	IFS		DC4	<	•	%	μ								
1101	D	CR	IGS	ENQ	NAK	()	-									
1110	E	so	IRS	АСК		+	• ;	>.	-								
m	F	51	IUS	BEL	SUB	1	-	?	ü								

Duplicate Assignment


EBCDIC Character Assignments (Part 1 of 2)


Choracter	Hex	Character	Hex		Chorocter	Hex
A	CI	6	44		RS .	35
8	C2	1	SA	1	51	OF
c	C3		7A		SM	2A
D E F	C4		78		SMM	0A
E	C5		68		50	OE
G	C6 C7	1 2	48		SOH	01
н	CB	.< .	4C 5C	- 1	sos .	21
1	C9	e	6C		Spoce STX	40
3	DI		70		SUB	3F
J K	D2	1	4D		SYN	32
L	D3	()	5D		- UC	36
M	D4		60		VT	08
N	D5	1.7	70			
0	D6 D7	+	4E			
P	D8	1	5E			
8	D9		6E 7E			
5	E2	1	4F			
R S T	E3	<u> </u>	SF			
U	E4	?	6F			
v	E5	۰۰۰ · ۷۰ - [۵۰ ک)	75		ETB and EOB	have
w	E6		CO		he same hex	
÷	E7 E8		DO		assignment. P	
X Y Z	83	1	EO		ESC have the	some her
0	81	l~	A1 79	c	assignment.	
ь	82	ì	6A			
c	83	BEL	2F			
d	84	BS	16			
e .	85	BYP	24			
1	86	CAN	18			
9	87 88	CC	IA			
h i	88	CR	OD			
1	91	DC1 DC2	11			
k	92	DC3	13			
î .	93	DC4	30			
m	94	DEL	07			
n	95	DLE	10			
0	96	DS	20			
P	97	EM	19			
9	98	ENQ	2D			
	A2	*EOB	26			
;	A3	EOT *ESC	37 27			
	A4	*ETB	26			
*	AS .	ETX	03		3	
	A6	FF	oc			
w x y	A7	FS	22			
У	A8	HT	05			
z 0 1	AP	IFS	10			
0	FO	IGS	ID			
2	FI	IL	17			
2	F3 F3	IRS	1E			
3	F4	IUS	1F			
5	F5	LC LF	06			
6	FÓ	LF NAK	25 3D			
2 3 4 5 6 7 8 9	F7	NAK	15			
8	F8	NUL	00			
9	F9	PF	04			
å	50	PN	34			
•	60	*PRE	27			
1	61	RES	14			
5	5B	RLF	09			


hez

EBCDIC Character Assignments (Part 2 of 2)

APPENDIX E CIO SPECIFICATION







Registers (Continued)

Interrupt Vector Register Addresses: 000010 Port A 000011 Port B 000100 Counter/Timers (Read/Write)

D, D, D, D, D, D, D, D,

Current Vector Register Address: 011111 (Read Only)

D₇ D₆ D₈ O₄ D₅ D₇ D₁ D₉

- INTERRUPT VECTOR BASE. ON HIGHEST PRIORITY UNMARKED IP IF NO INTERRUPT PENDING ALL 1'S OUTPUT.

INTERRUPT VECTOR

 PRIORITY ENCODED VECTOR MODE:

 D3
 D3

 X
 X

 WITH A MATCH

 ALL OTHER MODER:

 D3
 D1

 ORE INF PMF NORMAL

 0
 0

 D4
 D1

 ONTER PMF NORMAL

 0
 0

 D4
 D1

 D5
 COUNTEINTRER STATUS

 D5
 OT 2

 1
 EMOOR

Figure 7. Interrupt Vector Registers

Register		Main Control Registers		Port A Specification Registers	
Address	Address	Register Name	Address	Register Name	
Summary	000000	Master Interrupt Control	100000	Port A's Mode Specification	
57	000001	Master Configuration Control	100001	Port A's Handshake Specification	
	000010	Port A's Interrupt Vector	100010	Port A's Data Path Polarity	
	000011	Port B's Interrupt Vector	100011	Port A's Data Direction	
	000100	Counter/Timer's Interrupt Vector	100100	Port A's Special I/O Control	
	000101	Port C's Data Path Polarity	100101	Port A's Pattern Polarity	
	000110	Port C's Data Direction	100110	Port A's Pattern Transition	
	000111	Port C's Special I/O Control	100111	Port A's Pattern Mask	
		Meat Often Accessed Registers		Port B Specification Registers	
	Address	Register Name	Address	Register Name	
	001000	Port A's Command and Status	101000	Port B's Mode Specification	
	001001	Port B's Command and Status	101001	Port B's Handshake Specification	
	001010	Counter/Timer I's Command and Status	101010	Port B's Data Path Polarity	
	001011	Counter/Timer 2's Command and Status	101011	Port B's Data Direction	
	001100	Counter/Timer 3's Command and Status	101100	Port B's Special I/O Control	
	001101	Port A's Data	101101	Port B's Pattern Polarity	
	001110	Port B's Data	101110	Port B's Pattern Transition	
	001111	Port C's Data	101111	Port B's Pattern Mask	
		Counter/Timer Related Registers			
	Address	Register Name			
	010000	Counter/Timer 1's Current Count-MSBs			
	010001	Counter/Timer 1's Current Count-LSBs			
	010010	Counter/Timer 2's Current Count-MSBs			
	010011	Counter/Timer 2's Current Count-LSBs			
	010100	Counter/Timer 3's Current Count-MSBs			
	010101	Counter/Timer 3's Current Count-LSBs			
	010110	Counter/Timer I's Time Constant-MSBs			
	010111	Counter/Timer 1's Time Constant-LSBs			
	011000	Counter/Timer 2's Time Constant-MSBs			
	011001	Counter/Timer 2's Time Constant-LSBs	÷.		
	011010	Counter/Timer 3's Time Constant-MSBs			
	011011	Counter/Timer 3's Time Constant-LSBs			
	011100	Counter/Timer 1's Mode Specification			
	011101	Counter/Timer 2's Mode Specification			
	011110	Counter/Timer 3's Mode Specification			
	011111	Current Vector			

APPENDIX F ASCC SPECIFICATION

The Zilog 8531 ASCC chip contains 13 write registers in each channel that are programmed separately to configure each of the channels and 2 write registers shared by both channels.

Register addressing is direct only for the data registers (ports 7DH and 7FH). In all other cases programming the write registers requires 2 write operations, and reading the read registers requires 1 write and 1 read. The first write is to WRO and contains 3 bits which point to the selected register. The second write is to the actual register selected or, if a read, the selected register is accessed and read. The pointer bits are automatically cleared after a read or write so that the pointer register (WRO or RRO) is accessed again.

The ASCC contains 8 read registers which contain various status signals.

READ REGISTER FUNCTION


- RRO Transmit/Receive buffer status, and External status
- RR1 Special Receive Condition status, residue codes, error conditions
- RR2 Modified (Channel B only) interrupt vector and Unmodified interrupt vector (Channel A only)
- RR3 Interrupt Pending bits (Channel A only)

RR8 Receive buffer

- RR10 Miscellaneous XMTR, RCVR status parameters
- RR12 Lower byte of baud rate generator time constant
- RR13 Upper byte of baud rate generator time constant
- RR15 External/Status interrupt control information


WRITE REGISTER FUNCTION

- WRO Command Register, (Register Pointers, Z8530 only), CRC initialization, resets for various modes
- WR1 Interrupt conditions, Wait/DMA request control
- WR2 Interrupt vector (access through either channel)
- WR3 Receive/Control parameters, number of bits per character, Rx CRC enable
- WR4 Transmit/Receive miscellaneous parameters and modes, clock rate, number of sync charactars, stop bits, parity
- WR5 Transmit parameters and controls, number of Tx bits per character, Tx CRC enable
- WR6 Sync character or SDLC address field (1st byte)
- WR7 Sync character or SDLC flag (2nd byte)
- WR8 Transmit buffer
- WR9 Master interrupt control and reset (accessed through either channel), reset bits, control interrupt daisy chain
- WR10 Miscellaneous transmitter/receiver control bits, NR2I, NR2, FM encoding, CRC reset
- WR11 Clock mode control, source of Rx and Tx clocks
- WR12 Lower byte of baud rate generator time constant
- WR13 Upper byte of baud rate generator time constant
- WR14 Miscellaneous control bits: baud rate generator, Phase-Locked Loop control, auto echo, local loopback
- WR15 External/Statue interrupt control information-control external conditions causing interrupts



Write Registers. The SCC contains 13 write registers (14 counting WR8, the transmit buffer) in each channel. These write registers are programmed separately to configure the functional "personality" of the channels. In addition, there are two registers (WR2 and

WR9) shared by the two channels that may be accessed through either of them. WR2 contains the interrupt vector for both channels, while WR9 contains the interrupt control bits.



MONOSYNC, 6 BITS MONOSYNC, 6 BITS BISYNC, 16 BITS BISYNC, 12 BITS BDLC SDLC (ADDRESS RANGE)

SYNC. SYNC. SYNC.


Write Register Bit Functions

SYNC4 SYNC4 SYNC4 SYNC4 SYNC4 ADR4 ADR4

SYNC:

1 ADM2

Vo v,



Write Register Bit Functions (Continued)

THIS PAGE INTENTIONALLY LEFT BLANK

APPENDIX G PAL16L8 SPECIFICATION

U28 (DECODE):

/MREQ /IORQ /RD /WR BUSAK IEO BOOT /RFSH MASTER GND /INTA /GORAM PA16 /IO /BRFSH /MATCH /RAMENB /PROMENB /RDOFF VCC

IF (VCC) / RAMENB = / BOOT*MASTER*MATCH*PAl6+/BOOT*/MASTER*PAl6+ /BOOT*/MASTER*BUSAK*MATCH

IF(VCC)/PROMENB = BOOT+MASTER*/BUSAK*MATCH*/PA16+ /MASTER*/BUSAK*/PA16

IF(VCC)/GORAM = RAMENB*MREQ*RD+RAMENB*MREQ*WR+ RFSH*MREQ+BRFSH

U59 (SLAVE):

/ADSB /HOLD MATCH /DODSB /CEN MEMR SLVRQ DBIN BUSAK GND MEMW /BUSRQ /RDOFF MASTER /BUSENB /DIEN /DOEN /AEN /BRFSH VCC

IF (VCC) / BRFSH = MASTER* / MATCH*MEMR*DBIN*BUSAK

IF (VCC) / BUSENB = / CEN*MASTER+MATCH*/MASTER*AEN

IF (VCC) / BUSRQ = MASTER*HOLD+MASTER*BUSAK*ADSB+/MASTER*SLVRQ

IF (VCC) / AEN = MASTER* / ADSB+BUSAK

IF (VCC) / DOEN = MASTER* / DODSB* / BUSAK+BUSAK*MATCH*MEMW

IF (VCC) /DIEN = MASTER*RDOFF*/BUSAK+BUSAK*MATCH*MEMR*DBIN

THIS PAGE INTENTIONALLY LEFT BLANK

APPENDIX H PORT ASSIGNMENTS

Port (Hex)	Signal Name	Function
70	SASI*	SASI/Parallel portdata
71	MAPPER*	Memory mapper
72	ATTEN*	Attention bit for slave
		processor (used to generate an interrupt to master)
73-77	Not Connected	Not used
78-7B	CIOEN*	CIO (8536) enable
78	Port C	
79	Port B	
7A	Port A	
7B	Control	
7C-7F	SCCEN	Serial chip enable
	Channel	Function
7C	В	Control
7D	В	Data
7 E	А	Control
7F	A	Data

THIS PAGE INTENTIONALLY LEFT BLANK

APPENDIX I PARALLEL INTERFACES: SASI/CENTRONICS

SINGLE-ENDED SASI/SCSI COMPATIBLE INTERFACE CONNECTOR J4

NOTES:

All odd pins shall be connected to ground True on SASI = Signal Assertion = 0.0 VDC to 0.5 VDC False on SASI = 2.0 VDC to 5.25 VDC Parity not used To enable the data port for output (port 70), port 7A bit 5 must be high

Signal	J4 Pin Number	Port Number	Bit Number
DB0	2	70	0
DB1	4	70	1
DB2	6	70	2
DB3	8	70	3
DB4	10	70	4
DB5	12	70	5
DB6	14	70	6
DB7	16	70	7
BSY	36	7A	1(1)
ACK	38	(2)	
RST	40	7A	0(3)
MSG	42	7A	2
SEL	44	7A	7
C/D*	46	7A	3
REQ	48	7A	4
I/0*	50	7A	4 5

(1) Port 7A bit 6 is an enable for this line and must be high

(2) An I/O instruction to port 70 pulses this line

(3) Used in conjunction with port 78 bit 0 (see schematic sheet 4)

SASI TO CENTRONICS INTERCONNECT

NOTE: This table shows the pinouts for connecting a Centronics parallel port to the SBC-300 SASI port (J4). The pinouts are from J4 (50 pin) to a 25 pin 'D' connector. A second cable contains a mating 25 pin 'D' connector and the 34 pin Centronics connector. This cable is designed to be a 26 conductor flat ribbon to minimize the construction.

SASI Signal	J4 Pin Number	25 Pin 'D' Connector	Centronics Signal	(34 Pin) Pin
DB0	2	2	DATA 1	2
DB1	4	3	DATA 2	3
DB2	6	4	DATA 3	4
DB3	8	5	DATA 4	5
DB4	10<	>6<	>DATA 5	6
DB5	12	7	DATA 6	7
DB6	14	8	DATA 7	8
DB7	16	9	DATA 8	9
MSG	42	11	BUSY	11
SEL	44	1	STROBE*	1
GROUND	Any Odd Pin	14	GROUND	19

Port 76 Dit 6 is an enable for this line and must be high An 170 inclusion to port 74 doless this line Deed in Constration with port 38 Nix 8 West withings in enter 5

APPENDIX J MONITOR LOCATIONS

THIS PAGE INTENTIONALLY LEFT BLANK

CP/H RHAC ASSEN 1.1 (001 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/63

5. title 'SBC-300 Version of Monitor v2.0-VFW 9/30/83' ŝ 5 튤 ; 1/26/83 initial version dan hammond 8 \$ 5/30/83 initial release efj v1.0 # \$ 6/15/83 fix sp. misc optimization efj v1.1 # \$ 7/13/83 fix marity, vi's, step, & cio port c efj v1.2 # ŝ \$ 8/03/83 first version for vfm board efj -v0.0 #
 # B/19/83
 added modes for format routines
 dkb
 v0.1

 # 9/09/83
 fix for double density disks boot
 rlb
 v0.3
 dkb v0.1 # \$ 9/11/83 more fixes for dual-density booting dkb v0.4 # \$ 9/21/83 added mini-boot, winnie boot wbd w0.5 * ; 9/24/83 added vf2 disk routines and v0.6 * : * : 9/30/83 Fixed boot efi 4 \$ 9/30/83 Released as 2.0 efj v2.0 # : 4 # don't forset to update title, signon and version date — - 4 2 -: : s runa: Present restrictions are: : runa must be a page boundary 4 page Offh is reserved for tables, paras * : : runa equ OdfOOh : address to ors monitor :

DF00 =

· ·

-

CP/H RNAC ASSEM 1.1 0002 SBC-300 VERSION OF MONITOR V2.0-VFH 9/30/63

	:	++++++++	*******	***************************************
	\$			
	\$		system	equates #
	5	2		÷ •
	;*********		***	***************************************
	\$			
	;			
	;**********	****	++++++++	*****************
	1			
	i miscell	aneous	equates	and an and a state of the second state of the
	•			
	;***********	******	*******	**********************
	1	0000h		the stars
0000 = 0000 =	tor equ rbase equ	0000h		s top of ram s start of ram
DF00 =	ESTSP PAU	runa		; default user stack below monitor
0080 =	sctrsz	equ	128	s bytes per sector
- 0000	5	240	120	S DILES PEL DELLOI
	:			
8000 =	vdb\$conf	@9U	1000\$00	00\$0000\$0000b
4000 =	serSconf	640		00\$000\$00001
	;			42
	1			
004 0 =	active\$vctrs	690	0100\$00	ÚÚE -
	\$			bit mask for which vectored interrputs
	\$			are enabled. (vi0 -> \$7, vi1 -> \$6, etc.)
	9			only pberr (parity) enabled
	\$			
	if mhz4	10.00		
0000 =	mhz\$conf	690	0000\$00	00\$0000\$0000b
				<pre># bits 1.0 of conf\$vctr denote cpu clock spee</pre>
8000 =	initdlay	640	08000h	5 delay for system to stabilize after ciu ini
0400 =	codlar		e ¶U	400h : delay for init console service
	else			
	if mhz			
	mhz\$conf	690	0000\$00	00\$000\$0001b
				; (bit 1 reserved for 8 mhz)
	initdlay	640	0c0001i	100
	codlar		640	600h
12	endif			
	endif			
	;			
-	1			(as abation (
4000 =	confSinit	690	PELACON	f or mhz\$conf f initial vector is ser con and unbatever cloc
				S THIRING ALLON TO BLI CON CUO BUGIEAGL CIDE
	5			
	,			

N

· .

CP/H RHAC ASSEM 1.1 0003 SBC-300 VERSION OF MONITOR V2.0-VFH 9/30/83

	; ****** ****************	**********	************	
	5	<i>x</i>	e	
	i Pase 0001: equi	ites	*	
	8		6	
	; 	***********	*************	
<u> </u>	cid\$stk equ	rbase+80h	; cold boot stack	
0080 =	cld\$stk equ cold equ rbase		old start address	
0060 =	COID ENU FDASE		oro start adoress	
	1			
	•			
	; Page Offh equa	tec	e esta bita est	
	2 Pase of the even		to the second second second second second	

	:		Ne with any stars of a	
	tathi O a			
FF00 =	575P29 @4U	Offooh	: mase Offh reserved for monito	ir and os's
	;			
FF00 =	sys\$info equ	SYSPAS + 00	h : 8 bytes for system informatio	n
FF00 =	mon\$adr	290 SY5	Sinfo + O	
FF02 =	conf\$vctr equ	sys\$info + :	2	
FF02 =	conf\$lo	equ con	fsvctr + 0	
FF03 =	conf\$hi	equ con	f\$vctr + 1	
FF04 =	monsver		Sinfo + 4	
	;	6	rtes sysinfo(5 thru 7) are rfu	
122210	1			
FF00 =	ivt equ syspas	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	ase page ram location of interrupt w	
FF08 =	ivtcioc equ	ivt + 08h	s offset to cio counter/timers	isrv's - rfu
FF10 =	ivtciob equ	ivt + 10h ivt + 20h	<pre>i offset to cio port b isrv's i offset to cio port a isrv's</pre>	- rfu
FF20 =	ivtcioa equ ivtscc equ	ivt + 301	s offset to scc isrv's	- rfu
1130 -	1111111	IVI · Jon	Y UTISET LU SEE ISTY S	
FF10 =	visr7 equ ivtcia	b + 00h		
FF12 =		ot + 02h		
FF14 =		b + 04h		
FF16 =		ot + 06h		
FF18 =		b + OBh		
FF1A =		ob + Oah	R und halfer ha	
FF1C =		b + Och		
FFIE =	visro equ ivtcia	ab + Och	ters are file. It	
	;			
	 An and so the 			
FF40 =	Varsspc equ	SYSPES + 40	h i space for variables	
	;			
	s - twelve bytes		ext used by disk routines, loaders	21
FF40 =	taddr equ varssi		ransfer address	
FF 42 =	unit equ taddr	25 C	ew unit byte	
FF44 =			rack	
FF 46 =	sctr equ trk		ector	
FF48 =	arec equ sctr		of sectors	- rfu
FF4A =	nonds equinarec	+2 ; f	or winch	- 110
4	1			
FF4C =	tears equinobds	47 1 1	est of varibles are short terms	
1140 -	CENTS ENU MUNUS		ter er verserte ere prort teres	

2

CP/H RMAC ASSEM 1.1 0004 SBC-300 VERSION OF MUNITOR V2.0-VFH 9/30/83 -\$ - eight bytes -- next four used by ycad tears +0 FF4C = scri equ scr1 +2 FF4E = scr3 equ FF50 =first equ scr3 42 last equ first +2 FF52 =- miscellaneous disk temporaries : - seventeen bytes - they can share with ycmd wars : only erstat used by VFWIII : FF4C =690 teaps 40 \$ error mask ermask FF4D =ermask +1 erstat 694 ; error status FF4E = erstat +1 ; 4 bytes idsv equ FF4F = side equ idsv +1 ; id side byte FF52 = Chdsv equ idsv +4 ; command save codsv +1 : sp save (2 bytes) FF53 = SPSV equ templegu spsv +2 ; 1 byte temporary res FF55 = temp2 equ temp1 +1 FF56 = : 2 byte temporary res FF58 = ixsav equ temp2 +2 ; ix store buffer equ ixsav +2 ; old unit byte FF5A = unitck FF58 = rseek equ unitck +1 % mbr of reseeks FFSC = Ftry equ rseek +1 : abr of rtrys -2 ; - 2 bytes -- mext two used for parity err, interrupts : location for vectored interrupt flas ivn equ ptry 41 FF5D = Parsloc equ ivn +1 ; flas to note if parity err location is known FFE = par\$loc+1 ; mext available location FFSF = axt\$loc 694 but watch out for intrrupt stack \$: save sp during interrupt handling FF7E = sav\$isp Off7eh 69U stack for interrupts SavSisp FF7E = intSstk 294 tor-40h FFC0 = spad equ : FFC0 =B055P1 equ spad ; op sys stack pointer 2 ; software by flas FFC0 =sbek equ spad : software by user code FFC1 = spad+1 becod equ ; software by location FFC4 = beloc equ spad+4 FFC6 =s print format flas long equ spad+6 FFC7 =opent equ spad+7 FFC8 = axchr equ spad+8 FFC9 =spad+9 count equ 10 : dcad flas spad+10 = A000 flas equ FFD0 = 8P15 294 spad+10h FFD0 = opri equ eprs FTD2 = err2 equ eprs+2 FFD4 = OPT3 equ oprs+4 FFD6 = opr4 equ oprs+6 FFD8 =eer5 eeu OPTS+8 FFDA = oprs+10 epró equ FFDC = epr7 equ eprs+12

FFDE =

opr8 equ

oprs+14

CP/H RHAC ASSEN 1.1 0005 SEC-300 VERSION OF HONITOR V2.0-VFH 9/30/83

FFEO =	opr9 equ 💊	eprs+16			
FFE2 =	opr10 equ	ers+18			
	1				
0000 =	BOSSP COU	tor	OP SYS SP		
FFFE =	NPC equ	BUSSP-2	i user resister s	AVE ATER	
FFFC =	waf equ	BOSSP-4			-
FFFA =	wir equ	BOSSP-6			
FFF8 =	apc ean	BOSSP-B			
FFF6 =	ude equ	Bossp-10			
FFF4 =	whi equ	Bossm12			
FFF2 =	wafp equ	B055P-14			
FFF0 =	UDCP equ	B055P-16		in the second second	
FFEE =	uder equ	B055P-18	2		
FFEC =		BOSSP-20			
FFEA =	Wix equ	B055P-22			
FFE8 =	UIY CAU	B055P-24			
FFE6 =	85P @9U	B055P-26			
FFE4 =	tusp equ	Bossp-28			
	5				
FFFD =	049 64U	waf+1			
FFFC =	uf equ	waf			
FFFB =	ai ean	wir+1			
FFFA =	wif equ	air	140		
FFF9 =	ub equ	wbc+1			
FFF8 =	8C @9U	wbc			
FFF7 =	ures bu	ude+1			
FFF6 =	ଖଟ ଜମ୍ବଧ	ude			
FFF5 =	uh equ	wh1+1			
FFF4 =	ຢີ ຂຈນ	whl			
FFF3 =	WEP CAN	wafp+1			
FFF2 =	ofp equ	mafp			
FFF1 =	ubp equ	abce+1			
FFF0 =	8CP @9U	BOCP			
FFEF =	ude equ	uder+1			
FFEE =	00P 09U	ødep			
FTED =	whr equ	whip+1			
FFEC =	ups als	etile			
	5				
	8				
	;*******	************	{}}}}}	*****	
1.00	;				
	; i/o por	rt definitions,	commands. & masks	4	
	;*********		***************	******	
	1				
0001 =	vábd equ	1	; vdb data port		
0000 =	vdbs equ	ō	; vdb status port		
0070 =	sasid equ	70h	; sasi data port		
0071 =	Bapper	enu 71h	5 J. 52 State 199	Bapper port	
0072 =	atten equ	72h	# host attention		
0072 =	cioc equ	78h	f cio data Port c		*
0078 =	ciob equ	79ti	t cio data port b		
0079 =	Cioa 290	7ah	; cio data port a		
007B =	cioctl		i Cio Con		
		(175-175) (175-175)	t scc channel b c		
- 007C =	scobe equ	7ch	t scc channel b d		
0 07D =	sccbd equ	7dh	a pre channel b o		

•.

...

.

٠.

OP/M RMAC ASSEM 1.1 0006 SBC-300 VERSION OF MONITOR V2.0-VFN 9/30/83

) P

A.

.

007E =				
61023191625	SCCaC equ	7eh	;	scc channel a control
007F =	sccad equ	7fh		scc channel a data
	5			
0002 =	wransk	640	2	; vdb rx mask
0004 =	vtxmsk	640	4	; wdb tx mask
0001 =	sramsk	640	1	f scc rx mask
0004 =	stxask	640	4	\$ scc tx mask
	i			
0009 =	csr\$b	640		cod/status cio port b
0020 =	rst\$csr\$b	640	0010500006	
00 A0 =	ius\$1P\$ask	690	1010500000	
	;			
	;			
	;		FLOPPY II	
	s ports	used br	disk control	ler
	;		0.20	
0060 =	dports		60h	
0060 =	rset equ	dports		controller reset addr
0063 =	select		dports+3	; drive select port
0064 =	cad equ	dport		command port
0064 =	status2	107 C 197	dports+4	; status port
0065 =	track equ	deort		track port
0066 =	sector2		dports+6	; sector port
0067 =	data equ	dport	s+7 ;	data port
	5			
	i disko	controlli	er command co	062
0000	i de se d		0-01	a surd address and
0000 =	rdacad	640	OcOh	<pre>i read address cmd i read sector cmd</pre>
= 6800	rd2cad	690	88h	
00A8 =	wr2cad	640	Oa8h	<pre># write sector cmd # write track cmd</pre>
00F4 =	wrtcad	690	Of4ti	. Write track the
	1		•	
				e4+41
		ance at		51617
	; diske	error sta	atus bits ter	Juit
	s bit 7	- drive	not ready	
	; ; bit 7 ; bit 6	- drive - write	not ready protected	
	s bit 7 s bit 6 s bit 5	- drive - write - track	not ready protected seek error	
	5 5 bit 7 5 bit 6 5 bit 5 5 bit 4	- drive - write - track - sector	not ready protected seek error not found	
	5 bit 7 5 bit 6 5 bit 5 5 bit 4 5 bit 3	- drive - write - track - sector - crc er	not ready protected seek error mot found pror	
	5 bit 7 5 bit 6 5 bit 5 5 bit 4 5 bit 3 5 bit 2	- drive - write - track - sector - crc er - data	not ready protected seek error mot found pror lost	
	i bit 7 bit 6 bit 5 bit 3 bit 2 bit 1 bit 2	- drive - write - track - sector - crc er - data - dra b:	not ready protected seek error mot found rror lost it	
	i bit 7 bit 6 bit 5 bit 3 bit 2 bit 1 bit 2	- drive - write - track - sector - crc er - data i - dra b: - write	not ready protected seek error mot found fror lost it deleted sect	
	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - dra b: - write control	not ready protected seek error mot found fror lost it deleted sect ler hans up	
	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - dra b: - write control	not ready protected seek error mot found fror lost it deleted sect	
• 1 .	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - dra b: - write control	not ready protected seek error mot found fror lost it deleted sect ler hans up	
* *	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - drg b: - write controll invalid	not ready protected seek error mot found fror lost it deleted sect track error	or read
	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - drg b: - write controll invalid	not ready protected seek error mot found fror lost it deleted sect ler hans up	or read
•	5 5 5 5 5 5 5 5 5 5 5 5 5 5	- drive - write - track - sector - crc er - data 1 - drg b: - write controll invalid	not ready protected seek error mot found fror lost it deleted sect track error	or read
	<pre> 5 bit 7 bit 6 bit 5 bit 5 bit 4 bit 3 bit 3 bit 2 bit 1 bit 0 feh - s ofh - s s s s s s s s s s s s s s s s s s s</pre>	- drive - write - track - sector - crc er - data 1 - drg b: - write controll invalid	not ready protected seek error mot found fror lost it deleted sect ler hans up track error FLOPPY WINCHE	or read STER III
0050 =	<pre>bit 7 bit 6 bit 5 bit 5 bit 4 bit 3 bit 2 bit 1 bit 0 feh - contained of the feh - con</pre>	- drive - write - track - sector - crc er - data 1 - dra b: - write controll invalid VERSAF	not ready protected seek error mot found fror lost it deleted sect track error FLOPPY WINCHE 50h	or read STER III ; base of vfw ports
0050 =	<pre>bit 7 bit 6 bit 5 bit 5 bit 4 bit 3 bit 2 bit 1 bit 0 feh - foh - f</pre>	- drive - write - track - sector - dra b - dra b - dra b - write controll invalid VERSAF	not ready protected seek error not found fror lost it deleted sect track error FLOPPY WINCHE 50h vfwbas+0	or read STER III : base of vfw ports : sector buffer
0110-01-0	<pre>bit 7 bit 6 bit 5 bit 5 bit 4 bit 3 bit 2 bit 1 bit 0 feh - contained of the feh - con</pre>	- drive - write - track - sector - crc er - data 1 - dra b: - write controll invalid VERSAF	not ready protected seek error not found fror lost it deleted sect track error FLOPPY WINCHE 50h vfwbas+0 s+1 \$	or read STER III ; base of vfw ports

•

•.

CP/H RHAC ASSEM 1.1 0007 SBC-300 VERSION OF HONITOR V2.0-VFW 9/30/83

	0050		secto			wfuhar42	; sector number
	0053						s sector number cylinder (lower byte)
	0055		cylh				cylinder (upper byte)
	0056		sdt		vfubas		size/drive/head select
	0057		statu	A 52 8 5			t vfw status
	0057		COBBA				f vfw command Port
	0058		deal				dma address port (low)
	0059		daas				dma address port (mid)
	005A		. daah				dma address port (hish)
	005B		contr				: dea/floppy control
			;				
			:	control	port b	it masks	
	0001	-	bisf	0011	1		8" Floppy
	0002		hd3		2	6.5	bit3 of winch head select
	0002		nd3 sden		4		single density
	0004		mode		8		motor mode : 1= 1 sec delay for motor start
	0010		dread	0.5.25	10h		disk read
	0010		dnaetu	10.000 0.000	640 100	20ti	i des enable
	0040		PCe	T 1	40h		Prom chip select enable - should be O
	0080		bank	10 TO 100 PT	BOh		select upper half of prom : n.u.
	9960	-	F F	1010	0011		Select offer main of from a new.
			5	status	port bi	t masks	
	0001		err	640	1	-	error bit
	0002		irs	690	2		interrupt rast bit
	0004		COL	690	4	1	corrected read bit
	8000		dra	690	8	1	data request bit
	0010		scb	e 9u	10h	1	seek complete bit
	0020		wf	690	20h		write fault/prot bit
	0040		rdy	e 90	40h		drive ready bit
	0030		bsy	690	801		vfw busy bit
			5				
			;				
			1	vfw com	mands		•
	0010	=	resto	re	e ¶u	10h	; heads to trk00
			•	if daa			
			;				
			rdcad	640	28h		i read sector
			;	- <u>-</u>			
				else	; mot i	60%	
			ï				
	0020	2	rdced	640	20h		read sector
			÷				
				endif	s not		
	10000000		;		(Vacano)		
	0030		erced		30h		s write sector
	0050		facad		50h	10 A 17 A 18	format command
5	0051		sdfac		640	51h	; format command for single density
2	0070	ε .	seekc	ad ba	640	70h	\$ seek command
1			Ŧ				
				if dea			

DP/H RHAC ASSEM 1.1 0006 SBC-300 VERSION OF MONITOR V2.0-VFH 9/30/83

ren3	300	6 90	01	; hish byte,	onboard ram	address	010000
ş							
	endif	t dea					
:							-
8							

Admit they will be a set of the s

A of Manha - Maker Solar and a		

12

All and have a set

.

CP/H RHAC ASSEN 1.1 4009 SEC-300 VERSION OF MONITOR V2.0-VFH 9/30/83

	;++++		*******	******	нн	*******	
	8						
	ĩ	Desin	executabl	e code			
	; ;****		+++++++++	******	++++	•	New get
	;					rise in	
DF 00	;	019	runa				
	:	412					
	:						
	;		all cod	e must be	P2.9	e zero executable until init2	entry
	;	-					
	;++++		******	*****	••••	*****	
	;	harie	linkages		• • •		
			n compatab		tor		
		I CP/I		12 /			
	1				****	*	
	;					*************	
	mon\$s	trt:					
		JOPT	init	3	; 0	monitor cold boot	
DF00+1862							
	1						
DF02 20	versb ;	YI:	đb	Ver\$10f0		<pre>% version number byte</pre>	
DF03 C380E1	wsstr	t:	JBP	rentry		; 1 monitor re-entry	
DF06 C32CE9	cse:	JMP	const	3	; 2	console status	
DF09 C322E9	cie:	JMP	conin	3	; 3	read console	
DFOC C327E9	coe:	JB P	conout	3	; 4	write console	
DFOF C327E9		JBP	conout	3	; 5	list	
DF12 C327E9		JB P	conout	3	; 6	Pun	
DF15 C322E9		JBP	conin		; 7		
DF18 C37EEE	h2:	JBP	home		: 8		
DF1B C35AEC		JBP	seldsk		; 9		
DF1E C35FEC		JBP	settrk		; 10		
DF21 C364EC		JEP	setsec		: 11		
DF24 C369EC			setdea				
DF27 C392EE			read		: 13		
OF2A C385EE	w2: 1	JB P	write		: 14		
OF 2D C36EEC	Sec.	inp	loader		: 15		
F30 C37DEC			saver		16		
IF33 C34EEB		JBP	retsconi		17		
	i					***********	13
	1					*	
		signon	and versi	on/date			
	;****	******	*****	******		********	
	5						
-	1						
0020 =	ver\$i	nfo	640	20h			
0020 =	verSi	nfo	e 90		ve	rsion 2.0	

OP/H RHAC ASSEM 1.1 0010 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

	signon\$esg:	
DF36 0A0D534453	đb	Oah. Odh, 'SDSYSTEMS SBC-300 MONITOR V2.0', Oah. Odh, OOH
	ş -	
DF5A 3039333038	đb	*0730 83 '
	1	
	IF PHZ4	
	5	
DF60 20344020	đb	~~~~~~ · · · · · · · · · · · · · · · ·
	\$	
	ELSE	\$ 19 4Z6
	5	
	đb	·
	;	
	ENDIF	\$ MHZ6
	;	

.

î

.

the second se

.

a alabierterne bin children

PT VETER TAXABLE AND A VETER AND A

Adventure station of the

OP/H RHAC ASSEM 1.1 0011 SEC-300 VERSION OF HONITOR V2.0-VEH 9/30/83

	4	*******		F###	6	
	5	enter	here after reset		8	
	2	ENCEL	mere writer, reset			
	:**	***	******	нн		
	-					
	ini	t:				
DF64 F3		di		;	if not by reset	
#F65 31COFF		lxi	SP.BOSSP1	ş	initialize stack pointer	
				52	initialize men mapper	
DF68 216D01		lxi	h.map\$init - ru	Ina		
		lxix	map\$ret0			
DF68+DD21						
DF60+7100		1				
DF6F+186D		JBPT	initSer.			
DFOF+100U	;					
0071 =	7.2	\$ret0	equ S - run		· · · · · · · · · · · · · · · · · · ·	
DF71 DB7B		in	cioctl		reset cio	
DF73 AF		XLS 211	a		Jesti cio	
DF74 D37B		out	cioct]		wrt ptr or clr rst	
DF76 DB7B		in	cioctl	- 12.	state 0	
					now do basic cio init	
DF78 21C001		lxi	h,ciotab - runa	1		
DF78 0617		evi	b, cionb		# of bytes	
DF7D OE7B		evi	c.cioct1	ş	cio control port	
		outir		ş	control bytes to cio	
DF7F+EDB3						
	ï					
DF81 110080		lxi	d, initdlar	;	delay for system to stabilize	after cio init
	ini	td0:	523			
DF84 1B		dcx	4			
DF85 7A		DOV	ard			
DF86 B3		ora	e			
		jrnz	inite0			
DF87+20FB					*	
	\$				now init scc	
BEOD 210301	\$	1	h eachal - auro		BOA THIL PCC	
DF89 21D701 DF8C 0610		lxi mvi	hiscotab - runa bisconb		8 of bytes	
DEBE OFTE		BV1	CISCCOC	- 10	scc channel a control	
BFOC UC/E		eutir	CINCLES		control bytes to scc a	
F90+EDB3		0.011				1.2
DF92 21D701		Ixi	hiscotab - runa			
DF95 0610		svi	b.sccnb			
DF97 DE7C		evi	C.SCCbC	;	scc channel b control	
		outir		;	control brtes to scc b	
#F99+ED83						
-	8					
	ş				print signon msg	
DF98 213500		lxi	A.sisnonSass -	1.	- runa	
11		lxix	sasret			
F9E+DD21						
DFA0+A200		100	-100			
Q0A 2 =	se4	ret	ean 8 - Lau	ha.		

.

CP/H RHAC ASSEM 1.1 0012

.

SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

•

DFA2	23	inx	h
DFA3	7E	BOV	8.8
DFA4	B7	era	8
DFA5	C24B01	jnz	outSchar - runa

...

	i		
	initSmpr:		; enter with h1 => map table
DFDE OE71	∎vi	C.Bapper	
DFEO 56 ·	BOV .	d	
DFE1 23	inx	h	
DFE2 TE	initm1:	80V 8.8	; lower data for mapper
DFE3 23	inx	h	
DFE4 46	(INC V	6.8	; upper data/address
DFES 23	inx	h	*
	eutp	8	# write to mapper
DFE6+ED79			
DFE8 15	dcr	d	f dec word count
	jrnz	initml	
JFE9+20F7			the second second
	PCix		
DFEB+DDE9			
	:		

...

:

...

.

	;		
	outschar		; output accum to both possible consoles
E048 D301	eu'	t ve bd	
E040 0370	eu	sccbd	
	;		
E04F 110004	lx	i d.codlay	; delar - no status available vet
	dlay:		
E052 1B	dex	x d	
E053 7A		v a.d	and submit in the property and
E054 B3	010	e	
	jri	nz dlav	
E055+20FB			
	;		
	. PC:	ix	; jump back by ix
E057+DDE9			

.

CP/H RHAC ASSEM 1.1 0013 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

•

		;*******	****	*****	*******	******	
		1				4	
		S Bebory		18 - 19 and 18 and 1	lization da		
		1			inboard pros	•	
		5			inboard ram		
			800	v-tttt : c	mboard ram	low/h1 @	
		1				4	
		;**********	*****	111111111111	*****	********	
		map\$init:					
EO	6D 10	db	16				
2.55	6E FF0FFE1FF1			AFOOD	0-0015+	0d002h.not	0-0026
	76 EB4FEASFE				217 22 23 23 23 24 24 2	090161. not	
	TE EF &FEL 9FE					05012h, not	
	86 EBCFEADFE					01016h, not	172.0.5.700.00
		:		0001411101	0201303000	ererentinet	0001711
		mapShigh:			2.5		
EO	6E 0 8	đb	8				
	OF ETOFE69FE		-	07018h. not	06019h.not	0501ah.not	0401bh
	97 E3CFE2DFE					O101eh.not	
		1				••••••	
		9					
		;++++++++++++++++++++++++++++++++++++++	*****	*********	*****	*******	
		1 1			1		
		5 Debory		er - map al			
		i	000	0-ffff : o	nboard ran		
		5					
		;**********	19199	**********	********	*******	
		5					
		1					
EM	9F 10	map\$ran:	41		1 august	of words of	4.4.
1.1	Vale Frank	db	16	0.0101		Od012ti.not	
	AO EFOFEE1FEI AB EB4FEA5FE9						
100						09016h, not	
	BU E78FE69FE			The strate sector sector and	Contraction of the second second	0501ah, not 0101eh, not	
EOI	B8 E30FE2DFE1	1 6 V	BOI	USUICA, not	U2UIdi, not	Ololen.not	000141
		i .					
		1					
		;*********	12299		111111111111		
		1					
		\$ C10 C01	ntrol	byte table	5		
		;				*	
		;+++++++++++++++++++++++++++++++++++++		*****	*******	*******	
-		cietab:	-			nates also	his
2010	20 0001	đb	OUt	0000\$0001	8	reset cio c	912.D.4
EOC	2 00	đb		0000\$0000	6 8	2 byte see	wence
		8					1
		20	1000				by above reset
		s db		0000\$0000		dppr-c: non	
EOC	3 0602	đb	122200	000060010			out except pberr
		i di	A Standard	0000\$0000	5. <u>(j</u>)	sior-c: nor	
•.		i db	01h.	0001\$00000	;	oust have p	ort c enabled

. ... CP/H RNAC ASSEM 1.1 0014 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

above is the bare minimum that the cio requires \$ the following inits port-b to bandle vectored interrupts off the s-100 bus. -\$ E0C5 2806 db 28h, 0000\$0110b ; masr-b: bit port, or-pev 29th 0000\$0000b db : Phar-b -2at. 0000\$0000t db ; dppr-b: non inverting ; EOC7 2BFF 2th, 1111\$1111b db ; ddr-b : all inputs EOC9 2CFF db 2ch, 1111\$1111b ; sior-b: all 1's catchers 2d thru 2f define ptrn msk : 5 EOCE 2DFF db 2dt., 1111\$1111b : ppr-b : set for interrupt on any : ptr-b : 1 bit enabled by mask in 2f, 2eh, 0000\$0000b db ; EOCU 2F40 2fh, active\$vctrs ; par-b : according to system equate dt : EOCF 0310 O3h, ivtciob and OOffh ; ivr-b : 1sb of vector table db 09h, 1100\$0000b : csr-b : ei on port b E0D1 09C0 db : E0D3 0190 db 01h, 1001\$0000b : mccr : leave b,c enabled 00h, 1000\$1000b i micr : ei, vis-b E005 0068 db 0017 = S-ciotab cionb equ : 0084 = sivenb 1011\$0100b ; clear slave reset 691 : 8 충 scc control byte table \$: . 2 : scctab: if mhz4 Oc103h E0D7 03C1 du 4404h E0D9 0444 du ; #16 clock 0ea05h EODB OSEA du 560bh EUDE OB56 du EODF OCOB ObOch. du : 9600 baud at 4miz EOE1 ODOO 000dh du EOE3 OE03 du 030eh EOES OFOO du 000fh else if mhz6 Oc103h du 0404h ; #1 clock du 8 4404h #16 clock du Dea05h ć. 560bh du 360ch : du : 9600 baud at 6mhz 010dh : 120ch ; 9600 baud at 6mhz 000dh des 03úeh 000fh és: endif endif

sccnb equ 0010 = :

S-scctab

5

CP/H RMAC ASSEM 1.1 0015 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

	;********	*************	*********
	1		*
()#/(\$ s-100) vectored inter	rupts (via cio port b) 🖷
	\$ inter	rupt vector tab	le e
	5		
	;++++++++++	***********	*******************************
	ş		
	vtable:		
EOE7 3DE8	du	vi7	•
E0E9 37E8	du	vió	
EOEB 31E8	du	vi5	
EDED 2BE8	du	vi4	
EOEF 25E8	du	vi3	
EOF1 1FEB	du	vi2	
EOF3 CSE7	du	Pberr\$sr	; parity is on vi-1
EOF5 19E8	du	vi0	
	1		
	i		
	;*********	*********	*****
	s syste	a configuration	info #
	100 C C C C C C C C C C C C C C C C C C	moved up to ff	
	1		
	;+++++++++		*******************
₹.	:		
	sys\$data:		
EOF7 OODF	da	monSstrt	S munitor start address
E0F9 0040	du	conf\$init	16 bit configuration vector
E0FB 20	đb	verSinfo	# monitor version @
EOFC 000000	db.	0,0,0	S SPare
	;	erere	1 preis
			*
	8		
		n pala berian	
		n pela sucia	

•

•

5

CP/H RHAC ASSEM 1.1 0016 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/83

		; 44 1		*******	**************************************
			besin	hish memory exe	ecution #
				HER BLEFF F LA	and a set of the set o
		; (++)		*******	*****
		;			hitting -
		init	t2:		
	EOFT 219FE0		lxi	h.map\$ram	: map out prom
	E102 CDDCDF		call	mapit	
		;	0536	070707	
	E105 21F7E0		Ixi	h.sys\$data	f move up sysinfo
	E108 1100FF		lxi	d.sysinfo	
	E10B 010800		lxi	6.8	
			ldir		
	E10E+EDB0				
		ï			
	E110 21E7E0		Ixi	h, vtable	: cio port b interrupt vectors service routines
	<i>v</i> .				: (i.e. s-100 vectored interrupts)
	E113 1110FF		lxi	d, ivtciob	: ram location port b iv table
	2)	;			
	E116 7A	1	DOV	and	5 im2 interrupts base page
			stai		into i resister
	E117+ED47				· · · · · · · · · · · · · · · · · · ·
	E119 32FBFF		sta	ui	; and into user ram resister map
		;			
	E11C 011000		lxi	6,16	: eight vectors
			Idir		; move then to ram
	E11F+EDBO		0.70.5		
	- -	;			
	E121 0E00		e vi	c.0	; rst\$ciob takes mask in res c
	E123 CDUCE9		call	rstsciob	; clear any interrupts from init
		;			
	E126 3EC3	<u>,</u>	evi	a, 0c3h	<pre>fix mmi vector</pre>
	E126 326600		sta	66h	
	E128 210FE8		lxi	h.naie	5 nmi entry
	E12E 226700		shld	67h	
		5			
	E131 3EB4		ovi	a,slvenb	; release slave reset line
	E133 D378		out	CIOC	
		;			
			in2		
	E135+ED5E				
	E L	;			
		5			
		÷		******	*********************
		2			ER TYPE AND SET ACCORDINGLY .
Э	•				***************************
		:	353573		
	E137 AF		ara	a	
	E138 3273E1		sta	cflas	; initialize controller flas to zero
	E138 DE53		in	sector	; check for VFW-III
1	E130 4F		BOV	Cià	save char in case it is
	E13E 3E55		evi	a.55h	; send test byte
	E140 D353		out	sector	
	E142 D853		2D	sector	
	as is port		411		

CP/H RNAC ASSEM 1.1 0017 SBC-300 VERSION OF MONITOR V2.0-VFH 9/30/83

E144 FE55	CP	Sector Contractor and	; see if ther match
E146+2008	jr	nz setsvf2	
E148 3EAA	BY	i a.Oaah	; send test byte
E146 353	6U		s benu test bite
E14C DB53	· in	5. (5.5.7.) S.	
EI4E FEAA	CP		; see if they match
ETAC LEVAN	setsvf2:	1 Visali	s bee at their match
	je uvizi	z i53	; yes- is VFN3 so restore char & continue
E150+2822		2 230	a 162 Th Alwo be leader circle a contained
E152 2124F1	lx	i h.home2	; reset imp table to VF-II entries
E155 2219DF	sh		I TESEL OUP LEDIE LO VI AL ENLITES
	ייג זג	AND	
E158 2133F1			
E15B 2228DF	sh		
E15E 214FF1	lx		
E161 222BDF	sh		
E164 2167F3	lx		
E167 222EDF	sh	ld 12+1	
E16A 2174F3	lx	i h,saver2	
E16D 2231DF	sh	ld s2+1	
E170 C380E1	ja	p rentry	5 entry warm boot point
E173 00	cflas:	db O	
E174 79	i is3: mo	v a.c	; restore char in vfu3
E175 D353	6U	21 T N C	
E177 3EFF	BY		; set cflas to non-zero
E179 3273E1	st		
EI/7 SC/SCI	1	e criss	
E17C 3E13	DV	i a.13h	: now do restore to clear controller
E17E D357	OU	t comand	; after its self test
	;		
		*****	•
	;		
	1 64	rm boot entry point	THE REAL PROPERTY OF THE PROPERTY OF THE REAL PROPE
			*
	19771777	******************	
	rentry:		
E100 21000E	reative.	i husesp	; init user sp save loc
E180 2100DF			; load user sp loc
E163 22E6FF	sh		; make .G default = exec0 entry
E186 2180E1	lx		i Bare .0 Gerauit - exect entri
E189 22FEFF	sh	489 - 198 - N	
E18C AF	X	75° (77)	a day with my be floor
E180 3200FF	st		; clear software by flag
E190 3250FF	st		t clear interrupt flag
E193 32FAFF	st		; set user interrupts - disabled
E196 325EFF	st	a parsloc	<pre>\$ clear parity known flag</pre>
E199 3C	in	r a	
E19A 32C6FF	st	a lons	s set long register print
	5		
E190 FB	ei		s enable interrupts immedately before
	;		: fall through to compand interpreter loop

here is a second to be

CP/H RHAC ASSEM 1.1 0018 SBC-300 VERSION OF MONITOR V2.0-VFH 9/30/63

		; ***********	****************	**************************************
		COBBAD	d re-entry point	
	<i>*</i>	2	o it that i voint	
		:	****	
		:		the second s
F	19E 3100FF	exec0:	lxi SP.BOSS	se1
1000	1A1 CDCEE9	call	crlf	
	1A4 DEZE	evi	c,'.'	
1.1	1A6 CDOCDF	call	COP	t write the character
1.000	1A9 CDC7E9	call	echo	collect the command
	IAC FEZE	CPI		v correct the comment
		jrz	exec0	
F	1AE+28EE		EALLY	
	1B0 C5	Push	b	
1.575	1B1 CDDSE9	call	space	
1.002	1B4 CDFEEA	call	scan	s can for the operands to the command
2553	1B7 C1	POP	b	s scall for the overallos to the country
	1BS 79	BOY	a,c	 Legit and provide the second se
	1B9 219EE1	Ixi	a,exec0	· L'HORAL AND COMPLETE
1.122	187 217EE1	Push	h	f push return address
E	IBC ED	Push	n	e push return address
E	100 0/41	i mada akt	aui (A(
E	1BD D641	condact:	sui 'A'	
		arc	invcad	
1.574	1BF+3851		171 161.1	
E.	ICI FEIA	CPI	'Z'-'A'+1	
		jrnc	invcmd	
	1C3+304D			
	1C5 21DEE1	Ixi	h, cmdvct	
1.73	108 87	add	a	
	109 85	add	1	
E	1CA 6F	DOV	I.a	
		jrnc	cod ac1	
	1CB+3001			
	1CD 24	inr	h	
	1CE 5E	cadac1:	BOV C.B	Period and a company design design of the second
	1CF 23	inx	h	
	1D0 56	BOV	6.8	
	1D1 D5	Push	d	<pre># push destination address</pre>
E	102 2A02FF	Ihid	epr2	" hlide set operands
		lded	epr1	
	1D5+ED5B			
E	1D7+DOFF			
		lxir	smad	f point in to spad
	109+FD21			
	1DB+COFF			
E	1DD C9	ret		t jump to it
		5		
		codvct:		
E	IDE 1AE236E275	i da	acad, bcad,	
E	1E6 EFE226E336		ecad, fcad,	scad, head
	1EE 68E39EE312		icad, icad, i	invcad, lcad
	IF6 BBE 412E2DE		acad, invcad,	ecad, ecad
	IFE 12E240E54L		invend, rend,	scad, tead
1.5	206 12E22EE766		invend, vend,	wond, xond

 \sim

- :

) 8

٠.

CP/H RHAC ASSEM 1.1 0019 SBC-300 VERSION OF MONITOR V2.0-VFW 9/30/63

E20E	9CE79FE7		du 🛛	vcad,	zcad
		;			
E212	OE3F	inva	ed:	evi	c,'?'
E214	CDOCDF		[[so	COE	
E217	C39EE1		JOP	exec0	
		;			

•

APPENDIX K SAMPLE I/O SUPPORT CODE

RESETTING VECTORED INTERRUPTS

reset clob data catcher(s) and port b interrupt state. 5 assumes interrupts have been disabled by caller i on entry res c must have mask for clob port. i i.e. to reset D6, c = 1011\$1111b 3 1 interrupts must be disabled through all code 57 that accesses cio internal registers. 87 5 ; 79h ; SBC-300 CIO port b data port 640 ciob ; SBC-300 CIO control port 7bh cioctl UP9 i cmd/status port b 09h csr\$b 690 ; reset ius, ip in cmd/status port rst\$csr\$b 690 0010\$0000b \$ rst\$ciob: ; first reset 1's catcher @ data port b ciob in ; according to flag passed in reg c С ana ciob ; O's clear out 3 a, csr\$b ; cmd/status for port b nvi ; register select cioctl out a,rst\$csr\$b ; clear ius & iP mvi f reset ip,ius cioctl out ignoring errors for now 5 ret ž

fit and the families the

MONITOR INITIALIZATION CODE

5

false equ O

```
true equ not false
;
                    false
sasi
             640
cntrs
             equ
                     true
cntr3
                     false
            e90
;
  I/O Port addresses S D Systems SBC-300 cpu
;
;
     ; chip bases
;
$
                     ; SBC-300 Parallel Data Port
             equ 70h
P$300Par
P$300cio
            egu 78h
                         ; Z8536 Counter/Timer & Parallel I/O
;
;
     ; Z8536 Counter/Timer & Parallel I/O Chip
2
                     P$300cio+0
P$cioc
             equ
                    p$300cio+1
P$ciob
             640
P$cioa
                    P$300cio+2
             690
P$cioctl
             e9u
                    p$300cio+3
:
-
;
             Off7eh ; space for interrupts in page ff
sp$sav equ
int$stk equ
           sp$sav
;
;
$
-
    SBC-300 cio init
$
cioinit:
;
                             set up z-80 i-reg
;
       nvi
             a, iv$page
       stai
;
                             set up im2 vectors in page.Offh
;
                           ; just move the table up there
       lxi
             h,i$sr
             d,i$sr$tab
       lxi
             b,i$sr$nb
       lxi
       ldir
5
              P$cioct1
                          ; force cio to state O
       in
;
                         ; send init info
       nvi
              c,p$cioct1
       nvi
              b, cionb
       lxi
              h,ciotab
       outir
;
```

```
K-2
```

ŧ im2 ei ret -data for sbc\$300 cio initialization ÷ ÷ ÷ Offh ; all im2 vectors are in page Offh iv\$page 1199 i\$sr\$tab OffOSh ; start of im2 vector table in page Offh 640 08h ; Off08 - Off0f reserved for cio cntr/timers sr\$cio\$ct 690 sr\$cio\$b 10h ; Off10 - Off1f reserved for cio port b 640 ; Off20 - Off2f reserved for cio port a 20h sr\$cio\$a 690 30h : Off30 - Off3f reserved for scc sr\$scc 690 5 : i\$sr: ; service routine addresses to move up cio cntr/timers require 4 addresses 3 sr\$ct3 ; service routine address sr\$cioct3 du sr\$ct2 % service routine address sr\$cioct2 dw sr\$ct1 ; service routine address sr\$cioct1 dw ct\$err ; service routine address sr\$ciocte du cio port b requires 8 addresses 1 sr\$vir7 ; service routine address sr\$ciob0 du sr\$ciob1 dω sr\$vir6 ; service routine address sr\$ciob2 dw sr\$vir5 ; service routine address sr\$vir4 ; service routine address sr\$ciob3 du sr\$vir3 ; service routine address sr\$ciob4 du sr\$ciob5 dω sr\$vir2 ; service routine address sr\$virl ; service routine address sr\$ciob6 du sr\$ciob7 du sr\$vir0 ; service routine address 0000\$0000b actv\$ints e90 -; any bit set will activate the VI e.s. the following would activate 5 the parity error line: 8 0100\$0000b ;perr\$enbl 690 ;actv\$ints Perr\$enb] 6911 3 cio port a requires 8 addresses ; cio port a interrupts not currently used ÷. scc requires 8 addresses . ; scc interrupts not currently used i\$sr\$nb \$-i\$sr ; number of bytes in table 691 3

```
5
二<del>쭕쭕뚢븧챃뢒탒똜쭕쭕쭕툹쭕뜛뚶쭕쭕쭕쭕</del>쑵
                                            5
       cio control byte table
                                            분
-
                                            4
5
27
            cio port a data
2
3
     if sasi
:
d$ems$a_equ
              0000$0000b
                          ; bit port, no pattern match
                         ;-ignored if bit port
d$phs$a equ
              0000$0000b
d$dpp$a equ
              1111$11116
                             ; sasi is negative logic
                             ; sel,bsy-out,i/o,req,c/d,ms9,bsy-in,rst
d$dd$a equ
              0011$1110b
d$sio$a equ
              0000$0000b
                             ; normal io bits
                                      2d thru 2f define ptrn msk
;
              0000$0000b
                             ;-ignored when no pattern match used
d$PP$a equ
d$pt$a equ
              0000$0000b
                             ; leave all masked off
d$pm$a equ
              0000$0000b
                             -
3
d$iv$a equ
                             ; 1sb of vector table
              sr$cio$a
d$dr$a equ
              0000$0000b
                             ; init port to all O's
1
       else
              ; not sasi
÷
                             ; bit port, no pattern match
d$pms$a_equ
              0000$0000b
                             ;-isnored if bit port
d$phs$a equ
              0000$0000b
                             ; invert strobe, ?, dev$rdy
d$dpp$a_equ
              1010$0100b
                             ; pa7-strobe, pa3-on$line, pa2-dev$rdy
d$dd$a equ
              0000$1100b
d$sio$a equ
              0000$0000b
                             ; normal io bits
                                      2d thru 2f define ptrn msk
;
                             ;-isnored when no pattern match used
d$PP$a equ
              0000$0000b
                             ; leave all masked off
d$pt$a equ
              0000$0000b
d$pm$a equ
              0000$0000b
                             8
;
d$iv$a equ
                             ; isb of vector table
              sr$cio$a
d$dr$a equ
              0000$0000b
                             ; set strobe at data port
2
   endif ; not sasi
2
-
              cio port b data
              0000$0110b
                             ; bit port, or-pev
d$pms$b_equ
              0000$0000b
d$phs$b equ
                             5
d$dpp$b equ
              0000$0000b
                             ; non inverting
d$dd$b equ
              1111$1111b
                             ; all inputs
d$sio$b equ
              1111$1111b
                             ; all 1's catchers
                                      2d thru 2f define etrn msk
:
                             ; set for interrupt on any
d$pp$b equ
              1111$1111b
d$pt$b equ
              0000$0000b
                             ; bit enabled by mask in 2f
d$pm$b equ
              actv$ints
                             ; whichever bits are set are enabled
```

K-4

```
-
d$iv$b equ sr$cio$b ; lsb of vector table
1
            cio cntr/timer data
÷
5
            1000$0011b
                        ; continuous, no external pins, no dcs
d$PMs$3 equ
d$Pm5$1 equ
            1000$0000b
                       ; continuous, no external pins, pulse output
d$pms$2 equ
            1000$0011b
                        ; continuous, no external pins, no dos
d$tcm$3 equ
            244
                       ; = 62500; = 1/32 second
d$tc1$3 equ
            65
d$tcm$1 equ
            244
                     ; = 62500; = 1/32 second
            65
d$tcl$1 equ
d$tcm$2 equ
            0
d$tc1$2 equ
                       ; = 32; for 1 second
            32
;
                      ; note that cio chip provides bits d2,d1
d$iv$ct equ
            sr$cio$ct
4
            cio c/s resister commands
-
8
                        f clear interrupt service flags (ip, ius)
d$cisfs equ
            0010$0000b
            1100$0000b
                        ; set ie
d$sei equ
                        ; clear ie
d$cei equ
            1110$0000b
d$trgr equ
            0000$0110b
                        trisser a c/t without sating
1
            besin ciotab
-
ciotab:
                         ; micr : disable mie
     db
            00h, 0000$0000b
            01h, 0001$0000b
                         ; mccr : must leave port c enabled
      db
1
-
            port a first parallel port status in port a
3
-
            20h, d$pms$a ; pattern mode specification
      db
            21h, d$phs$a ; pattern handhake specification
      db
5
      db
            22h, d$dpp$a ; data path polarity
                      ; data direction
      db
            23h, d$dd$a
            24h, d$sio$a ; special io
      db
-
-
      db
            25h, d$pp$a
                       ; port polarity
*
      db
            26h, d$pt$a ; port transition
            27h, d$pm$a
                        ; port mask
ę,
      db
*
      db
            02h, d$iv$a ; interrupt vector
      db
            OSh, d$cei ; command status
;
```

5			
1		next, port b	init'd to handle vector'd interrupts
;			
	db	28h, d\$pms\$b	; pattern mode specification
5	db	29h, d\$phs\$b	; pattern handhake specification
	db	2ah, d\$dpp\$b	; data path polarity
	db	2bh, d\$dd\$b	; data direction
	db	2ch, d\$sio\$b	; special io
;			
	db	2dh, d\$pp\$b	; port polarity
	db	2eh, d\$pt\$b	; port transition
	db	2fh, d\$pm\$b	; port mask
;			
	db	O3h, d\$iv\$b	; interrupt vector
	db	09h, d\$sei	; command status
;			
\$			
;		finally, c/t's	; use either 1&2 linked, or 3 alone
;			
	db	1ch, d\$Pms\$1	; c/t-1 mode specification resister
	db	1dh, d\$pms\$2	<pre>; c/t-2 mode specification resister</pre>
	db	1eh, d\$pms\$3	; c/t-3 mode specification register
n 7			
	db	16h, d\$tcm\$1	; c/t-1 time constant register msb
	db	17h, d\$tc1\$1	; c/t-1 time constant register lsb
	db	18h, d\$tcm\$2	<pre>c/t-2 time constant register msb</pre>
	db	19h, d\$tc1\$2	<pre>; c/t-2 time constant register lsb</pre>
	db	1ah, d\$tcm\$3	; c/t-3 time constant register msb
	db	1bh, d\$tc1\$3	; c/t-3 time constant register lsb
5			
	db	O4h, d\$iv\$ct	; c/t interrupt vector register
5			
	db	Oah, d\$cei	; c/t-1 command/status resister
	db	Oah, d\$cisfs	
9 7			and the second
	if not	cntrs	; disable interrupts on all c/t's
;			
	db	Obh, d\$cei	; c/t-2 command/status resister
	db	Obh, d\$cisfs	
	db	Och, d\$cei	; c/t-3 command/status register
		Och, d\$cisfs	
;		ten, arassis	
	else	; cntrs	enable interrupts on either c/t-2 of c/t-3
;	croc	r citers	
5)	if cnt	т <u>3</u>	; enable interrupts on c/t-3
;	11 5.00	.1.5	
<u></u>	db	Obh, d\$cei	; c/t-2 command/status register
	db	Obh, d\$cisfs	, sit a company states restated
	db	Och, d\$sei	; c/t-3 command/status register
;	00	VCH7 0#JT1	- Cress Command/Status (ESISTE)
	else	; not cntr3	enable interrupts on c/t-2
;	C13C	7 nyt entro	cheere anterrores on cre L
\$2	db	Obh, d\$sei	; c/t-2 command/status resister
	db	Och, d\$cei	; c/t-2 command/status register ; c/t-3 command/status register
		107 00 00 0 10 00 00 00 00	, CIL O COMMANDISTATUS IESISTET
	db	Och, d\$cisfs	

```
;
       endif ; not cntr3
5
        endif ; cntrs
;
;
       db
               Olh: 1111$0111b ; master configuration control
;
;
                            ; c/t-2 command/status register
        db
               Obh, d$trar
        db
               Oah, d$trsr ; c/t-1 command/status resister
        db
               Och, d$trer
                            ; c/t-3 command/status register
5
3
        db
               OOh, 1000$1100b ; master interrupt control
;
       690
               $-ciotab
cionb
*
;
;
;
ï
3
       routine to service counter/timer err and transfer control
;
         to routine of highest priority counter/timer needing
÷
         service
;
1
csr$ct3
               690
                       0ch
                                     ; command/status resister; c/t-3
err$msk
               694
                       0001$0000b
                                     ; ERR bit in csr's
*
ct$err:
                       ; z80 has disabled interrupts
                            ; save state
       SSPO
               sp$sav
       lxi
               sp;int$stk
       Push
               PSW
       Push
               h
       Push
               h
;
       lxi
               h,i$sr$tab - 2 ; c/t isr's are 1st in table
       mvi
               c, p$cioct]
               b,csr$ct3 + 1 ; c/t-3 is highest priority
       avi
ct$err0:
                              ; 1 word per address .
       inx
               ħ
       inx
               h
       dcr
                              i csr's are sequential
               b
       outp
                               ; read the csr
               b
       INP
               a
                              ; check ERR bit
       ani
               err$msk
       jrz
               ct$err0
                              ; if not set then so check next c/t
```

;			
1	mov	C 1 M	; else set up address of service routine
	inx	h	
	mov	b.m	
	lhld	sp\$sav	; put it on user's stack (no choice)
	dcx	h	
	mov	m,b	
	dcx	h	
	mov	m, c	
	shld	sp\$sav	; update user's stack ptr
;			
	POP	b	; restore state
	POP	h	
	POP	P5W	
	lspd	sp\$sav	
	ret		<pre>s and jump to service routine</pre>
;			with interrupts still disabled
;			

end

1

APPENDIX M DISCLAIMER

SDSystems, INC. makes no representations or warranties with respect to the contents hereof and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose. Further, SDSystems, INC. reserves the right to revise this publication and to make changes from time to time in the content hereof without obligation of SDSystems, INC. to notify any person of such revision or changes.

APPENDIX N LIMITED WARRANTY

All SDSystems printed circuit board assemblies are warranted for a period of one (1) year from date of invoice to be free from defects of material and workmanship.

Should an SDSystems board fail to perform to specifications, obtain a Return Material Authorization (RMA) number from your distributor or from SDSystems. Include this number in all correspondence and with the returned product. Ship the item prepaid to SDSystems and it will, at our option, be repaired or replaced free of charge provided the unit is received during the warranty period.

In order to validate this warranty, the enclosed warranty card must be returned to SDSystems. If no warranty card is on file at the time of product return, dated proof of purchase will be required.

This warranty is invalid if product has been misused or improperly modified. Modifications documented in the SDSystems unit publications may be performed without invalidating the warranty. All other modifications will invalidate the warranty. Warranty is limited to replacement of defective parts and no responsibility is assumed for damage to other equipment.

SDSYSTEMS MAKES NO WARRANTIES, GUARANTEES, OR REPRESENTATIONS, EXPRESSED OR IMPLIED, WITH RESPECT TO THE PRODUCTS COVERED HEREBY, EXCEPT AS EXPRESSED HEREIN, AND BUYER EXPRESSLY WAIVES ANY OTHER WARRANTIES, GUARANTEES, OR REPRESENTATIONS INCLUDING, BUT NOT LIMITED TO, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR USE. SDSYSTEMS NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR SELLER ANY OTHER LIABILITIES IN CONNECTION WITH THE SALE OF THE PRODUCTS. IN NO EVENT WILL SDSYSTEMS BE LIABLE FOR ANY SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

N-2

APPENDIX O PARTS LIST FOR SBC-300

QTY REQD	DESCRIPTION	PART/SUB NUMBER	DESIGNATION
	SBC-300	4 MHZ	
0 1 1 1 4	SBC-300 BOARD SCHEMATIC SBC-300 PC BOARD IC, 7406 IC, 7438 IC, 74LS00	0300723 7000066 7010007 7010030 7010160	
5	IC, 74LS02	7010162	U30 U4, U26, U27,
2	IC, 74LS04	7010164	U51, U68 U32, U37
2 1 5	IC, 74LS08 IC, 74LS10 IC, 74LS14	7010166 7010168 7010172	U17
1 2 7	IC, 74LS20 IC, 74LS32 IC, 74LS74	7010174 7010181 7010195	U56 U18, U20 U1, U2, U7, U9, U33, U43,
1 1 2 1 3 2 5	IC, 74LS93 IC, 74LS112 IC, 74LS139 IC, 74LS158 IC, 74LS163 IC, 74LS164 IC, 74LS240 IC, 74LS244 IC, 74LS245	7010205 7010210 7010220 7010229 7010233 7010234 7010260 7010264 7010265	U74 U42 U15 U57 U64, U72 U25 U67 U13, U21, U35 U55, U71 U61, U70, U76-
2 1 2 1 1 2	IC, 74LS373 IC, 74LS374	7010279 7010303 7010304 7010305	U39 U36 U29, U40 U38 U10, U11 U3, U12 U69 U47
9 1 1 1	IC, PIN 1 REFR 200 NS DRAM DELAY LINE, 5 TAP, 200 NS PAL 16L8 - DECODE PROG. PAL 16L8 SLAVE PROG.		U23, U31, U41, U49, U50, U58, U66, U73, U79 U22 U28

QTY		PART/SUB	
REQD	DESCRIPTION	NUMBER	DESIGNATION
S STREET, STREET, STR			
	SBC-300 4 MHZ	(Continued)	
	nutifulli, man hijitinga -		
1	SIP, 4.7K OHM	7010434	RN4
1	SIP, 1K OHM, 6 PIN 5 RES	7010556	
2	SIP, 220/330, 10 PIN		RN1, RN2
1	RES 22 OHM 1/4W 5% CC	7020033	
i	RES 100 OHM 1/4W 5% CC	7020049	
1	RES 220 OHM 1/4W 5% CC	7020049	
2 5			
5	RES 1K OHM 1/4W 5% CC	7020073	
-		7000000	R16
3	RES 4.7K OHM 1/4W 5%	7020089	R3, R13, R15
2	RES 10K OHM 1/4W 5% CC	7020097	
2	RES 150 OHM 1/2W 5% CC	7020171	
3	10 PIN 1K RES NTWK	7020223	RN5-RN7
2 3 4	CAP 10MF 16V TANT	7030009	C1, C2, C6, C9
2	CAP 150PF	7030042	C15, C39
2 1	CAP 300PF 20% 50V .2	7030044	C14
33	CAP .1UF 50V	7030045	
			C10, C11, C16-
			C38, C40-C42
1	CAP .01MF 16V CRAMIC	7030046	C13
î	CAP 33PF 50V	7030047	
1		7040002	CR3
1 2	DIODE, 1N4001	7040002	CRJ CDJ
	ZENER DIODE 1N4742A		CR1, CR2
1	TRANS PNP 2N3906	7040006	Q1
1	8 POSITION DIP SWITCH	7050002	
2 1	SOCKET 16 PIN 300 ML	7060003	J5, J6
1	SOCKET 28 PIN GOLD PL	7060022	
1	CRYSTAL, 8 MHZ	7080007	Yl
2 2	6-32 X 3/8 PPH SCREW	7130006	
2	6-32 NUT	7130007	
2	LOCKWASHER #6	7130009	
1	78H05C +5V 5 AMP VLT RGLR	7160012	VRl
1	2X25 CONN, STRT HDR	7090197	J4
2	CONN, 26 PIN STRT HDR	7090196	J2, J3
2	HDR ASSY	0100736	J5, J6
2 2 1	HEATSINK TMH 6103-B	7130004	00,00
	65474 BERG PV JUMPER	7170004	
7	BERG 1X2 STR .230 PIN TIN	7170018	W4, W5, W9,
1	BERG IAZ SIR .250 PIN IIN	1110018	
			W11, W12,
-	DEDG 102 GED 020 DIN MIN	7170001	W15-1, W21
5	BERG 1X3 STR .230 PIN TIN	7170021	W1, W3, W6,
			W10, W19
2	BERG 2X5	7170105	W13, W17
2	HDR ASSY	0100736	J5, J6
1	BERG STIK ST 2X9 TIN PL	7170097	Wl4
1	SIP, 1K OHM, 8 PIN RES	7010413	RN8
1	SOCKET, 40 PIN GOLD PL	7060025	XU48
1	BERG 2X4	7170020	W16
1	BERG 2X15	7170106	W15
1 2	PCB EJECTORS	7130228	
õ	SBC-300 TEST PROCEDURE ASSY		
U	PPC 200 TEPT TROOPPORT WPPT	0000120	

()

QTY REQD	DESCRIPTION	PART/SUB NUMBER	DESIGNATION
	SBC-300	6 MHZ	
0 1 1 1 4	SBC-300 BOARD SCHEMATIC SBC-300 PC BOARD IC, 7406 IC, 7438 IC, 74LS00	0300723 7000066 7010007 7010030 7010160	U5 U8, U16, U24,
5	IC, 74LS02	7010162	U30 U4, U26, U27,
2 2 1 5	IC, 74LS04 IC, 74LS08 IC, 74LS10 IC, 74LS14	7010164 7010166 7010168 7010172	U34, U75 U17 U6, U19, U52,
1 2 7	IC, 74LS20 IC, 74LS32 IC, 74LS74	7010174 7010181 7010195	U9, U33, U43,
1 1 2 1 3 2 5	IC, 74LS92 IC, 74LS112 IC, 74LS139 IC, 74LS158 IC, 74LS163 IC, 74LS164 IC, 74LS240 IC, 74LS244 IC, 74LS245	7010233 7010234 7010260	U15 U57 U64, U72 U25 U67 U13, U21, U35 U55, U71 U61, U70, U76-
1 2 1 2 1 1 2	IC, 74LS280 IC, 74LS368 IC, 74LS373 IC, 74LS374 IC, 75188 OR MC1488 IC, 75189 OR MC1489 IC, 74LS682 8531A 6 MHZ ASCC	7010279 7010303 7010304 7010305 7010332 7010333 7010518 7010520	U36 U29, U40 U38 U10, U11 U3, U12
2 3 1 9	74LS125 74LS189 28400B- 6 MHZ CPU (280B) 8536A 6 MHZ CIO 150 NS DRAM	- 7010526	U14, U44 U54, U62, U63 U48 U46 U23, U31, U41, U49, U50, U58,
1 1 1 1	150 NS DELAY LINE PAL 16L8 - DECODE PROG. PAL 16L8 SLAVE PROG. SIP, 4.7K OHM	7010535 7250006 7250007 7010434	U66, U73, U79 U22 U28 U59

QTY REQD DESCRIPTION

PART/SUB NUMBER DESIGNATION

SBC-300 6 MHZ (Continued)

2	SIP, 1K OHM 6 PIN 5 RES SIP, 220/330, 10 PIN RES 22 OHM 1/4W 5% CC RES 100 OHM 1/4W 5% CC	7020033	RN1, RN2 R8
2 5	RES 220 OHM 1/4W 5% CC RES 1K OHM 1/4W 5% CC	7020057 7020073	
3 2 3 4 2 1 33	RES 4.7K OHM 1/4W 5% RES 10K OHM 1/4W 5% CC RES 150 OHM 1/2W 5% CC 10 PIN 1K RES NTWK CAP 10MF 16V TANT CAP 150PF CAP 300PF 20% 50V .2 CAP .1UF 50V	7020171 7020223 7030009 7030042 7030044	R3, R13, R15 R10, R11 R1, R2 RN5-RN7 C1, C2, C6, C9 C15, C39 C14 C3-C5, C7, C8, C10, C11, C16-
1 2 2 1 1	ZENER DIODE 1N4742A TRANS PNP 2N3906 8 POSITION DIP SWITCH SOCKET 16 PIN 300 ML SOCKET 28 PIN GOLD PL XTAL, 12 MHZ	7030046 7030047 7040002 7040004 7040006 7050002 7060003 7060022 7080019 7130006 7130007 7130009 7160012 7130004 7170004	Cl2 CR3 CR1, CR2 Ql SW1 J5, J6 XU65 Yl
1 2 2 1	SIP, 1K OHM 8 PIN RES 2X25 CONN, STRT HDR	7010413 7090197 7090196 0100736 7060025 7170018	J4 J2, J3 J5, J6 XU48 W4, W5, W9, W11, W12,
5	BERG 1X3 STR .230 PIN TIN	7170021	W15-1, W21 W1, W3, W6, W10, W19
1 2 1 1 2 0	BERG STIK ST 2X9 TIN PL BERG 2X5 BERG 2X4 BERG 2X15 PCB EJECTORS SBC-300 TEST PROCEDURE ASSY	7170097 7170105 7170020 7170106 7130228 0900723	W14 W13, W17

REPLACEMENT CHIPS (Or Equivalent)

	RAMs 150 ns	200 ns	ROMs	Delay 150 ns	Lines 200 ns
		200 115		100 110	200 110
	(P)				
MITSUBISHI	M5K4164S-15	-20	2716	DDU-4-5150	DDU-4-5200
FUJITSU	MB8265-15	-20	2732		
MOSTEK	MK4164-15	-20	2764		
MOTOROLA	MCM6664-15	-20			

APPENDIX P PARTS PLACEMENT DIAGRAM

JUMPER NUMBERING NOTATION

Throughout the manual, jumper locations are referenced by 'W' number and pin number. The following number convention is adhered to for all jumpers on the board.

For horizontal jumpers that are single row (1x3, 1x4, etc.), pins are numbered consecutively from left to right.

For vertical jumpers that are single row (1x3, 1x4, etc.), pins are numbered consecutively from top to bottom.

For horizontal jumpers that are dual row (2x3, 2x4, etc.), pins are numbered consecutively from bottom left to right, continuing on the top right to left.

EXAMPLE: W7(1), W7(6), and W7(8) are to be jumpered.

	16	15	14	13	12	11	10	9
						-		-
W7	0	0	0	0	0	0	0	0
VV /	0	0	0	0	0	0	0	0
								Anne anne Miler
	l	2	3	4	5	6	7	8

For vertical jumpers that are dual row (2x3, 2x4, etc.), pins are numbered consecutively from left top to bottom, continuing on the right bottom to top.

For horizontal jumpers that are triple row (3x3, 3x4, etc.), pins are numbered consecutively from left bottom to top, continuing from bottom to top for each column from left to right.

EXAMPLE: W3(4-5) is to be jumpered.

			6	9		
	3	0	0	0	ò	12
W3	2	0	0	0	0	11
	1	0	0	0	0	10
			Anny sizes from			

APPENDIX L JUMPER CONNECTION QUICK REFERENCE TABLES

STANDARD JUMPER CONNECTIONS

(Example: "1-2" means jumper pins 1 and 2 together)

	Master	5	Slave	
Wl	OUT		OUT	
W3	1-2		1-2	
W4	OUT		IN	
W5	IN		OUT	
Wб	1-2		1-2	
W9	IN		OUT	
W10	1-2		1-2	
W11	IN		OUT	
W12	IN		IN	
W13	POSITION	1	POSITION	1
W14	POSITION	5	POSITION	5
W15-W18	ALL IN		CUT ALL	
W19	OUT		2-3	
W21	IN		OUT	

JUMPER DEFINITIONS


NOTE: "(etch)" means an etch jumper. If a change is desired, the user must cut the etch and insert a jumper.

Jumper	Purpose		Setup
Wl	SCC Port A Baud CLK	1-2	External (modem) clock
	select	2-3	2 mHz system clock
W2	RAM size select		64K DRAM
(etch)		2-3	Future expansion
W3	Wait state generator	1-2	Memory cycle
			OP CODE fetch only (M1)
W4	Master/Slave select		Slave
		OUT	Master
W5	Bus refresh signal pin 66	IN	Outputs RFSH* signal
	(for SD EXPANDORAM II & III)		No connection to bus
Wб	pSTVAL* source select	1-2	IEEE-696 timing
			Øl clock
W7	Bus clock select		Future expansion
(etch)			4/6 mHz board
W8	CPU clock select		4/6 mHz board
(etch)			Future expansion
W9	WAIT* for EXPANDORAM III		EXPANDORAM III
	compat.	OUT	All others
W1.0	PROM select	1-2	64K and smaller
			128K

JUMPER DEFINITIONS--Continued


Jumper	Purpose		Setup
Wll	MWRT select	IN OUT	SBC-300 creates MWRT MWRT created elsewhere
W12	BRFSH jumper	IN	
		OUT	Ignore refresh
W13	TMA wait generator Jumper		Wait states inserted
W14	Interrupt select 1 2 3 4 5 6 7 8 9		PWR FAIL to NMI Attention to VI6 Attention to VI7 Parity error to VI1 Attention to VI2 ERROR* to VI0 Attention to VI4 Attention to VI5 Attention to VI3
W15-W18	Bus pull up resistors for master; remove for slave		
Wl9	SLVCLR select		Manual reset for slave SLVCLR from bus
W21	RDY/XRDY enable	IN OUT	RDY/XRDY gated to WAIT* RDY/XRDY not used

L-2




₽-3


APPENDIX Q SCHEMATIC



Q-3




2-4



11)

Q-5



0-0